



**Guerreiro, José and Reid, Andrew and Jackson, Joseph C. and Windmill, James F.C. (2017) Bio-inspired active amplification in a MEMS microphone using feedback computation. In: IEEE Biomedical Circuits and Systems Conference 2017. IEEE, Piscataway, NJ. (In Press) ,**

This version is available at <https://strathprints.strath.ac.uk/62300/>

**Strathprints** is designed to allow users to access the research output of the University of Strathclyde. Unless otherwise explicitly stated on the manuscript, Copyright © and Moral Rights for the papers on this site are retained by the individual authors and/or other copyright owners. Please check the manuscript for details of any other licences that may have been applied. You may not engage in further distribution of the material for any profitmaking activities or any commercial gain. You may freely distribute both the url (<https://strathprints.strath.ac.uk/>) and the content of this paper for research or private study, educational, or not-for-profit purposes without prior permission or charge.

Any correspondence concerning this service should be sent to the Strathprints administrator: [strathprints@strath.ac.uk](mailto:strathprints@strath.ac.uk)

The Strathprints institutional repository (<https://strathprints.strath.ac.uk>) is a digital archive of University of Strathclyde research outputs. It has been developed to disseminate open access research outputs, expose data about those outputs, and enable the management and persistent access to Strathclyde's intellectual output.

# Bio-inspired Active Amplification in a MEMS Microphone using Feedback Computation

José Guerreiro, Andrew Reid, Joseph C. Jackson and James F.C. Windmill

Centre for Ultrasonic Engineering  
University of Strathclyde  
Glasgow, Scotland  
jose.guerreiro@strath.ac.uk

**Abstract** — Auditory signal processing relies on feedback mechanisms between mechanical and electrical systems that work together to enhance acoustic conditioning. In this paper a nonlinear amplification mechanism in the mosquito’s auditory system is exploited as a model of inspiration. An acoustic system that provides active amplification of sound was developed using feedback computation integrated with a MEMS microphone to implement the concept. Experimental results generated by a purpose-built embedded system show signal amplification and hysteresis which replicate the response shown by the biological mosquito’s hearing system as a function of input sound intensity.

**Keywords**—*bio-inspired acoustic sensor system; active hearing; signal amplification; feedback computation; real-time embedded signal processing; prototyping.*

## I. INTRODUCTION

Hearing capabilities are often achieved as a result of active processes that have evolved to be adaptable to cope with different environmental demands. Several auditory features have been identified which greatly enhance the ear’s responsiveness in many species, humans included [1]. Amplification and tuning are two of the most important functions of a hearing organ, and therefore hearing thresholds can be at levels below the thermal vibrations of the receptor organ [2]. Considering the example of the vertebrate’s inner ear, amplification is achieved due to somatic electro-motile outer hair cells acting over the basilar membrane in a sort of positive feedback mechanism pumping in additional energy that adds to the vibrational patterns inside the cochlea, providing up to 40-60dB of gain. Moreover, hearing is more sensitive to weak sounds and less responsive as signals become louder - a phenomenon called “compressive nonlinearity” [3]. This adaptive mechanism significantly increases the dynamic range achieved by a healthy hearing system; up to 120dB (refer to [4] for further background knowledge about auditory sensory processing). Active hearing has also been a topic of study within other species such as insects, likewise supporting the concept that nonlinear amplification may have its origin from active cell motion inside the hearing organ [5][6]. From the engineering point of view, this sophisticated method of signal amplification and inherent tuning can provide inspiration regarding the development of adaptable sensors and systems. Designing acoustic sensors and systems that can adapt dynamically to cope with different signal demands has already been the subject of other bio-inspired studies which feature frequency agility

exploited at the transducer level [7]. This paper aims to extend the topic further by presenting an unconventional signal-amplifier concept with a MEMS microphone using a feedback mechanism that can provide amplification of acoustic signals at the transducer level. This faithfully mimics a nonlinear response seen in the mosquito’s hearing system.




Fig. 1—Nonlinear response of the mosquito’s hearing. (A) Male antenna, highlighting the plumose flagella (fl) and the pedicel (pd) – scale bar 1 mm. (B) Envelop of the single-tone sound stimuli used to test nonlinearities in the antenna’s response - increasing (red) and decreasing (black) intensity. (C) Antennal response showing amplification and hysteresis.  $\Delta E$  is the rational energy of oscillation between the hysteretically amplified and the initial nonamplified response. Redrawn and adapted from [6].

## II. BIOLOGICAL SYSTEM OF INSPIRATION

### A. Mosquito’s Auditory System

Mosquitoes present one of the most complex hearing systems found in insects. These antenna-like ears can detect sound through induced movement of the antennae, called a plumose flagella – a hair shaft which works as a mechanical

structure for sound sensing, see Fig. 1a. At the antenna base sits the pedicel in which a chordotonal organ called Johnston’s organ contains up to 16,000 mechanoreceptor cells (scolopidia). These cells have the role of transducing sound induced mechanical energy into electrical signals which leads to consequent neuronal responses. Mosquitoes use their auditory receptors commonly for mating purposes. Males can detect a flying female that generates sound particle displacements of 3.5nm at a distance of 10cm [8], within the range of 350-450Hz. This ability to sense such weak and fast transient signals relies on active mechanisms with nonlinear responses that quickly amplify and tune to the signal preferentially generated from a female’s beating wings.

### III. ACTIVE AMPLIFIER CONCEPT

An initial elementary modelling of a type of acoustic receiver is to consider it as a passive oscillator. From the physical point of view, it can be approximated to a driven damped harmonic oscillator – a 2<sup>nd</sup> order system which in Laplace form can faithfully be expressed by (1). Its resonant frequency is defined by the ratio between stiffness and mass ( $\omega_0 = \sqrt{k/m}$ ) and quality factor expressed by the ratio between resonant frequency and damping ( $Q = \omega_0/\gamma$ ), where  $k$  represents the spring factor or stiffness and  $m$  is the mass of the mechanical structure.

$$H(s) = \frac{s\omega_0/Q}{s^2 + s\omega_0/Q + \omega_0^2} \quad (1)$$

A passive sensor of this type is linear with bandwidth ( $\Delta\omega = \omega_0/Q$ ) expressed by the ratio between its resonance frequency and Q factor. On the one hand, a sensor with low-Q can achieve fast temporal resolution with the cost of a poor frequency selectivity. On the other hand, a high-Q system has a slower temporal transient responsiveness with the benefit of a higher frequency selectivity, as illustrated in Fig. 2. That sets the trade-off within a passive acoustic sensor system and its design requirements.




Fig. 2 – A 2<sup>nd</sup> order system as the basic model for a passive acoustic sensor. Transient time response and frequency selectivity can be adapted by manipulating the Q factor of the system.

Importantly, for a male mosquito to sense and pursue a female successfully, its ears need to transit from a fast transient time sensing mode to a frequency-selective form of operation. That capability cannot be achieved only by a passive sensor itself. A feedback mechanism of synchronized neurons pumping additional energy to the passive mechanical system (antenna) plays the role of dynamically adapting the Q factor of the overall

system (antenna and electro-motile neurons) when required [6]. Inspired by that unconventional mechanism of signal conditioning, an engineered system using feedback computation was developed to manipulate the response of a front-end acoustic transducer (MEMS microphone), as illustrated in Fig. 3.




Fig. 3 – Diagram overview of the feedback control system that can be used to achieve Q control and active amplification, inspired by the mosquito’s hearing system. “Active Amplifier Sensor” represents the front-end acoustic transducer (i.e. MEMS microphone); “Spike Generator” is the feedback pathway of signal computation used to pump additional energy to the front-end transducer.

### IV. EMBEDDED SYSTEM SETUP

The concept of an acoustic system with adaptive Q factor that enables active amplification is engineered and an electromechanical setup is developed and presented as follows. The front-end transducer is a MEMS microphone fabricated on single crystal Silicon-On-Insulator (SOI) using MEMSCAP services (SOIMUMPs®). The device comprises an 800μm radius diaphragm mounted on 6 serpentine spring arms. The membrane itself is fringed by 176 (6μm wide) capacitive combs, interdigitated with a stator bank of combs on the surrounding die at 6μm intervals, as shown in Fig. 4a. The “Spike Generator” is an embedded system computing an algorithm that generates phase-lock pulses to be entrained with the input sound signal inducing mechanical vibrations over the microphone’s diaphragm (Fig. 4b).




Fig. 4 – (A) SEM top view of the MEMS microphone. (B) Spike Generator simplified based on integrate-and-fire computation [9]; where  $T$  represents the integrator constant,  $\tau$  is the delay time to reset the integrator and  $V_{th}$  is the comparator threshold (positive value).

In order to implement a complete closed-loop system it was necessary to design an experimental setup that could provide results in real-time. The approach is based on our previous embedded system design presented in [7], with the schematic illustrated in Fig. 5. It integrates an optical readout of displacements induced by sound onto the microphone’s diaphragm using a single-point laser vibrometer device






Fig. 8 – Time domain response of the purpose-built active amplifier system. (A) Single-tone acoustic stimuli at 3.3kHz (blue); overall response of the system (red) with phase-locked spike-type signals (black). (B) Amplification and hysteresis of the system. The rational energy  $\Delta E$ , represents the maximum amount of additional energy injected to the front-end sensor due to feedback computation using spike-type pulses (spike\_width=20 $\mu$ s @ +3V), providing an additional energy of about 166% to the overall system response. Recall to Fig. 1c for comparison with the mosquito’s nonlinear hearing response.

It should be highlighted that the entrainment between both systems (MEMS and Spike Generator) is gradual which means that at the transitory states, the spikes may not be perfectly phase-locked with the input stimuli – from that an uncontrolled behaviour of the overall system can originate. Additionally, the width, amplitude and polarity of the spikes can influence the system’s stability. It also means that if the amount of additional energy injected by the feedback computation is greater than the amount of energy which can be dissipated by the front-end sensor an uncontrolled oscillatory response of the overall system can occur – behaviour that can be expressed by nonlinear active systems [10]. An additional control mechanism would ensure an improved command of the system’s stability. It should also be noted that the front-end transducer consists of a MEMS microphone in its designed form, which is placed in a positive feedback loop with an internal system’s generator of spike-type signals. These are short and positive square-shaped pulses (with duty-cycle smaller than  $T/2$ , where  $T$  is the period of the input signal), entrained with the input stimuli of interest. Harmonic noise that could appear at the system’s output introduced by the spiking entrainment is dependent on the natural selectivity of the front-end transducer. It means that the natural frequency response of the MEMS microphone has the role of filtering out the harmonic noise resulting from the active processes within the system.

## VI. CONCLUSIONS

This paper presents a novel mechanism for sound amplification by exploiting feedback computation at the sensor level. Experimental results given by a purpose-built embedded system show dynamic adaptation of a MEMS microphone and

that its Q factor can be manipulated. The overall system response shows amplification with hysteretic behaviour as similarly reported from the biological system of inspiration. This unconventional transducer concept has the potential to be applied in novel designs of sensors and systems that require dynamic adaptations in a real-time scenario. Future investigations based on the work presented in this paper might include further characterizations of the overall system response and stability while varying different parameters in the feedback loop such as, averaging time, threshold of firing, spike shape, width, amplitude and polarity. Additional study should include simulation with a theoretical model of the overall system, which can be used to better characterize the concept and understand its applicability within acoustics. Work to compare and contrast this concept with standard positive feedback amplification techniques and other techniques may also be of great interest, for example where the theory of Q control has already been studied at the circuit and system levels, such as in active analog filters [11] and atomic force microscopy [12]. It would also be valuable to investigate if the nonlinear response given by this system can be applied in a similar manner to other work that reported similar hysteretic behaviour used in speech processing [13].

## ACKNOWLEDGMENT

The authors would like to thank the staff and researchers of the Centre for Ultrasonic Engineering at University of Strathclyde for all the support throughout this research work.

## REFERENCES

- [1] A. J. Hudspeth. “Making an Effort to Listen: Mechanical Amplification in the Ear”. *Neuron*, 59(4): 530-545, 2008.
- [2] P. Martin and A.J. Hudspeth. “Compressive nonlinearity in the hair bundle’s active response to mechanical stimulation”. *PNAS*, 98(25): 14386-14391, 2001.
- [3] K. Dierkes, B. Lindner and F. Julicher. “Enhancement of sensitivity gain and frequency tuning by coupling of active hair bundles”. *PNAS*, 105(48): 18669-18674, 2008.
- [4] Schnupp, J., Nelken, I. and King, A., “Auditory Neuroscience: Making Sense of Sound”. The MIT Press, 2012.
- [5] M. C. Göpfert, et al., “Power gain exhibited by motile mechanosensory neurons in *Drosophila* ears”. *PNAS*, 102(2): 325-330, 2005.
- [6] Joseph C. Jackson, James F. C. Windmill, Victoria G. Pook and Daniel Robert, “Synchrony through twice-frequency forcing for sensitive and selective auditory processing”. *PNAS*, 106(25): 10177-10182, 2009.
- [7] José Guerreiro, Joseph C. Jackson and James F.C. Windmill. “Simple Ears Inspire Frequency Agility in an Engineered Acoustic Sensor System”. *IEEE Sensors Journal*, 2017.
- [8] J. C. Jackson and D. Robert, “Nonlinear auditory mechanism enhances female sounds for male mosquitoes”. *PNAS*, 103(45): 16734-16739, 2006.
- [9] A. A. Lazar, “Time encoding with an integrate-and-fire neuron with a refractory period”. *Neurocomputing*, 58(60): 53-58, 2004.
- [10] Pikovsky A., Rosenblum M., and Kurths J., “Synchronization: A Universal Concept in Nonlinear Sciences”, Cambridge Univ. Press, 2001.
- [11] C. D. Salthouse and R. Sarpeskar, “Jump resonance: A feedback viewpoint and adaptive circuit solution for low-power active analog filters”, *IEEE Trans. Circuits and Systems*, 53(8): 1712-1725, 2006.
- [12] Rodriguez, T. and Garcia, R., “Theory of Q control in atomic force microscopy”, *Applied Physics Letters*, 82(26): 4821-4823, 2003.
- [13] K. Aono, et al., “Exploiting jump-resonance hysteresis in silicon auditory front-ends for extracting speaker discriminative formant trajectories”, *IEEE Trans. Biomedical Circuits and Systems*, 7(4): 389-400, 2013.