

FLEXIBLE MATERIALS FOR ULTRA WIDEBAND ANTENNA DESIGN

HUSAMELDIN ABDELRAHMAN ELMOBARAK ELOBAID

UNIVERSITI TEKNOLOGI MALAYSIA

FLEXIBLE MATERIALS FOR ULTRA WIDEBAND ANTENNA DESIGN

HUSAMELDIN ABDELRAHMAN ELMOBARAK ELOBAID

A thesis submitted in fulfillment of the
requirements for the award of the degree of
Doctor of Philosophy (Electrical Engineering)

Faculty of Electrical Engineering
Universiti Teknologi Malaysia

APRIL 2018

To my beloved wife: Eman Jaffar Ali and my beloved parents.

ACKNOWLEDGEMENT

I wish to appreciate the Almighty God for His protection, provision and guidance all through the period of my PhD. I express my profound gratitude to my supervisor, Professor Ir. Dr. Sharul Kamal Abdul Rahim for his encouragement, guidance, and ceaseless support throughout this research. I would also like to thank my external-supervisors, Professor Dr. Mohamed Himdi for his advice, motivation and sustainable support.

I am also indebted to all the staff of Wireless Communication Center (WCC), Faculty of Electrical Engineering (FKE), Universiti Teknologi Malaysia (UTM), especially Dr. Igbafe Orikumhi, Dr. Mohamed Abedian and Dr. Bashir Muhammad Saad for their advice and support. I would also like to acknowledge all my colleagues at WCC for their useful views and tips. This work is not complete without the help of IETR research lab in Universite de Rennes 1 in France that assisted in all the fabrication and measurement stage of this research specially Prof Mohamed Himdi, Prof Xavier and Mr Christov. I express my profound gratitude to Ministry of High Education in Malaysia and the Ministry of High Education in Sudan for the financial support. May the Almighty God bless you all and reward you for the kindness.

Finally, I would like to sincerely appreciate my wife, Eman Jaffar for constantly giving me the motivation, support and encouragement to continue with my work. Her prayers, love, patience and understanding contributed immensely to the completion of this work.

ABSTRACT

The demand for ultra-wideband (UWB) antennas increases rapidly with the magnified growth of the wireless systems aiming to support wireless and mobile services by simplifying the systems and to reduce the overall device dimensions, and costs. Vast efforts are offered to the development of UWB antennas that aim to improve the seamless integration with various handheld devices such as laptops, mobile phones, and vehicles such as airplanes, cars, and ships. Consequently, the mechanically flexible antennas are the most suitable for such requirements rather than the antennas based on rigid substrate technology. Hence, the antenna should be conformal and able to be conveniently conformed onto the device's body surface or to be fabricated using the same material in which the devices are fabricated. Subsequently, in some scenarios, the flexible antenna should be optically transparent to overcome the visual impact of the massive use of the antenna in indoor and public areas. Low-cost antenna fabrication technologies are highly expected to take place in future UWB antenna requirements for more economical resource utilization. Generally, UWB systems require the antenna with high efficiency, however, maintaining a high efficiency while achieving extremely wide bandwidth in UWB system is a challenging task. Therefore, conduction and dielectric losses should be minimized in UWB antenna by using highly conductive and low dielectric loss materials. Metals are commonly used as antenna radiating elements because of their high conductivity. However, the poor mechanical flexibility of the metals limit their usage for flexible and conformal applications. The question arises if non-metallic flexible conductive materials having conductivity close to metals can be integrated into the flexible dielectric materials to replace metals. This thesis proposes fabrication techniques to integrate flexible conductive materials into flexible dielectric materials to fabricate transparent UWB antenna and Polymer Matrix Composite (PMC) antenna with improved performance for conformal applications. Moreover, the research evaluates a new low-cost instant printing technique to print UWB flexible antenna with good performance. A technique is proposed to integrate a transparent conductive fabric tissue into a transparent PDMS to fabricate a flexible and transparent UWB antenna with improved performance. The fabricated antenna exhibited an efficiency over 75% and a maximum gain of 4.5 dBi. Moreover, an integration process is proposed to fabricate a flexible PMC composite UWB antenna by integrating the conductive fabric tissue into E-glass fiber mate using Vacuum Infusion Process (VIP). The technology is assessed by fabricating UWB antenna for conformal applications and the results showed high efficiency over 80% for the UWB antenna. Furthermore, a UWB antenna is printed instantly onto a Polyethylene Terephthalate (PET) substrate based on chemical sintering silver inkjet technology using ordinary inkjet printer and the measured results present over 80% of efficiency for antenna.

ABSTRAK

Permintaan terhadap antena ultra jalur lebar (UWB) meningkat dengan pesat seiring pertumbuhan besar sistem tanpa wayar bertujuan untuk menyokong perkhidmatan tanpa wayar dan mudah alih dengan meringkaskan sistem dan mengurangkan dimensi dan kos keseluruhan peranti. Usaha meluas diberikan untuk pembangunan antena UWB yang bertujuan untuk menambah baik persepaduan selanjar dengan pelbagai peranti bimbit seperti komputer riba, telefon mudah alih, dan kenderaan seperti kapal terbang, kereta, dan kapal. Oleh itu, antena yang mudah lentur secara mekanikal adalah paling sesuai untuk keperluan tersebut berbanding antena berasaskan teknologi substrat tegar. Maka, antena harus bersifat menyebentuk dan dapat disesuaikan dengan mudah ke atas permukaan badan peranti atau dibuat dengan menggunakan bahan yang sama seperti peranti tersebut. Selanjutnya, dalam beberapa senario, antena yang fleksibel perlu lutsinar secara optikalnya untuk mengatasi kesan visual penggunaan antena secara besar-besaran di kawasan tertutup dan awam. Teknologi fabrikasi antena berkos rendah dijangka akan memenuhi keperluan antena UWB masa depan untuk penggunaan sumber yang lebih ekonomi. Umumnya, sistem UWB memerlukan antena dengan kecekapan tinggi, namun, mengekalkan kecekapan yang tinggi ketika mencapai lebar jalur yang sangat luas dalam sistem UWB adalah tugas mencabar. Oleh itu, pengaliran dan kehilangan dielektrik harus diminimalkan dalam antena UWB dengan menggunakan bahan yang sangat konduktif dan bahan yang kehilangan dielektriknya rendah. Logam biasanya digunakan sebagai elemen pemancaran antena kerana pengalirannya yang tinggi. Walau bagaimanapun, kelenturan mekanikal logam yang lemah menghadkan penggunaannya untuk aplikasi mudah lentur dan menyebentuk. Persoalan timbul jika bahan konduktif mudah lentur bukan-logam yang mempunyai pengaliran yang hampir sama dengan logam dapat dipersepadukan ke dalam bahan dielektrik mudah lentur untuk menggantikan logam. Tesis ini mencadangkan teknik fabrikasi untuk mensepadukan bahan konduktif yang mudah lentur ke dalam bahan dielektrik yang mudah lentur untuk memfabrikasikan antena UWB lutsinar dan antena Komposit Matriks Polimer (PMC) dengan prestasi yang dipertingkatkan untuk aplikasi menyebentuk. Selain itu, kajian ini menilai teknik percetakan segera berkos rendah baharu yang digunakan untuk mencetak antena mudah lentur UWB dengan prestasi yang baik. Teknik ini dicadangkan untuk mensepadukan tisu fabrik konduktif yang lutsinar ke dalam PDMS lutsinar untuk memfabrikasikan antena UWB yang mudah lentur dan lutsinar dengan prestasi yang lebih baik. Antena yang difabrikasi menunjukkan kecekapan melebihi 75% dan gandaan maksimum 4.5 dBi. Selain itu, proses persepaduan dicadangkan untuk memfabrikasikan antena UWB komposit PMC yang mudah lentur dengan mensepadukan tisu fabrik konduktif ke dalam pasangan gentian E-kaca menggunakan Proses Infusi Vakum (VIP). Teknologi ini dinilai dengan memfabrikasikan antena UWB untuk aplikasi menyebentuk dan keputusannya menunjukkan kecekapan tinggi melebihi 80% untuk antena UWB. Tambahan lagi, antena UWB dicetak segera ke atas bahan Polietilena Tereftalat (PET) berdasarkan teknologi inkjet perak pensinteran kimia menggunakan pencetak inkjet biasa dan hasil yang diukur menunjukkan kecekapan melebihi 80% untuk antena.

TABLE OF CONTENTS

CHAPTER	TITLE	PAGE
	DE CLARATION	ii
	DEDICATION	iii
	ACKNOWLEDGEMENT	iv
	ABSTRACT	v
	ABSTRAK	vi
	TABLE OF CONTENTS	vii
	LIST OF TABLES	xiii
	LIST OF FIGURES	xv
	LIST OF ABBREVIATIONS	xxiii
	LIST OF APPENDICES	xxv
1	CHAPTER 1 INTRODUCTION	1
	1.1 Research Background	1
	1.2 Problem Statement	4
	1.3 Research Objectives	6
	1.4 Scope of Work	7
	1.5 Research Contributions	8
	1.6 Thesis Outline	10
2	CHAPTER 2 LITERATURE REVIEW	12
	2.1 Introduction	12

2.2	Flexible Antenna	12
2.2.1	Polymer Based Flexible Antenna	13
2.2.1.1	Flexible Antenna Based on LCP Substrate	13
2.2.1.2	Flexible Antenna Based on PTFE Substrate	15
2.2.1.3	Flexible Antenna Based on PET Substrate	17
2.2.1.4	Flexible Antenna Based on PDMS Substrate	18
2.2.2	Textile Substrate Flexible Antenna	20
2.2.2.1	Flexible Antenna Based on Flannel Textile Substrate	20
2.2.2.2	Flexible Antenna Based on Denim Textile Substrate	21
2.2.3	Micro Fluidics Flexible Antenna	22
2.2.4	Carbon Nanotube (CNT) Flexible Antenna	23
2.3	Conductive Textile	24
2.4	Planar UWB Antenna	26
2.5	Circular Disc Monopole	26
2.6	Conformal Antenna Applications	28
2.7	Flexible Transparent Antenna Technology	30
2.8	Flexible Transparent Conductive Oxide (TCO) Materials Development Review	30
2.8.1	AgHT Flexible Transparent Conductive Films	31
2.8.2	The Silver nano-wire (AgNW) Transparent Conductive Film	32
2.9	Flexible Transparent Antenna Fabrication Technology Review	33
2.10	Composite Materials	48
2.11	Polymer Matrix Composites (PMC)	49
2.11.1	The PMC Composite Manufacturing Processes	52

2.11.1.1	Spray Lay-up Process	52
2.11.1.2	Wet Lay-up/Hand Lay-up Process	53
2.11.1.3	Vacuum Infusion Process (VIP)	54
2.11.2	Applications of PMC Composite Materials	55
2.12	Conductive Materials Used in PMC Composite Antennas	59
2.12.1	CNT Conductive Composites	60
2.12.2	Reinforced Continuous Carbon Fiber (RCCF)	61
2.12.3	Conductive Carbon Fiber Fabric	61
2.13	PMC Composite Antenna Review	62
2.14	Inkjet Printed Electronics	73
2.15	Conductive Inks	73
2.16	Silver-nano Ink	74
2.17	Room-temperature Chemical Welding and Sintering of Silver Nanostructures	75
2.18	Silver-nano Inkjet Printing Technology for Antenna	77
2.19	Silver Inkjet Printed Antenna in Polymer and Paper Substrates	79
2.20	Summary	85
3	CHAPTER 3 RESEARCH METHODOLOGY	86
3.1	Introduction	86
3.2	Research Framework and Flowchart	86
3.3	Simulation Tools	89
3.4	Materials Characterization Tools and Methods	90
3.4.1	Conductivity Measurement Using Four Probe Method	90
3.4.2	Dielectric Material Characterization Based on Coaxial Probe Method	92

3.4.3	Dielectric Material Characterization using RF Material Analyzer	93
3.4.4	Optical Transparency Measurement	94
3.4.5	Printed layers Surface Roughness and Thickness Measurement Using Profilometer	95
3.5	Antenna Fabrication Machines and Tools	96
3.5.1	Laser Machine	96
3.5.2	Conductive Glue	98
3.6	Far Field Anechoic Chamber	98
3.6.1	The Radiation Pattern Measurement	100
3.6.2	The Gain Measurement	101
3.6.3	The Directivity Measurement	101
3.6.4	The Efficiency Measurement	102
3.7	Fabrication Technology for Flexible Transparent Antenna	102
3.7.1	Transparent Fabric/ PDMS Conductive Panel Fabrication Stage	106
3.7.2	Transparent Fabric/PDMS Antenna Fabrication Process Stage	110
3.8	Flexible PMC Composite Antenna Fabrication Technology	116
3.8.1	Flexible Conductive Composite Panel Fabrication Stage	119
3.8.2	PMC Composite Antenna Fabrication Stage	126
3.9	Low-Cost Instant Inkjet Printing Technology	127
3.10	Design Specifications	130
3.11	Summary	131

4 FLEXIBLE TRANSPARENT UWB ANTENNA FABRICATION TECHNIQUE VALIDATION 133

4.1	Introduction	133
4.2	Material Characterization	133
4.3	Design, Analysis, and Fabrication of the Proposed Flexible Transparent UWB Antenna	134
4.4	Simulation and Measured Results of the Flexible UWB Transparent Antenna Performance	139
4.5	Summary	145
5	FLEXIBLE PMC COMPOSITE UWB ANTENNA FABRICATION TECHNIQUE VALIDATION	146
5.1	Introduction	146
5.2	Material Characterization	147
5.3	Design and Fabrication and Performance Evaluation of Flexible UWB PMC Composite Antenna	148
5.4	Summary	158
6	LOW COST SILVER – NANO INKJET PRINTING TECHNOLOGY FOR FLEXIBLE UWB ANTENNA APPLICATIONS	159
6.1	Introduction	159
6.2	Ink Characterization and Conductivity Measurement	160
6.3	UWB Antenna Printed on Flexible PET Substrate	162
6.4	Summary	169
7	CONCLUSION AND RECOMMENDATIONS FOR FURTHER WORKS	171
7.1	Conclusion	171
7.2	Recommendations for Future Work	173

8 REFERENCE

APPENDICES

LIST OF TABLES

TABLE NO.	TITLE	PAGE
2.1	Measured dielectric constant for pure PDMS and PDMS mixed with (Glass microspheres, Phenolic microspheres, and Silicate microspheres) [29]	18
2.2	Some common conductive fabric	25
2.3	Summary of the reviewed transparent antenna	47
2.4	Summary of the reported composite antenna	72
2.5	Cost comparison of the silver-nano inkjet printing technologies	79
2.6	Summary of literature review in silver inkjet printed antenna	84
3.1	PDMS mixture partial curing temperature and time	110
3.2	Laser beam feed speed and power effect on fabric cutting	113
3.3	Required temperature and time to complete the curing for a partially cured PDMS	115
3.4	Laser beam scan speed and power effect on fabric etching	127
3.5	Design specifications of the UWB transparent antenna	130
3.6	Design specifications of the composite UWB antenna	131
3.7	Design specifications of the silver-nano ink printed UWB antenna	131

4.1	Materials characterization measurement results	134
4.2	Dimensions of Optimized Antenna Design	135
4.3	The fabricated flexible transparent antenna measured efficiency and gain in flat and bending situation	142
4.4	Comparison of the proposed technique and the existing flexible transparent antenna techniques	144
5.1	E-glass fiber composite characterization measurement result	147
5.2	Conductive materials characterization measurement result	147
5.3	Dimensions of optimized UWB antenna design	149
5.4	Gain of the UWB PMC composite antenna and the reference antenna in flat and bent situation	154
5.5	Efficiency of the UWB PMC composite antenna and the reference antenna flat and bent situation	155
5.6	Comparison of the composite UWB antenna with existing similar composite antenna	157
6.1	Silver ink characterization according to multilayers	160
6.2	Skin depth calculation for the three layers in different frequencies	161
6.3	The Characterization measurement results of the PET	162
6.4	Dimensions of optimized UWB antenna design	163
6.5	Comparing the investigated inkjet technology with current technologies	168
6.6	Comparison between the different fabricated flexible antennas	169

LIST OF FIGURES

FIGURE NO.	TITLE	PAGE
2.1	Flexible antenna classification	13
2.2	Fabricated LCP based antenna [18]	14
2.3	The fabricated LCP based patch array antennas (a) 4×4 array (b) 8×8 array [19]	15
2.4	Fabricated PTFE based antenna (a) Flat antenna (b) Bent antenna [20]	16
2.5	The fabricated 4×4 PTFE based patch array antenna [21]	16
2.6	Fabricated PET based antenna [22]	17
2.7	A UWB transparent antenna made of AgHT-4 transparent conductive films based on PET [23]	17
2.8	Fabricated PDMS mixed with different materials to tune the permittivity [29]	19
2.9	Fabricated mm – wave flexible antenna based on PDMS [30]	19
2.10	Fabricated textile antenna based on fannel substrate (a) Using copper tape (b)Using Shielded conductive fabric [31]	21
2.11	Fabricated textile antenna based on denim substrate [32]	22
2.12	Micro fluidic flexible antenna (a) Flat antenna (b) Stretched antenna (c) Bent antenna [33]	23
2.13	CNT flexible patch antenna [34]	24
2.14	Circular disc monopole geometry [37]	27
2.15	Multiple resonance modes [37]	28

2.16	Some of the conformal antenna applications fields (a) Conformal mobile (b) Wearable devices (c) Unmanned aerial vehicle (UAV) (d) High speed trains (e) Naval ships (f) Aircrafts	29
2.17	AgHT TCF materials composite layer	31
2.18	(a) The silver nanowire zoomed photo (b) The TCF film	32
2.19	AgNW TCF stacked materials layers [53]	33
2.20	Schematic displaying the construction of the optically transparent patch antenna (a) Microstrip feed (b) Probe feed [10]	34
2.21	Transparent monopole antenna (a) Schematic view (b) Antenna	35
2.22	Antenna efficiency using TCF with different sheet resistivity [64]	36
2.23	(a) The transparent UWB antenna (b) Return loss measurements of the antenna [65]	36
2.24	Gain sweep for transparent and aluminium UWB antenna using coaxial and optical fibre cables [65]	37
2.25	(a) RFID dipole antenna (b) RFID meandering dipole antenna [66]	37
2.26	(a) Schematic view of the antenna (b) The fabricated antenna [26]	38
2.27	Simulated and measured VSWR of the UWB antenna [26]	38
2.28	Measured gain of the antenna from 3 to 32 GHz [26]	39
2.29	Fabricated antenna [24]	39
2.30	Simulated and measured S11 of proposed UWB antenna with CSRR [24]	40
2.31	Measured gain [24]	40
2.32	(a) Schematic view of the UWB antenna (b) Fabricated antenna [67]	41
2.33	Simulated and measured S11 of the designed UWB [67]	41

2.34	Simulated and measured peak gain of the proposed antenna in [67] compared to the antenna with 50x 60 of size which reported in [68]	41
2.35	Simulated and measured efficiency of the proposed antenna in [67] compared to the antenna with 50x 60 of size which reported in [68]	42
2.36	Proposed flexible transparent antenna for wearable glass [70]	43
2.37	The PVD fabrication process. (a) PI substrate cleaning. (b) Masking. (c) Deposition. (d) Mask removal [70]	43
2.38	Photographs of the fabricated antennas. (a) ITO transparent antenna. (b) Homogeneously transparent antenna (7-nm gold). (c) Heterogeneous transparent antenna (7-nm gold) [72]	45
2.39	(a) Sheet resistance versus different thicknesses of the gold nano-layer (b) Transparency versus different thicknesses of the gold nano-layer [72]	46
2.40	A sample of epoxy resin with hardener [78]	49
2.41	(a) A sample of a carbon fiber material (b) A sample of a glass fiber material [78]	50
2.42	PMC composite components	50
2.43	The mechanical properties of the resin, fiber and the FRP [78]	51
2.44	Spray lay-up fabrication process [78]	52
2.45	Wet Lay-up/Hand Lay-up fabrication process [78]	53
2.46	Vacuum infusion process system set up [78]	54
2.47	The usage of the PMC composites in aero- structures [81]	56
2.48	Developed economical cars based on carbon fiber PMC composites [86]	57
2.49	(a) Apple brand mobile phone made of carbon fiber PMC composite (b) Apple brand laptop made of carbon fiber PMC composite	58

2.50	(a) Schematic view of the SWCNT [105] (b) Schematic view of the MWCNT [102]	60
2.51	(a) RCCF composite, (b) Cross-view of RCCF composite, (c) Optical micrograph of RCCF Composite (scale bar 50 μm) [107]	61
2.52	Conductive Carbon fiber fabric photo	62
2.53	(a) The radiation elements made of RCCF (b) The frequency shift in S11 as a result of using the RCCF (c) The current distribution in metal and RCCF [109]	63
2.54	Monopole UWB antenna, (a) Schematic front view, and (b) EM model in CST [112]	63
2.55	Simulated reflection coefficient of the monopole antenna with metal and composite radiating element [112]	64
2.56	Fabrication process of the RCCF/MWCNT composite (a) Milling the MWCNT (b) The unidirectional RCCF [112]	65
2.57	(a) Efficiency due to different thickness of RCCF/MWCNT (b) Gain due to different thickness of RCCF/MWCNT [112]	65
2.58	(a) Prototype of the fabricated antenna (b) S11 of the antenna [113]	66
2.59	(a) Bucky paper preparation. (b) Substrate plating with bucky papers: 1- Impregnated bucky paper-patch 2- Composite substrate 3- Vacuum bag 4- Breather 5- Release film 6- Sealant [113]	67
2.60	Lozenge monopole antenna schematic view: (a) Front-view (b) Side-view [12]	68
2.61	Lozenge monopole antennas photo: (a) Copper radiating element embedded inside composite laminate (reference antenna) (b) Carbon-fiber radiating element (one ply) embedded inside composite laminate [12]	68
2.62	Measured gain for the carbon fiber based antenna and the reference copper based antenna (from 600 MHz to 3 GHz) [12]	69

2.63	Input impedances measured at (700 MHz to 4.5 GHz) for the carbon fiber based antenna (grey-dashed line) and the (black-solid line) is the copper counterpart [114]	70
2.64	Measured gain at frequency band (600 MHz to 6 GHz) for the carbon fiber based antenna and the copper reference antenna [114]	70
2.65	Progression of silver-nano particle contact during sintering (a) Seconds after printing (b) 5 minutes at 1500 (c) 3 hours at 1500 [121]	75
2.66	Room-temperature chemical welding of AgNWs network by capillary condensation of H ₂ O ₂ vapour (a) Schematic illustration of chemical welding by capillary condensation (b) Zoomed photo of the AgNWs network on plastic (PET) substrate, the dotted red circle shows the junction between AgNWs (c) Zoomed photo of the chemically welded AgNWs junctions are highlighted in dotted red circles	77
2.67	Fujifilm Dimatix 2800 material printer [129]	78
2.68	Brother printer using Mitsubishi NBSIJ-MU01 ink (a) The printer (b) Filling the ink cartridge [130]	78
2.69	The printed Vivaldi antenna (a) Front view, and (b) Back view [133]	80
2.70	Simulated and measure (a) S ₁₁ of the UWB Vivaldi antenna (b) Realized gain of Vivaldi antenna [133]	80
2.71	Fabricated fractal UWB antenna with (a) Koch Snowflake (b) Koch Snowflake patterned with Sierpinski gasket [134]	81
2.72	The S ₁₁ of the Fractal UWB antenna [134]	81
2.73	(a) The fabricated antenna (b) The simulated and measured return loss of the antenna [130]	82
2.74	The fabricated antenna [15]	83
2.75	The TAG antenna reflection coefficient [15]	83
3.1	Research process framework	88
3.2	(a) The schematic layout (b) The four-probe connected to the MUT (c) The standard four-probe setup	91

3.3	Coaxial probe measurement set up	93
3.4	RF analyzer (a) The test head (b) The RF analyzer photo	94
3.5	UV– visible PerkinElmer Lambda 20 spectrophotometer	95
3.6	Profilometer photo	96
3.7	ProtoLaser S4 124102 laser machine	97
3.8	Silver epoxy pastes	98
3.9	(a) Antenna under testing in chamber (b) Reference horn antenna in far field chamber	99
3.10	Schematic view of the radiation pattern measurement setup	100
3.11	Transmission spectra of transparent fabric tissue and PDMS	104
3.12	Transparent fabric tissue (a) Zoomed view and (b) Photo of the fabric tissue	104
3.13	Transparent antenna fabrication process flowchart	105
3.14	Mixing the elastomer and hardener based on 10:1 ratio; (a) Pouring 7.2g of elastomer (b) Pouring 0.72g of the hardener	106
3.15	PDMS mixture with air bubbles	107
3.16	PDMS mixture placed in a vacuum chamber	107
3.17	The mixture after bubbles removal	108
3.18	The prepared mold made of thermoplastic material	109
3.19	PDMS mixture placed in the oven	109
3.20	Steps of exporting the CST file to Gerber file format	111
3.21	Setting the laser parameters	112
3.22	Burned fabric photo during laser cutting due to improper laser settings as in Table 3.2	113
3.23	The transparent conductive panel placed in the laser machine for fabrication	114
3.24	Importing the Gerber file to the CircuitPro PM machine software	114
3.25	Starting the laser machining	115
3.26	The E-glass fiber mat	117
3.27	PMC composite antenna fabrication process flowchart	118
3.28	Schematic view of the vacuum infusion process equipment set up	119

3.29	The improvement of the composite flexibility with thickness reduction	120
3.30	Wax the glass mold	121
3.31	Prepare the vacuum bag	121
3.32	Setting up the spiral tubes	122
3.33	Closing the vacuum bag	122
3.34	Vacuum Drop Test	123
3.35	Checking for leaks for vacuum drop test	123
3.36	E-fiber glass and the conductive fabric under the vacuum bag are placed under vacuum	124
3.37	Infusion with a liquid epoxy resin	124
3.38	The fabricated flexible conductive PMC composite thin panel	125
3.39	E-glass fiber epoxy resin composite panel	125
3.40	The composite substrate is burned during laser etching using improper laser settings as in Table 3.4	127
3.41	(a) Silver-nano ink cartridge compatible with Brother (MFC J430W) printer (b) The ink cartridge installed in the printer	129
3.42	Brother MFC-J430W printing set up	129
4.1	Schematic view of the antenna	135
4.2	Surface current distribution (a) at 4 GHz and (b) at 12 GHz	136
4.3	The effect of the ground plane length L_g in the S11	137
4.4	The effect of disk modification and ground slots in S11	138
4.5	The effect of the ground plane width (W) in the S11	138
4.6	The fabricated fabric – PDMS transparent UWB antenna	139
4.7	Simulated and measured S11 of the transparent antenna	140
4.8	(a) Antenna S11 under bending conditions where the antenna bent to (b) 90° (c) 50mm (d) 25mm	141
4.9	Measured and simulated antenna radiation patterns in flat and bending situations at (a) 3.3 GHz and (b) 6 GHz	143
5.1	The schematic view of the proposed UWB antenna	149
5.2	Surface current at: (a) 3.5 GHz (b) 5 GHz (c) 9 GHz (d) 11 GHz	150

5.3	The effect of R2 and R3 in the antenna S11	151
5.4	The effect of G1 in S11	151
5.5	The effect of G2 in S11	152
5.6	Fabricated antenna: (a) Composite antenna (b) Reference copper antenna	152
5.7	(a) Simulated and measured $ S_{11} $ of the composite antenna in flat and bending conditions (b) Photo of the antenna bent to 50 mm (c) Photo of the antenna bent to 25 mm	153
5.8	The radiation patterns of the PMC composite UWB antenna in flat and curved situations	156
6.1	Square shapes is printed onto a PET substrate with different layer thickness	160
6.2	The UWB antenna schematic view	163
6.3	(a) Printing the UWB antenna into PET film (b) The printed antenna can easily bent without damaging the antenna	164
6.4	Zoomed view of the printed CPW feed line showing G1 = 0.30 mm	164
6.5	The simulated and measured S11 result of the flexible printed UWB antenna	165
6.6	The measured S11 of the flexible printed UWB antenna in flat and curved situation	165
6.7	The simulated and measured gain of the flexible printed UWB antenna	166
6.8	The simulated and measured efficiency of the flexible printed UWB antenna	166
6.9	E and H planes radiation patterns	167
B.0.1	CST simulation tool	197
B.0.2	Parametric Analytical tool	198
B.0.3	CST MWS optimizer user interface settings	198

LIST OF ABBREVIATIONS

1-D	-	One Dimensional
2-D	-	Two Dimensional
4G	-	Fourth Generation
5G	-	Fifth Generation
AF	-	Array Factor
Ag	-	Silver
AgHT	-	Silver-coated Polymer
AUT	-	Antenna Under Test
AWR	-	Applied Wave Research
BW	-	Bandwidth
CST	-	Computer Simulation Technology
Cu	-	Copper
CPW	-	Coplanar Waveguide
D2D	-	Device To Device
DOA	-	Direction Of Arrival
EBG	-	Electronic Band Gap
FFT	-	Fast Fourier transform
FIR	-	Finite Impulse Response
FR4	-	Frame Resistance 4

HPBW	-	Half Power Beamwidth
IMT	-	International Mobile Telecommunications
ITU	-	International Telecommunication Union
ITO	-	Indium Tin Oxide
LHCP	-	Left Hand Circular polarization
LTCC	-	Low Temperature Co-fired Ceramics
M2M	-	Machine to Machine
MIMO	-	Multiple Input Multiple Output
MMIC	-	Monolithic Microwave Integrated Circuit
MWS	-	Microwave Studio
NLOS	-	Non-Line of Sight
PCB	-	Printed Circuit Board
PIN	-	Positive-Intrinsic-Negative
PET	-	Polyethylene terephthalate
RF	-	Radio Frequency
RHCP	-	Right Hand Circular polarization
RSS	-	Received Signal Strength
SAS	-	Smart Antenna System
SBSA	-	Switched Beam Smart Antenna
SIR	-	Signal to Interference Ratio
SIW	-	Substrate Integrated Waveguide
SLL	-	Side Lobe Level
VNA	-	Vector Network Analyzer

LIST OF APPENDICES

APPENDIX	TITLE	PAGE
A	List of Publications	194
B	Computer Simulation Technology (CST) Microwave Studio	196
C	Applied Wave Research	199

CHAPTER 1

INTRODUCTION

1.1 Research Background

It is worthwhile to note that the sparks radiated by Hertz experiments using a wideband loaded dipoles represent the first generated UWB signals. However, due to the lack of resources at that time, the wideband energy could not be retrieved effectively, therefore the discovered communication setup was abandoned. Later, the radar, sensing, and military communications applications were developed by applying impulse radio technologies during the 1960s and 1970s. Nevertheless, the “Ultra Wideband” term found for the first time by the United State U.S department of defense in 1989. During the 1990s, the UWB systems started to receive a wide interest with the improvement in digital signal processing. In 2002, the interest in UWB system greatly increased when the Federal Communications Commission (FCC) (the frequency regulating body of the United States) decided to release the approving report the use of UWB devices to operate a number of unlicensed frequency bands [0-960 MHz], [3.1-10.6 GHz], and [22-29 GHz]. Subsequently, several regulations were defined by various frequency regulatory bodies around the world [1].

Unlike the conventional carrier wave system, UWB possess abundant unique characteristics which enables it to present an eloquent solution to the broadband wireless systems.

Firstly, UWB system is a sort of base-band signal transmission process that has low cost and low complexities which arise from the fact that it does not modulate and demodulate a complex carrier waveform. Therefore, components such as filters, mixers, amplifiers and local oscillators are not required in UWB transmission.

Secondly, the main aim of the UWB is to achieve very high capacity through the utilization of an ultra-wide bandwidth which can reach up to several Gbps in short distance from 1 to 10 m [2]. Therefore UWB plays a very important role in wideband technologies such as Wireless Personal Area Network (WPAN). It provides a reliable wireless connectivity between portable devices, computers, and consumer electronics via a short range. Furthermore, the high data rate feature enables a fast data exchange and storage between several UWB systems.

Thirdly, the UWB concept is very attractive for the spreading systems since it facilitates optimal bandwidth sharing between various applications and systems. With a very high-frequency adaptive feature, the UWB systems are able to employ the various RF spectrum which enables it to prevent interference to other existing systems while using the entire spectrum. Moreover, the UWB systems nature is immune to the multipath and lossy media effect. The transmission of the UWB systems operates at extremely low level power. Therefore, UWB radio technologies operate at short-range to complements the long-range technologies such as cellular wide area communications, Wireless Fidelity (WiFi), and Worldwide Interoperability for Microwave Access (WiMAX).

Finally, UWB systems provide a highly secure and reliable connectivity solutions. This is because the UWB operates with a low power density which makes the signal comparable to noise signal thereby making it difficult to detect or intercept.

With the increasing growth in wireless communication systems and services, factors such as high data rate, device form factor and cost has led to the increasing demand for wideband, multiband and UWB antennas. Many efforts are offered to integrate various types of conventional rigid antennas and flexible antennas into various handheld devices such as laptops, mobile phones, tablets in addition to the radio base stations and vehicles such as airplanes, cars, and ships. However, the mechanically flexible antennas are the most suitable for such requirements rather than the antennas based on rigid substrate technology such as printed circuit boards (PCB). Hence, the antenna should be conformal to the devices body surface or it should be fabricated using the same material with which the device is fabricated from. Furthermore, the antenna should be designed and fabricated based on highly conductive and flexible materials to be integrated with low loss flexible dielectric materials so that the antenna will gain high performance. The performance should not sacrifice under bending conditions when the antenna is bent. Therefore, new fabrication technologies are required to fabricate UWB antennas from the most common materials that consisting most of the things around us such as ploymer matrix composite (PMC) materials [3]. The PMC composite materials made of polymer material such as epoxy resin called matrix and a reinforcement material such as carbon fiber or glass fiber, are known as a future material that will be the rough material to fabricate different devices and things such as (electronic and electrical devices, house's structure, furniture, vehicles, medical tools and devices, trans, marine boats and ships, aircrafts and many other applications [4, 5].

Moreover, with the increase of wireless communication systems in indoor living spaces and public places, flexible optically transparent antennas are an attractive solution to reduce the visual impact of these systems. For example, the transparent antennas could be used for an indoor security system or in future transparent communication devices such as femtocell [6]. Consequently, the transparent antenna should be able to be conformed to different surfaces and shapes by fabricating the transparent antenna from flexible transparent materials.

The increasing demand for seamless integration of UWB systems with wearable microelectronics to provide low-cost high performance wearable systems. As such, new fabrication techniques should be developed to fabricate flexible UWB antennas using low-cost materials and low-cost fabrication process. In recent years, inkjet printing technologies have been investigated and evaluated to print antennas into flexible printable substrates and films. In addition, low-cost and the simplicity of the fabrication process is a key factor for the technology by instantly printing an antenna that is able to operate efficiently seconds after printing.

1.2 Problem Statement

Due to high data rate, low power and short distance in indoor environment, UWB systems are increasingly being considered for various wireless wearable applications such as flexible microelectronics, wearable devices, and portable electronic gadgets [7, 8]. However, maintaining high radiation efficiency is mandatory to ensure the achievement of the required extremely low transmitted spectral power density for UWB applications and the excessive UWB antenna losses could significantly compromise the whole system functionality.

The demand for wireless wearable applications is increased rapidly in the recent years leading to the employment of a huge amount of antennas in the indoor and public areas. This has increase the demand for flexible antennas that is able to fit into devices of various shapes and sizes, as well as being environmentally friendly to overcome the negative visual impact. Flexible UWB transparent antennas are expected to fulfill these requirements. The flexible UWB antennas have been widely used in various applications, such as vehicle communication and navigation, integration with satellite solar cell panels and with glass for security concerns [9, 10]. However, the fabrication complexity, lossy nature and low efficiency of transparent conductive materials limit the amount of research conducted on such antenna for

UWB applications. Cost reduction and seamless integration is required for the integration of the flexible UWB antennas with handheld devices such as laptops, mobile phones, tablets, radio base stations and various vehicles. Therefore, flexible UWB antennas should be fabricated from or integrated with the materials that most of these devices are fabricated from. Polymer matrix composite (PMC) materials are expected to be the future materials, which will be used in a massive amount of applications [11]. Conductive materials such as carbon fiber composites (CFC) and carbon fiber fabrics have been used as radiating elements in PMC composite antennas. However, its low conductivity is negatively impacting the efficiency, gain and the overall antenna radiation performance [12]. Inkjet printing technology is another factor to be considered to achieve the low cost and seamless integration of antennas with microelectronic systems based on low cost substrates such as polymeric materials and papers. Several technologies have been proposed recently by using silver nanoparticles ink based onto a different flexible substrate such as Kapton polyimide [13], papers [14] and polyethylene terephthalate (PET) [15]. Most of the reported inkjet printing methods are based on thermal sintering, which requires long time process for ink thermal curing to achieve the highest conductivity. Moreover, the main bottleneck in inkjet-printed features on flexible polymeric substrates is the low softening point of the substrate or the amount of temperature that when reached the substrate material will melt or burned, which limits the processing temperature. The softening point of commonly used polymeric substrates, like PET or polycarbonate (PC), is lower than 150° C. Typically, colloidal suspensions of conductive materials need a sintering temperature higher than 200° C, which is hence not compatible with most polymeric substrates [16].

The use of highly conductive flexible materials as radiating elements can improve the low radiation efficiency due to high conduction losses in the flexible UWB transparent and PMC composite antennas. Consequently, a method is required to produce a flexible transparent antenna with improved radiation efficiency by integrating highly conductive flexible transparent material with low loss transparent and flexible dielectric material. Polymer material such as PDMS possess high optical transparency, mechanical flexibility, high ability for

integration with other materials and low tangent loss around ($\epsilon_r = 2.85$ at 10 GHz), can be used as a transparent substrate. Similarly, a fabrication method should be developed to integrate a high conductive material which is suitable for resin lamination to be embedded with the reinforcement fibers such as carbon fiber or glass fibers to produce a fully PMC composite antenna. Conductive fabrics can be good choice because it has high conductivity and the mesh style of the fabric will help in absorbing the resin and hence allow full lamination and integration with the PMC composites. The free sintering inkjet printing technologies in which the conductive ink can be cured in room temperature can provide a low cost, low processing time and seamless integration for flexible UWB antennas with microelectronic and wearable devices.

In summary, the currently used transparent conductive films have poor conductivity which significantly affects the antenna radiation performance. Therefore, integrating highly conductive transparent and flexible material with low loss transparent and flexible dielectric material can produce low loss transparent UWB antenna. In addition, the use of highly conductive materials to integrate with PMC composite materials will produce a fully PMC composite antenna with high radiation performance. Moreover, new inkjet printing technologies having superior features such as low cost, sintering free and high conductivity can produce a low cost, low processing time and seamless integration method to integrate the UWB antennas into various microelectronics and wearable devices.

1.3 Research Objectives

This research has the following objectives:

- i. To develop a method to improve the radiation performance of the flexible transparent antenna by using highly conductive flexible transparent material

and to verify the method by fabricating a flexible transparent UWB antenna for conformal antenna applications.

- ii. To develop a method to improve the radiation performance of the flexible PMC composite antenna by using highly conductive flexible material and to verify the method by fabricating a flexible PMC composite UWB antenna for conformal antenna applications.
- iii. To investigate the use of a chemically sintered low cost silver-nano ink for inkjet printing technology, to instantly print flexible UWB antenna.

1.4 Scope of Work

This study is limited to develop a method to integrate a highly conductive flexible material onto a flexible dielectric materials to produce a flexible antenna with significantly enhanced radiation performance in terms of efficiency and gain for conformal applications for UWB systems and future wireless networks. The study focused on flexible transparent antenna technology, flexible polymer matrix composite (PMC) antenna technology based on composite laminate material made of E-glass fiber mat and epoxy resin. Moreover, the study investigated the use a low cost chemically sintered silver-nano inkjet printing technology for printed flexible UWB antenna. The study focused on the conformal antenna case where the antenna is bent to a certain curved surface.

CST microwave studio[®] software is used in designing the flexible antenna prototypes, testing, and optimization. Moreover, the bending test will be conducted by bending the antennas on a loss less surface such as flexible foam having dielectric constant and tangent loss closed to air. The study also includes measuring the

radiation performance of the antenna such as (S_{11} , radiation pattern, gain, and efficiency).

1.5 Research Contributions

The research, major contributions are listed below:

a. **A Transparent and Flexible Fabric -Polymer Tissue Fabrication Technique for UWB Antenna**

In this contribution, the study has proposed a method to integrate a flexible transparent and highly conductive fabric tissue onto a PDMS substrate with a thickness of 2 mm to produce a transparent conductive film with very low sheet resistivity $R_s = 0.089$ ohm/sq compared to the conventional transparent conductive films such as indium tin oxide ITO and silver-coated polymer (AgHt) having sheet resistivity of (2-15) ohm/sq. Due to the high sheet resistivity of the conventional TCF, transparent antennas made of this kind of TCF suffer from high loss and thus exhibit low efficiency. Therefore, the low sheet resistivity of the produced TCF using the proposed method will help in reducing the losses and hence improve the antenna efficiency. Then the method proposed a laser etching process to fabricate a flexible transparent UWB antenna precisely. The fabricated UWB antenna exhibits an average measured radiation efficiency of 75% throughout the operating band, and shows a maximum gain of 4.5 dBi at 18 GHz and a stable radiation pattern. It performs well under bending conditions, as observed from the measured results.

b. **A Flexible Fabric/ E-glass Fiber PMC Composite Fabrication Technique for UWB Antenna**

A full flexible PMC composite antenna with high radiation performance is fabricated using highly conductive fabric as a radiating element compared to a reference antenna made of a metal conductor. The contribution of this technique is to improve the radiation efficiency of the composite antenna by integrating the composite dielectric material with a highly conductive material suitable for integration with composites. Therefore, a thin sheet of a highly conductive fabric with high conductivity of 2×10^5 S/m is embedded by infusion process in a thin composite laminate made of E-glass fiber mat and epoxy resin to produce a flexible conductive PMC composite film to be used for the fabrication of a UWB antenna with high radiation performance. The composite antenna made of the conventional conductive composite materials such as carbon fiber composite (CFC) and carbon fiber fabrics suffer from high losses and poor radiation efficiency due to the low conductivity of these materials which is about (3.5×10^2 S/m – 3×10^4 S/m). In addition, the fabric mesh style of the conductive fabric makes it very suitable to be laminated with resin and thus seamless integration with composite material. Moreover, the fabrication technique proposes a laser etching method for precise antenna fabrication where the conductive fabric is embedded inside the resin; therefore, the laser will etch the unnecessary parts of the fabric without affecting the dielectric substrate. The fabrication technique is validated by fabricating a UWB antenna. The fabricated antenna exhibited a measured radiation efficiency reaches over 80% averaged value throughout the operating frequency band with a maximum gain of 3.1 dBi at 5 GHz and stable radiation patterns. The composite antenna performs well under bending conditions as demonstrated by the measurements.

c. A Low Cost Instant Inkjet-Printed Flexible UWB Antenna

This contribution investigated low-cost silver–nano inkjet printing technology for seamless integration of the UWB antennas with printable electronics and systems. The investigated printing technology possesses

superior properties such as low cost, room temperature fast sintering and low processing time compared to the conventional silver–nano printing technology based on thermal sintering. A UWB antenna is printed onto a PET film and the printed traces are sintered instantly where the highest conductivity value achieved within few seconds without any further sintering process and without affecting the polymer substrate. The antenna elements are printed precisely using an ordinary inkjet printer. The antenna operates effectively in the 3.3 GHz - 12 GHz band. Its radiation efficiency reaches over 80% average value throughout the operating frequency band with stable radiation patterns. It exhibits highly flexible mechanical properties enabling it to be bent without sacrificing its performance.

1.6 Thesis Outline

This thesis is outlined in seven chapters. The first chapter presents the overall view of the project, which includes the research background, problem statement, the research objectives, the contributions to knowledge, the research scope, and the thesis organization.

The second chapter reviews the literature. The chapter discusses structural aspects of the flexible antenna and the electrical characteristics of flexible materials. Also, the requirements and challenges of transparent, composite and inkjet printed antenna applications are presented.

The methodology used to realize the proposed technologies and the antenna design are discussed in Chapter 3 initiated with the detail discussion of the research framework. The step by step fabrication technology which proposed in this research to fabricate flexible transparent antenna, flexible PMC composite antenna and the inkjet printed antenna is presented. In addition, the fabrication and measurement

procedures and tools used are demonstrated. The design specifications and parameters used to achieve the desired results are demonstrated.

Chapter 4 discuss the validation of the flexible transparent antenna technique presented in chapter 3 through the design and fabrication of a UWB antenna. The antenna radiation performance has been evaluated via analysing the measurement and simulated results of the return loss, gain, efficiency and radiation patter. At the end of the chapter the achieved antenna performance results has been compared to the previous reported flexible transparent antenna radiation performance.

Chapter 5 illustrate the validation of the flexible PMC composite antenna technique presented in chapter 3 by designing and fabricating a UWB antenna. To evaluate the antenna radiation performance, the measurement and simulated results of the return loss, gain, efficiency and radiation patter has been compared and analysed. At the end of the chapter the achieved antenna performance results has been compared to the previous reported flexible composite antenna radiation performance.

Chapter 6 demonstrates the evaluation of a sintering free and instant inkjet printing technology for printed flexible UWB antenna applications. The technology assessment has been presented throughout the chapter by printing UWB antenna and discussing the performance results.

Finally, the conclusion and the recommendations for further work are presented Chapter 7. The achievements of the research and future works recommendations are depicted. A list of the references and some appendices are documented at the end.

REFERENCE

- [1] Y. Duroc and A. I. Najam, *UWB antennas: design and modeling*: INTECH Open Access Publisher, 2010.
- [2] I. Oppermann, M. Hämäläinen, and J. Iinatti, *UWB: theory and applications*: John Wiley & Sons, 2005.
- [3] R. Cicchetti, E. Miozzi, and O. Testa, "Wideband and UWB antennas for wireless applications: a comprehensive review," *International Journal of Antennas and Propagation*, 2017.
- [4] R. F. Gibson, "A review of recent research on mechanics of multifunctional composite materials and structures," *Composite structures*, vol. 92, pp. 2793-2810, 2010.
- [5] G. Gupta, A. Kumar, R. Tyagi, and S. Kumar, "Application and Future of Composite Materials: A Review," *Int. J. Innov. Res. Sci. Technol*, vol. 5, pp. 6907-6911, 2016.
- [6] J. R. Saberlin and C. Furse, "Challenges with optically transparent patch antennas," *IEEE Antennas and Propagation Magazine*, vol. 54, pp. 10-16, 2012.
- [7] Y. Hao, A. Alomainy, P. Hall, Y. Nechayev, C. Parini, and C. Constantinou, "Antennas and propagation for body centric wireless communications," in *Wireless Communications and Applied Computational Electromagnetics, 2005. IEEE/ACES International Conference on*, 2005, pp. 586-589.

- [8] A. Fort, C. Desset, P. De Doncker, P. Wambacq, and L. Van Biesen, "An ultra-wideband body area propagation channel model-from statistics to implementation," *IEEE Transactions on Microwave Theory and Techniques*, vol. 54, pp. 1820-1826, 2006.
- [9] C.-T. Lee, C.-M. Lee, and C.-H. Luo, "The transparent monopole antenna for WCDMA and WLAN," in *2006 IEEE Annual Wireless and Microwave Technology Conference*, 2006, pp. 1-3.
- [10] R. N. Simons and R. Q. Lee, "Feasibility study of optically transparent microstrip patch antenna," 1997.
- [11] M. Gururaja and A. H. Rao, "A review on recent applications and future prospectus of hybrid composites," *Int J Soft Comput Eng*, vol. 1, pp. 352-5, 2012.
- [12] L. Manac'h, X. Castel, and M. Himdi, "Performance of a lozenge monopole antenna made of pure composite laminate," *Progress In Electromagnetics Research Letters*, vol. 35, pp. 115-123, 2012.
- [13] S. Ahmed, F. A. Tahir, A. Shamim, and H. M. Cheema, "A Compact Kapton-Based Inkjet-Printed Multiband Antenna for Flexible Wireless Devices," *IEEE Antennas and Wireless Propagation Letters*, vol. 14, pp. 1802-1805, 2015.
- [14] A. Rida, L. Yang, R. Vyas, and M. M. Tentzeris, "Conductive inkjet-printed antennas on flexible low-cost paper-based substrates for RFID and WSN applications," *IEEE Antennas and Propagation Magazine*, vol. 51, pp. 13-23, 2009.
- [15] G. A. Casula, G. Montisci, and G. Mazzarella, "A wideband PET inkjet-printed antenna for UHF RFID," *IEEE Antennas and Wireless Propagation Letters*, vol. 12, pp. 1400-1403, 2013.
- [16] T. H. Van Osch, J. Perelaer, A. W. de Laat, and U. S. Schubert, "Inkjet printing of narrow conductive tracks on untreated polymeric substrates," *Advanced Materials*, vol. 20, pp. 343-345, 2008.

- [17] G. DeJean, R. Bairavasubramanian, D. Thompson, G. Ponchak, M. Tentzeris, and J. Papapolymerou, "Liquid crystal polymer (LCP): a new organic material for the development of multilayer dual-frequency/dual-polarization flexible antenna arrays," *IEEE Antennas and Wireless Propagation Letters*, vol. 4, pp. 22-26, 2005.
- [18] L. Marnat and A. Shamim, "Liquid crystal polymer (LCP) based antenna for flexible system on package (SoP) applications," in *Antenna Technology and Applied Electromagnetics (ANTEM), 2012 15th International Symposium on*, 2012, pp. 1-4.
- [19] P. Cabrol and P. Pietraski, "60 GHz patch antenna array on low cost liquid-crystal polymer (LCP) substrate," in *Systems, Applications and Technology Conference (LISAT), 2014 IEEE Long Island*, 2014, pp. 1-6.
- [20] H. Liu, S. Zhu, P. Wen, X. Xiao, W. Che, and X. Guan, "Flexible CPW-fed fishtail-shaped antenna for dual-band applications," *IEEE Antennas and Wireless Propagation Letters*, vol. 13, pp. 770-773, 2014.
- [21] A. Bondaruk and D. Sjöberg, "60 GHz microstrip antenna array on PTFE substrate," in *Antennas and Propagation (EUCAP), 2012 6th European Conference on*, 2012, pp. 1016-1018.
- [22] K. Hettak, T. Ross, R. James, A. Momciu, and J. Wight, "Flexible polyethylene terephthalate-based inkjet printed CPW-fed monopole antenna for 60 GHz ISM applications," in *Microwave Integrated Circuits Conference (EuMIC), 2013 European*, 2013, pp. 476-479.
- [23] T. Peter, T. A. Rahman, S. Cheung, R. Nilavalan, H. F. Abutarboush, and A. Vilches, "A novel transparent UWB antenna for photovoltaic solar panel integration and RF energy harvesting," *IEEE Transactions on Antennas and Propagation*, vol. 62, pp. 1844-1853, 2014.
- [24] M. Rani, S. K. A. Rahim, M. R. Kamarudin, T. Peter, S. Cheung, and B. Saad, "Electromagnetic behaviors of thin film CPW-fed CSRR loaded on UWB transparent antenna," *IEEE Antennas and Wireless Propagation Letters*, vol. 13, pp. 1239-1242, 2014.

- [25] T. Peter, "Optically transparent UWB antenna for wireless application & energy harvesting," Brunel University School of Engineering and Design PhD Theses, 2012.
- [26] S. Hakimi, S. K. A. Rahim, M. Abedian, S. Noghabaei, and M. Khalily, "CPW-fed transparent antenna for extended ultrawideband applications," *IEEE Antennas and Wireless Propagation Letters*, vol. 13, pp. 1251-1254, 2014.
- [27] M. A. Eddings, M. A. Johnson, and B. K. Gale, "Determining the optimal PDMS–PDMS bonding technique for microfluidic devices," *Journal of Micromechanics and Microengineering*, vol. 18, p. 067001, 2008.
- [28] C.-P. Lin, C.-H. Chang, Y. Cheng, and C. F. Jou, "Development of a flexible SU-8/PDMS-based antenna," *IEEE Antennas and Wireless Propagation Letters*, vol. 10, pp. 1108-1111, 2011.
- [29] J. Trajkovikj, J.-F. Zürcher, and A. K. Skrivervik, "PDMS, a robust casing for flexible W-BAN antennas [EurAAP corner]," *IEEE Antennas and Propagation Magazine*, vol. 55, pp. 287-297, 2013.
- [30] N. Tiercelin, P. Coquet, R. Sauleau, V. Senez, and H. Fujita, "Polydimethylsiloxane membranes for millimeter-wave planar ultra flexible antennas," *Journal of Micromechanics and Microengineering*, vol. 16, p. 2389, 2006.
- [31] M. A. Osman, M. Rahim, N. Samsuri, M. Elbasheer, and M. Ali, "Textile UWB antenna bending and wet performances," *International Journal of Antennas and Propagation*, vol. 2012, 2012.
- [32] M. E. Jalil, M. K. A. Rahim, M. A. Abdullah, and O. Ayop, "Compact CPW-fed ultra-wideband (UWB) antenna using denim textile material," in *Antennas and Propagation (ISAP), 2012 International Symposium on*, 2012, pp. 30-33.

- [33] S. Cheng, Z. Wu, P. Hallbjorner, K. Hjort, and A. Rydberg, "Foldable and stretchable liquid metal planar inverted cone antenna," *IEEE Transactions on antennas and propagation*, vol. 57, pp. 3765-3771, 2009.
- [34] Y. Zhou, Y. Bayram, F. Du, L. Dai, and J. L. Volakis, "Polymer-carbon nanotube sheets for conformal load bearing antennas," *IEEE Transactions on Antennas and Propagation*, vol. 58, pp. 2169-2175, 2010.
- [35] (2016). *Conductive Textile* Available: www.lessemf.com/fabric_guide.html
- [36] *conductive textile* Available: <https://www.sparkfun.com/>
- [37] J. Liang, C. C. Chiau, X. Chen, and C. G. Parini, "Study of a printed circular disc monopole antenna for UWB systems," *IEEE Transactions on antennas and propagation*, vol. 53, pp. 3500-3504, 2005.
- [38] L. Josefsson and P. Persson, "Scattering from Conformal Arrays," *Conformal Array Antenna Theory and Design*, pp. 421-461.
- [39] P. Salonen, J. Kim, and Y. Rahmat-Samii, "Dual-band E-shaped patch wearable textile antenna," in *Antennas and propagation society international symposium, 2005 IEEE*, 2005, pp. 466-469.
- [40] F. Colombel, X. Castel, M. Himdi, G. Legeay, S. Vigneron, and E. MOTTA CRUZ, "Ultrathin metal layer, ITO film and ITO/Cu/ITO multilayer towards transparent antenna," *IET science, measurement & technology*, vol. 3, pp. 229-234, 2009.
- [41] T. W. Turpin and R. Baktur, "Meshed patch antennas integrated on solar cells," *IEEE Antennas and Wireless Propagation Letters*, vol. 8, pp. 693-696, 2009.
- [42] G. Clasen and R. Langley, "Meshed patch antennas," *IEEE Transactions on Antennas and Propagation*, vol. 52, pp. 1412-1416, 2004.

- [43] N. M. Ali, N. Misran, M. Mansor, and M. Jamlos, "Transparent solar antenna of 28 GHz using transparent conductive oxides (TCO) thin film," in *Journal of Physics: Conference Series*, 2017, p. 012036.
- [44] Z. Meng, H. Peng, C. Wu, J. Li, S. Xiong, C. F. Qiu, *et al.*, "Room temperature deposition of thin-film indium-tin oxide on micro-fabricated color filters and its application to flat-panel displays," *Guangdianzi Jiguang/Journal of Optoelectronics Laser*, vol. 16, p. 140, 2005.
- [45] J. Hautcoeur, L. Talbi, K. Hettak, and M. Nedil, "60 GHz optically transparent microstrip antenna made of meshed AuGL material," *IET Microwaves, Antennas & Propagation*, vol. 8, pp. 1091-1096, 2014.
- [46] J. Van De Groep, P. Spinelli, and A. Polman, "Transparent conducting silver nanowire networks," *Nano letters*, vol. 12, pp. 3138-3144, 2012.
- [47] N. Durán, P. D. Marcato, O. L. Alves, G. I. De Souza, and E. Esposito, "Mechanistic aspects of biosynthesis of silver nanoparticles by several *Fusarium oxysporum* strains," *Journal of nanobiotechnology*, vol. 3, p. 8, 2005.
- [48] Y. Zhu, S. Murali, W. Cai, X. Li, J. W. Suk, J. R. Potts, *et al.*, "Graphene and graphene oxide: synthesis, properties, and applications," *Advanced materials*, vol. 22, pp. 3906-3924, 2010.
- [49] M. Neek-Amal and F. Peeters, "Lattice thermal properties of graphane: thermal contraction, roughness, and heat capacity," *Physical Review B*, vol. 83, p. 235437, 2011.
- [50] C. Zhou, S. Chen, J. Lou, J. Wang, Q. Yang, C. Liu, *et al.*, "Graphene's cousin: the present and future of graphane," *Nanoscale research letters*, vol. 9, p. 26, 2014.
- [51] J. C. Garcia, D. B. de Lima, L. V. Assali, and J. F. Justo, "Group IV graphene-and graphane-like nanosheets," *The Journal of Physical Chemistry C*, vol. 115, pp. 13242-13246, 2011.

- [52] Y.-E. Yang, Y.-R. Yang, and X.-H. Yan, "Universal optical properties of graphane nanoribbons: a first-principles study," *Physica E: Low-Dimensional Systems and Nanostructures*, vol. 44, pp. 1406-1409, 2012.
- [53] A. R. Madaria, A. Kumar, F. N. Ishikawa, and C. Zhou, "Uniform, highly conductive, and patterned transparent films of a percolating silver nanowire network on rigid and flexible substrates using a dry transfer technique," *Nano Research*, vol. 3, pp. 564-573, 2010.
- [54] Y. Sun, "Silver nanowires—unique templates for functional nanostructures," *Nanoscale*, vol. 2, pp. 1626-1642, 2010.
- [55] C.-H. Liu and X. Yu, "Silver nanowire-based transparent, flexible, and conductive thin film," *Nanoscale research letters*, vol. 6, p. 75, 2011.
- [56] S. De and J. N. Coleman, "Are there fundamental limitations on the sheet resistance and transmittance of thin graphene films?," *Acs Nano*, vol. 4, pp. 2713-2720, 2010.
- [57] H.-Z. Geng, K. K. Kim, K. P. So, Y. S. Lee, Y. Chang, and Y. H. Lee, "Effect of acid treatment on carbon nanotube-based flexible transparent conducting films," *Journal of the American Chemical Society*, vol. 129, pp. 7758-7759, 2007.
- [58] R. V. Gorbachev, A. S. Mayorov, A. K. Savchenko, D. W. Horsell, and F. Guinea, "Conductance of pnp graphene structures with "Air-Bridge" top gates," *Nano letters*, vol. 8, pp. 1995-1999, 2008.
- [59] A. K. Geim and K. S. Novoselov, "The rise of graphene," *Nature materials*, vol. 6, pp. 183-191, 2007.
- [60] W. Choi, I. Lahiri, R. Seelaboyina, and Y. S. Kang, "Synthesis of graphene and its applications: a review," *Critical Reviews in Solid State and Materials Sciences*, vol. 35, pp. 52-71, 2010.

- [61] B. Gharekhanlou, S. Tousaki, and S. Khorasani, "Bipolar transistor based on graphane," in *Journal of Physics: Conference Series*, 2010, p. 012061.
- [62] Q. Jiwei, L. Yudong, Y. Ming, W. Qiang, C. Zongqiang, P. Jingyang, *et al.*, "Fabrication of nanowire network AAO and its application in SERS," *Nanoscale research letters*, vol. 8, p. 495, 2013.
- [63] C. Mias, C. Tsakonas, N. Prountzos, D. Koutsogeorgis, S. Liew, C. Oswald, *et al.*, "Optically transparent microstrip antennas," in *Antennas for Automotives (Ref. No. 2000/002), IEE Colloquium on*, 2000, pp. 8/1-8/6.
- [64] N. Guan, H. Furuya, D. Delaune, and K. Ito, "Antennas made of transparent conductive films," *PIERS online*, vol. 4, pp. 116-120, 2008.
- [65] A. Katsounaros, Y. Hao, N. Collings, and W. Crossland, "Optically transparent ultra-wideband antenna," *Electronics letters*, vol. 45, pp. 722-723, 2009.
- [66] N. J. Kirsch, N. A. Vacirca, E. E. Plowman, T. P. Kurzweg, A. K. Fontecchio, and K. R. Dandekar, "Optically transparent conductive polymer RFID meandering dipole antenna," in *2009 IEEE International Conference on RFID*, 2009.
- [67] T. Peter, Y. Sun, T. Yuk, H. AbuTarboush, R. Nilavalan, and S. Cheung, "Miniature transparent UWB antenna with tunable notch for green wireless applications," in *Antenna Technology (iWAT), 2011 International Workshop on*, 2011, pp. 259-262.
- [68] T. Peter, R. Nilavalan, H. F. AbuTarboush, and S. Cheung, "A novel technique and soldering method to improve performance of transparent polymer antennas," *IEEE Antennas and Wireless Propagation Letters*, vol. 9, pp. 918-921, 2010.
- [69] T. Yasin, R. Baktur, and C. Furse, "A study on the efficiency of transparent patch antennas designed from conductive oxide films," in *Antennas and Propagation (APSURSI), 2011 IEEE International Symposium on*, 2011, pp. 3085-3087.

- [70] S. Hong, S. H. Kang, Y. Kim, and C. W. Jung, "Transparent and Flexible Antenna for Wearable Glasses Applications," *IEEE Transactions on Antennas and Propagation*, vol. 64, pp. 2797-2804, 2016.
- [71] Y. Kim, C. Lee, S. Hong, C. W. Jung, and Y. Kim, "Design of transparent multilayer film antenna for wireless communication," *Electronics Letters*, vol. 51, pp. 12-14, 2014.
- [72] M. R. Haraty, M. Naser-Moghadasi, A. A. Lotfi-Neyestanak, and A. Nikfarjam, "Improving the Efficiency of Transparent Antenna Using Gold Nanolayer Deposition," *IEEE Antennas and Wireless Propagation Letters*, vol. 15, pp. 4-7, 2016.
- [73] S. Hong, Y. Kim, and C. W. Jung, "Transparent Microstrip Patch Antennas With Multilayer and Metal-Mesh Films," *IEEE Antennas and Wireless Propagation Letters*, vol. 16, pp. 772-775, 2017.
- [74] Q. Li, S. Cheung, D. Wu, and T. Yuk, "Optically Transparent Dual-Band MIMO Antenna Using Micro-Metal Mesh Conductive Film for WLAN System," *IEEE Antennas and Wireless Propagation Letters*, vol. 16, pp. 920-923, 2017.
- [75] T. Peter, R. Nilavalan, and S. Cheung, "A Novel Transparent TSA for Laptop and UWB Applications," *PIERS Proceedings, Kuala Lumpur, MALAYSIA*, 2012.
- [76] M. Malek, S. Hakimi, S. A. Rahim, and A. Evizal, "Dual-band CPW-fed transparent antenna for active RFID tags," *IEEE Antennas and Wireless Propagation Letters*, vol. 14, pp. 919-922, 2015.
- [77] S. Sheikh, M. Shokooh-Saremi, and M.-M. Bagheri-Mohagheghi, "Transparent microstrip patch antenna based on fluorine-doped tin oxide deposited by spray pyrolysis technique," *IET Microwaves, Antennas & Propagation*, vol. 9, pp. 1221-1229, 2015.
- [78] (2017). *Guide To Composite Materials*. Available: <http://www.netcomposites.com/education.asp?sequence=2>

- [79] A. D. McNaught and A. D. McNaught, *Compendium of chemical terminology* vol. 1669: Blackwell Science Oxford, 1997.
- [80] D. Pathania and D. Singh, "A review on electrical properties of fiber reinforced polymer composites," *International journal of theoretical & applied sciences*, vol. 1, pp. 34-37, 2009.
- [81] M. Mrazova, "Advanced composite materials of the future in aerospace industry," *Incas bulletin*, vol. 5, p. 139, 2013.
- [82] J. HINRICHSSEN, "Airbus A380: Requirements for the selection of materials and manufacturing technologies," *ATB Métallurgie*, vol. 41, pp. 24-30, 2001.
- [83] P. Jerome, "Composite materials in the airbus A380-from history to future," 2001.
- [84] R. R. d. Assis and I. Bianchi, "Analysis of microstrip antennas on carbon fiber composite material," *Journal of Microwaves, Optoelectronics and Electromagnetic Applications*, vol. 11, pp. 154-161, 2012.
- [85] B. Karthikeyan, S. Ramanathan, and V. Ramakrishnan, "Thermo physical property measurement of metal-matrix composites," *Materials & Design*, vol. 31, pp. S82-S86, 2010.
- [86] E. Mangino, J. Carruthers, and G. Pitarresi, "The future use of structural composite materials in the automotive industry," *International Journal of vehicle design*, vol. 44, pp. 211-232, 2007.
- [87] M. Won, T. Park, and S. H. Son, "Toward Mitigating Phantom Jam Using Vehicle-to-Vehicle Communication," *IEEE Transactions on Intelligent Transportation Systems*, vol. 18, pp. 1313-1324, 2017.

- [88] L. Zhang, H. Ma, D. Shi, P. Wang, G. Cai, and X. Liu, "Reliability Oriented Modeling and Analysis of Vehicular Power Line Communication for Vehicle to Grid (V2G) Information Exchange system," *IEEE Access*, 2017.
- [89] E. Salernitano and C. Migliaresi, "Composite materials for biomedical applications: a review," *Journal of Applied Biomaterials & Biomechanics*, vol. 1, pp. 3-18, 2003.
- [90] M. Drewry and G. Georgiou, "A review of NDT techniques for wind turbines," *Insight-Non-Destructive Testing and Condition Monitoring*, vol. 49, pp. 137-141, 2007.
- [91] B. Suddell, "Industrial fibres: recent and current developments," in *Symposium on Natural Fibres*, 2008.
- [92] J. L. Wang, "Application of Composite Materials on Sports Equipments," in *Applied Mechanics and Materials*, 2012, pp. 903-906.
- [93] F. Froes, "Is the use of advanced materials in sports equipment unethical?," *JOM Journal of the Minerals, Metals and Materials Society*, vol. 49, pp. 15-19, 1997.
- [94] M. Lila, F. Kumar, and S. Sharma, "Composites from waste for civil engineering applications," *i-Manager's Journal on Material Science*, vol. 1, p. 1, 2013.
- [95] H. Rmili, J. L. Miane, H. Zangar, and T. Olinga, "Design of microstrip-fed proximity-coupled conducting-polymer patch antenna," *Microwave and Optical Technology Letters*, vol. 48, pp. 655-660, 2006.
- [96] Y. Bayram, Y. Zhou, J. Volakis, B. Shim, and N. Kotov, "Conductive textiles and polymer-ceramic composites for novel load bearing antennas," in *2008 IEEE Antennas and Propagation Society International Symposium*, 2008, pp. 1-4.

- [97] L. Yang, A. Rida, R. Vyas, and M. M. Tentzeris, "RFID tag and RF structures on a paper substrate using inkjet-printing technology," *IEEE Transactions on Microwave Theory and Techniques*, vol. 55, pp. 2894-2901, 2007.
- [98] R. Tellakula, V. Varadan, T. Shami, and G. Mathur, "Carbon fiber and nanotube based composites with polypyrrole fabric as electromagnetic absorbers," *Smart materials and structures*, vol. 13, p. 1040, 2004.
- [99] I. M. De Rosa, F. Sarasini, M. S. Sarto, and A. Tamburrano, "EMC impact of advanced carbon fiber/carbon nanotube reinforced composites for next-generation aerospace applications," *IEEE Transactions on Electromagnetic Compatibility*, vol. 50, pp. 556-563, 2008.
- [100] C. L. Holloway, M. S. Sarto, and M. Johansson, "Analyzing carbon-fiber composite materials with equivalent-layer models," *IEEE Transactions on Electromagnetic Compatibility*, vol. 47, pp. 833-844, 2005.
- [101] W. Bauhofer and J. Z. Kovacs, "A review and analysis of electrical percolation in carbon nanotube polymer composites," *Composites Science and Technology*, vol. 69, pp. 1486-1498, 2009.
- [102] R. K. Challa, D. Kajfez, V. Demir, J. R. Gladden, and A. Z. Elsherbeni, "Characterization of multiwalled carbon nanotube (MWCNT) composites in a waveguide of square cross section," *IEEE Microwave and Wireless Components Letters*, vol. 18, pp. 161-163, 2008.
- [103] B. Hornbostel, U. Leute, P. Pötschke, J. Kotz, D. Kornfeld, P.-W. Chiu, *et al.*, "Attenuation of electromagnetic waves by carbon nanotube composites," *Physica E: Low-dimensional Systems and Nanostructures*, vol. 40, pp. 2425-2429, 2008.
- [104] C. Buccella, "Quasi-stationary analysis of the electric field in anisotropic laminated composites," *IEEE Transactions on Industry Applications*, vol. 35, pp. 1296-1305, 1999.

- [105] Y. Huang, N. Li, Y. Ma, F. Du, F. Li, X. He, *et al.*, "The influence of single-walled carbon nanotube structure on the electromagnetic interference shielding efficiency of its epoxy composites," *Carbon*, vol. 45, pp. 1614-1621, 2007.
- [106] I. D. Rosca and S. V. Hoa, "Highly conductive multiwall carbon nanotube and epoxy composites produced by three-roll milling," *Carbon*, vol. 47, pp. 1958-1968, 2009.
- [107] A. Mehdipour, I. D. Rosca, A. Sebak, C. Trueman, and S. Hoa, "Advanced carbon-fiber composite materials for RFID tag antenna applications," *Appl. Comput. Electromagn. Soc.(ACES) J*, vol. 25, 2010.
- [108] A. Galehdar, W. S. Rowe, K. Ghorbani, P. J. Callus, S. John, and C. H. Wang, "The effect of ply orientation on the performance of antennas in or on carbon fiber composites," *Progress In Electromagnetics Research*, vol. 116, pp. 123-136, 2011.
- [109] A. Mehdipour, C. Trueman, A. Sebak, and S. Hoa, "Carbon-fiber composite T-match folded bow-tie antenna for RFID applications," in *2009 IEEE Antennas and Propagation Society International Symposium*, 2009, pp. 1-4.
- [110] A. Galehdar, P. J. Callus, and K. Ghorbani, "A novel method of conductivity measurements for carbon-fiber monopole antenna," *IEEE Transactions on Antennas and Propagation*, vol. 59, pp. 2120-2126, 2011.
- [111] M. S. Sarto, "Hybrid MFIE/FDTD analysis of the shielding effectiveness of a composite enclosure excited by a transient plane wave," *IEEE transactions on magnetics*, vol. 36, pp. 946-950, 2000.
- [112] A. Mehdipour, A.-R. Sebak, C. W. Trueman, I. D. Rosca, and S. V. Hoa, "Reinforced continuous carbon-fiber composites using multi-wall carbon nanotubes for wideband antenna applications," *IEEE Transactions on Antennas and Propagation*, vol. 58, pp. 2451-2456, 2010.
- [113] A. Mehdipour, I. D. Rosca, A.-R. Sebak, C. W. Trueman, and S. V. Hoa, "Full-composite fractal antenna using carbon nanotubes for multiband

- wireless applications," *IEEE Antennas and Wireless Propagation Letters*, vol. 9, pp. 891-894, 2010.
- [114] L. Manac'h, X. Castel, and M. Himdi, "Microwave performance of a carbon composite antenna," in *Microwave Conference (EuMC), 2013 European*, 2013, pp. 770-773.
- [115] S. S. Bhore, "Formulation and Evaluation of Resistive Inks for Applications in Printed Electronics," 2012.
- [116] J. E. Neff, "Investigation of the effects of process parameters on performance of gravure printed ITO on flexible substrates," Citeseer, 2009.
- [117] S. S. Joshi, "Evaluation of Silver/Graphite Ink Blends for Use in Printed Electronics," 2011.
- [118] A. Karwa, "Printing studies with conductive inks and exploration of new conducting polymer compositions," 2006.
- [119] N. D. Sankır, "Flexible electronics: materials and device fabrication," Virginia Polytechnic Institute and State University, 2005.
- [120] K. Eiroma, L. Hakola, J. Hast, A. Maaninen, and J. Petäjä, "UV Curing for Printed."
- [121] J. R. Greer and R. A. Street, "Thermal cure effects on electrical performance of nanoparticle silver inks," *Acta Materialia*, vol. 55, pp. 6345-6349, 2007.
- [122] K. Gilleo, *Polymer thick film: today's emerging technology for a clean environment tomorrow*: Springer Science & Business Media, 1996.
- [123] S.-S. Yoon and D.-Y. Khang, "Room-temperature chemical welding and sintering of metallic nanostructures by capillary condensation," *Nano letters*, vol. 16, pp. 3550-3556, 2016.

- [124] F. P. Bowden and D. Tabor, *The friction and lubrication of solids* vol. 1: Oxford university press, 2001.
- [125] E. Charlaix and M. Ciccotti, "Capillary condensation in confined media. handbook of nanophysics: Principles and methods. ed. klaus sattler," ed: CRC Press, 2010.
- [126] D. S. Hecht, L. Hu, and G. Irvin, "Emerging transparent electrodes based on thin films of carbon nanotubes, graphene, and metallic nanostructures," *Advanced materials*, vol. 23, pp. 1482-1513, 2011.
- [127] Y. Kawahara, S. Hodges, B. S. Cook, C. Zhang, and G. D. Abowd, "Instant inkjet circuits: lab-based inkjet printing to support rapid prototyping of UbiComp devices," in *Proceedings of the 2013 ACM international joint conference on Pervasive and ubiquitous computing*, 2013, pp. 363-372.
- [128] Ford, M. *Can the 'silver bullet' of printing revolutionize electronics? Digital Biz, CNN, December 10th, 2009.* Available: <http://edition.cnn.com/2009/TECH/12/09/electronics.printer.xerox/>
- [129] Dimatix *Dimatix Material Printer DMP-2831.* Available: http://www.fujifilmusa.com/products/industrial_inkjet_printheads/deposition-products/dmp-2800/
- [130] A. Mansour, N. Shehata, B. Hamza, and M. Rizk, "Efficient design of flexible and low cost paper-based inkjet-printed antenna," *International Journal of Antennas and Propagation*, vol. 2015, 2015.
- [131] *Dimatix printer Fuji series price.* Available: <https://www.labmakelaar.com/eng/detail/other/other-equipment/8405-dimatix-printer-van-fuji/8405>
- [132] *Dimatix Material Printer DMP-2831.* Available: http://www.fujifilmusa.com/products/industrial_inkjet_printheads/deposition-products/dmp-2800/

- [133] B. S. Cook and A. Shamim, "Inkjet printing of novel wideband and high gain antennas on low-cost paper substrate," *IEEE Transactions on Antennas and Propagation*, vol. 60, pp. 4148-4156, 2012.
- [134] A. R. Maza, B. Cook, G. Jabbour, and A. Shamim, "Paper-based inkjet-printed ultra-wideband fractal antennas," *IET microwaves, antennas & propagation*, vol. 6, pp. 1366-1373, 2012.
- [135] S. Kim, Y.-J. Ren, H. Lee, A. Rida, S. Nikolaou, and M. M. Tentzeris, "Monopole antenna with inkjet-printed EBG array on paper substrate for wearable applications," *IEEE Antennas and wireless propagation letters*, vol. 11, pp. 663-666, 2012.
- [136] S. Kim, Y. Kawahara, A. Georgiadis, A. Collado, and M. M. Tentzeris, "Low-cost inkjet-printed fully passive RFID tags for calibration-free capacitive/haptic sensor applications," *IEEE Sensors Journal*, vol. 15, pp. 3135-3145, 2015.
- [137] G. A. Casula, G. Montisci, P. Maxia, G. Valente, A. Fanti, and G. Mazzarella, "A low-cost dual-band CPW-Fed printed LPDA for wireless communications," *IEEE Antennas and Wireless Propagation Letters*, vol. 15, pp. 1333-1336, 2016.
- [138] V. Kale and D. Patil, "Antenna Simulation Tools and Designing of Log Periodic Dipole Antenna with CST Studio."
- [139] *Agilent 85070E Dielectric Probe Kit 200 MHz to 50 GHz*. Available: <http://www.imperial.ac.uk/media/imperial-college/research-centres-and-groups/centre-for-bio-inspired-technology/11949699.PDF>
- [140] I. Inc., "IEEE Standard Test Procedures for Antennas," ed: distributed by Wiley-Interscience, 1979.
- [141] A. B. Constantine, *Antenna Theory*, Third Edition ed. USA: Wiley-Interscience, 2005.

- [142] Y. Sun, S. W. Cheung, and T. I. Yuk, "Design of a textile ultra-wideband antenna with stable performance for body-centric wireless communications," *IET Microwaves, Antennas & Propagation*, vol. 8, pp. 1363-1375, 2014.
- [143] P. B. Samal, P. J. Soh, and G. A. Vandebosch, "UWB all-textile antenna with full ground plane for off-body WBAN communications," *IEEE Transactions on Antennas and Propagation*, vol. 62, pp. 102-108, 2014.
- [144] P. J. Soh, G. A. Vandebosch, S. L. Ooi, and N. H. M. Rais, "Design of a broadband all-textile slotted PIFA," *IEEE Transactions on Antennas and Propagation*, vol. 60, pp. 379-384, 2012.
- [145] M. Klemm and G. Troester, "Textile UWB antennas for wireless body area networks," *IEEE Transactions on Antennas and Propagation*, vol. 54, pp. 3192-3197, 2006.
- [146] J. Hautcoeur, X. Castel, F. Colombel, R. Benzerga, M. Himdi, G. Legeay, *et al.*, "Transparency and electrical properties of meshed metal films," *Thin Solid Films*, vol. 519, pp. 3851-3858, 2011.
- [147] D. Corning. Available:
<http://www.dowcorning.com/applications/search/products/Details.aspx?prod=01064291>
- [148] D. C. Duffy, J. C. McDonald, O. J. Schueller, and G. M. Whitesides, "Rapid prototyping of microfluidic systems in poly (dimethylsiloxane)," *Analytical chemistry*, vol. 70, pp. 4974-4984, 1998.
- [149] D. C. Duffy, O. J. Schueller, S. T. Brittain, and G. M. Whitesides, "Rapid prototyping of microfluidic switches in poly (dimethyl siloxane) and their actuation by electro-osmotic flow," *Journal of Micromechanics and Microengineering*, vol. 9, p. 211, 1999.
- [150] S. Satyanarayana, R. N. Karnik, and A. Majumdar, "Stamp-and-stick room-temperature bonding technique for microdevices," *Journal of Microelectromechanical Systems*, vol. 14, pp. 392-399, 2005.

- [151] G. Suresh and L. Jayakumari, "Evaluating the mechanical properties of E-Glass fiber/carbon fiber reinforced interpenetrating polymer networks," *Polímeros*, vol. 25, pp. 49-57, 2015.
- [152] R. FANGUEIRO and F. SOUTINHO, "University of Minho, Portugal," *Fibrous and Composite Materials for Civil Engineering Applications*, p. 62, 2011.
- [153] S. M. Lee, *Handbook of Composite Reinforcements*. USA: Wiley & Sons, 1993.
- [154] A. composite. (2016). *Vacuum Infusion* Available:
<https://www.amtcomposites.co.za/sites/default/files/media/howto/Gurit%20Guide%20to%20Infusion%20Part%202.pdf>
- [155] G. Shaker, S. Safavi-Naeini, N. Sangary, and M. M. Tentzeris, "Inkjet printing of ultrawideband (UWB) antennas on paper-based substrates," *IEEE Antennas and Wireless Propagation Letters*, vol. 10, pp. 111-114, 2011.
- [156] "Synthesis and Simulation Converge in CST STUDIO SUITE," *Microwave Journals*, January 2015.
- [157] F. Hirtenfelder, "Effective antenna simulations using CST MICROWAVE STUDIO®," in *Antennas, 2007. INICA'07. 2nd International ITG Conference on*, 2007, pp. 239-239.
- [158] F. Demming-Janssen and W. Koch, "3D Field simulation of sparse arrays using various solver techniques within CST MICROWAVE STUDIO®," in *Radar Conference, 2006. EuRAD 2006. 3rd European*, 2006, pp. 80-83.