

STATISTICAL TIME DIVISION MULTIPLEXING ARCHITECTURES AND DESIGN

A2 15 mV

Asadullah Shah
Asadullah Shaikh
Muniba Shaikh
Zeeshan Bhatti
Nuha Abdullah Zammarh
Dini Oktarina Dwi Handayani
Zoya Shah

200mV

20mV



0.1 500ns

IIUM Press
INTERNATIONAL ISLAMIC UNIVERSITY MALAYSIA

STATISTICAL TIME DIVISION MULTIPLEXING ARCHITECTURES AND DESIGN

Editors

Asadullah Shah

Asadullah Shaikh

Muniba Shaikh

Zeeshan Bhatti

Nuha Abdullah Zammarh

Dini Oktarina Dwi Handayani

Zoya Shah



IIUM Press

Published by:

IIUM Press

International Islamic University Malaysia

First Edition, 2011

©IIUM Press, IIUM

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, electronic, mechanical, photocopying, recording, or otherwise, without any prior written permission of the publisher.

Perpustakaan Negara Malaysia

Cataloguing-in-Publication Data

Asadullah Shah

**Statistical Time Division Multiplexing Architecture and Design / Asadullah Shah
... [et al.].**

ISBN: 978-967-418-190-1

Member of Majlis Penerbitan Ilmiah Malaysia – MAPIM
(Malaysian Scholarly Publishing Council)

Printed by:

IIUM PRINTING SDN. BHD.
No.1, Jalan Industri Batu Caves 1/3
Taman Perindustrian Batu Caves
Batu Caves Centre Point
68100 Batu Caves
Selangor Darul Ehsan

10. Discontinuous Transmission and Multiplexing

Asadullah Shah, Muniba Shaikh
Department of Computer Science,

Kulliyah of Information and Communication Technology,

International Islamic University of Malaysia,

Malaysia

10.0 Abstract

Discontinuous Transmission (DTX) is a concept used in some mobile standards, mostly in Groupe Special Mobile (GSM) systems. In DTX systems, Voice Activity Detection (VAD) and comfort noise are essential elements. The usage of DTX in the systems allows transmissions during activity periods and remains silent during non-activities. This chapter is dedicated for DTX and VAD, their usage in STDMA designs.

The DTX concept has been implemented for the Groupe Special Mobile (GSM) standard, where VAD and comfort noise are the essential elements of the DTX system. When DTX is in operation, the transmitter is switched off during periods of silence. This increases system efficiency by reducing (a) the co-channel interference and (b) also reduces transmitter power consumption (an important consideration for hand-held portables). DTX comprises basically of two parts, a VAD at the transmitter to detect the speech from silences, and a comfort noise generator at the receiver. Comfort noise is generated by the receiver when DTX has switched the transmitter off. The purpose of this is to fill the gaps of silences with low level noise normally generated from normal distribution and scale it to eliminate the unpleasant subjective effect of switching between speech in high noise, and silence. The block diagram of figure shows the DTX system concept.