



# A less conservative criterion for stability analysis of linear systems with time-varying delay

A. Farnam<sup>a</sup>, R. Mahboobi Efsanjani<sup>b,\*</sup> and M. Farsi<sup>b</sup>

a. *SYSTeMS Research Group, Ghent University, Ghent, Belgium.*

b. *Department of Electrical Engineering, Sahand University of Technology, Tabriz, Iran.*

Received 5 April 2014; received in revised form 21 January 2015; accepted 22 August 2015

## KEYWORDS

Stability analysis;  
Interval time-varying  
delay;  
Linear Matrix  
Inequalities (LMIs);  
Maximum Allowable  
Delay Bound  
(MADB).

**Abstract.** This paper investigates the problem of stability analysis for linear systems with time-varying delay. To reduce the conservativeness of sufficient stability conditions, a novel augmented Lyapunov-Krasovskii Functional (LKF) which includes quadratic terms of double-integral phrases is introduced; as well, the technique of free-weighting matrices with new slack variables is employed; moreover, a tighter integral inequality is derived for bounding the cross-product terms in the derivative of chosen LKF. Numerical examples are presented to illustrate the superiority of the proposed method compared to some of the previously developed approaches.

© 2015 Sharif University of Technology. All rights reserved.

## 1. Introduction

Variable time-delays are encountered in many practical systems, especially in the processes that involve transportation or propagation of material and data such as chemical reactors, combustion engines, and networked control systems. The presence of time-delay in the dynamic equations of the system brings important challenges in its stability analysis and stabilization. Therefore, recently, considerable attention has been attracted to the analysis and control of time-delay systems [1-8].

Most of the time-domain stability criteria for systems with time-varying delay are based primarily on the Lyapunov-Krasovskii Theorem, combined with the model transformation schemes and bounding techniques for the cross-terms in the derivative of the Lyapunov-Krasovskii Functional (LKF) [1]. In order to obtain less conservative delay-dependent conditions,

more efficient augmented LKFs were constructed; besides more accurate bounding methods were developed for the cross-terms in the derivative of the energy functional [9,10]. In [11], delay-dependent stability criteria were derived for linear systems with a constant discrete delay, wherein a new simple LKF was introduced by uniformly dividing the delay interval into multiple segments and choosing different weight matrices corresponding to each segment. The idea of [11] was generalized in [12] to obtain less conservative stability conditions for linear systems with time-varying delay in which the delay interval is decomposed into equidistant subintervals; then, choosing different matrix pairs for each subinterval, a new LKF was constructed. In [13], Wirtinger inequality was used for the first time to reduce the conservatism in computing the derivative of LKFs. This more accurate integral inequality depends not only on the state, but also on the integral of the state over the delay interval.

The method of free-weighting matrices that injects additional variables to add extra-degree of freedom in the sufficient stability condition made an important progress in delay-dependent stability criteria of systems with time-varying delay [14,15]. The stability

\*. *Corresponding author. Tel.: +98 41 33459356;  
Fax: +98 41 33444322  
E-mail address: mahboobi@sut.ac.ir (R. Mahboobi Efsanjani)*

measures were further improved by involving novel slack matrices in the derivative of energy functionals. On the other hand, the technique of free-weighting matrices was combined with the conventional ideas, such as descriptor transformation approach and augmented vectors method, to further reduce the conservativeness of stability conditions [16,17]. But, in some cases, using functional parameters and/or free-weighting matrices leads to complex stability criteria. Therefore, in order to reduce computational burden, a simplified criterion was obtained in [18].

Most of the mentioned methods, such as [19] utilize LKFs, include double-integral terms. For the first time, triple-integral terms were added to the LKF in [20] to enhance stability criterion for the constant delay system. This type of augmented LKF was used to develop the stability measure for the linear systems with time varying-delay in [21]. It is worth noting that some types of LKFs yield infinite dimensional LMIs. That is why many authors have considered the simple form of LKFs and thus derived simpler, but more conservative, conditions [22].

In [23], delay-range-dependent stability criterion for linear systems with time-varying delay was derived, where a new estimation method, along with the convex combination and delay partitioning was employed to obtain a less conservative stability condition. More recently, the stability of a linear system with interval time-varying delay was investigated in [24], where a new LKF was presented and some novel integral inequalities were established for bounding the cross terms appearing in the derivative of the chosen LKF. Moreover, the matrix-based quadratic convex approach was used to ensure both the positive definiteness of LKF and negative definiteness of its derivative.

This paper presents an improved stability condition for systems with time-varying delay compared to some of the currently available conditions in literature. To develop this novel condition, a new type of LKF containing quadratic phrases of double-integral terms is introduced and the method of free-weighting matrices with novel slack variables is utilized. Moreover, a tighter integral inequality is derived to bound cross-terms in the derivative of LKF. Efficiency of the suggested approach is demonstrated by two illustrative examples. Note that since less conservativeness of the proposed stability condition is the consequence of increasing the number of matrix parameters in the derived LMIs, more computation time is needed in the testing procedure.

This paper is organized as follows: The problem is described in Section 2. Section 3 introduces the sufficient condition for stability analysis of the linear system with time-varying delay. In Section 4, two numerical examples are presented to demonstrate the advantages of the proposed method compared to some

of the existing approaches. Section 5 concludes the paper.

Notations: In this paper,  $R$  denotes real numbers set. The symbol  $*$  stands for symmetric block in the symmetric matrices.  $I$  is identity matrix with appropriate dimensions. The notation  $P > 0$  ( $P \geq 0$ ) means that  $P$  is real symmetric and positive definite (positive semidefinite). The superscript  $T$  stands for matrix transposition.  $\text{col}\{\}$  shows column vector of the elements in the bracket.

## 2. System description and preliminaries

The linear system with time-varying delay is described as follows:

$$\begin{aligned} \dot{x}(t) &= Ax(t) + A_1x(t - \eta(t)), \quad t \geq 0, \\ x(t) &= \varphi(t), \quad t \in [-\eta_2, 0), \end{aligned} \tag{1}$$

where  $x(t) \in R^n$  is the state vector;  $A$  and  $A_1$  are system matrices with appropriate dimensions; and  $\eta(t)$  denotes time-varying delay and satisfies:

$$0 \leq \eta_1 \leq \eta(t) \leq \eta_2, \tag{2}$$

where,  $\eta_1 < \eta_2$  are the constant upper and lower bounds of time-varying delay.

The problem is to find a new delay-dependent condition in terms of linear matrix inequalities to investigate the asymptotic stability of the system (Eqs. (1)) with the delay satisfying Relation (2). Before proceeding further, inspired by Jensen’s inequality in [23], the following lemma is extracted.

**Lemma 1.** Suppose  $0 \leq \eta_1 \leq \eta_2$  and  $\omega(t) \in R^n$ ; for any positive definite matrix  $Z \in R^{n \times n}$ , the following inequality holds:

$$\begin{aligned} &(\eta_2^2 - \eta_1^2) \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t \omega^T(\alpha) Z \omega(\alpha) d\alpha d\beta \\ &\geq 2 \left( \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t \omega(\alpha) d\alpha d\beta \right)^T \\ &\quad Z \left( \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t \omega(\alpha) d\alpha d\beta \right). \end{aligned}$$

**Proof:** Regarding the Schur complement, the following holds:

$$\begin{bmatrix} \omega^T(\alpha) Z \omega(\alpha) & \omega^T(\alpha) \\ \omega(\alpha) & Z^{-1} \end{bmatrix} \geq 0,$$



$$\hat{\Sigma}_{44} = Q_{122} + \eta_1 T_{122} + \eta_{21} T_{212} + \frac{\eta_1^4}{4} Z_{122} + \frac{(\eta_2^2 - \eta_1^2)^2}{4} Z_{222},$$

$$\hat{\Sigma}_{12} = P_{24}^T - P_{14} + P_{15},$$

$$\hat{\Sigma}_{13} = P_{34}^T - P_{15},$$

$$\hat{\Sigma}_{18} = P_{44} - P_{16} + \eta_1 Z_{122},$$

$$\hat{\Sigma}_{19} = P_{45} - P_{17} + \eta_{21} Z_{222},$$

$$\hat{\Sigma}_{110} = P_{46} - \eta_1 Z_{112}^T,$$

$$\hat{\Sigma}_{111} = P_{47} - \eta_{21} Z_{212}^T,$$

$$\hat{\Sigma}_{23} = -P_{34}^T + P_{35}^T - P_{25},$$

$$\hat{\Sigma}_{24} = -P_{12}^T + \eta_1 P_{26} + \eta_{21} P_{27},$$

$$\hat{\Sigma}_{25} = -Q_{112} + Q_{212},$$

$$\hat{\Sigma}_{28} = -P_{44} + P_{45}^T - P_{26},$$

$$\hat{\Sigma}_{29} = -P_{25} + P_{55} - P_{27},$$

$$\hat{\Sigma}_{210} = -P_{46} + P_{56},$$

$$\hat{\Sigma}_{211} = -P_{47} + P_{57},$$

$$\hat{\Sigma}_{33} = -P_{35}^T - P_{35} - Q_{211} - X_2,$$

$$\hat{\Sigma}_{34} = P_{13}^T + \eta_1 P_{36} + \eta_{21} P_{37},$$

$$\hat{\Sigma}_{36} = P_{33} - Q_{212},$$

$$\hat{\Sigma}_{38} = -P_{45}^T - P_{36},$$

$$\hat{\Sigma}_{39} = -P_{55} - P_{37},$$

$$\hat{\Sigma}_{48} = P_{14} + \eta_1 P_{46}^T + \eta_{21} P_{47}^T,$$

$$\hat{\Sigma}_{49} = P_{15} + \eta_1 P_{56}^T + \eta_{21} P_{57}^T,$$

$$\hat{\Sigma}_{410} = P_{16} + \eta_1 P_{66} + \eta_{21} P_{67}^T,$$

$$\hat{\Sigma}_{411} = P_{17} + \eta_1 P_{67} + \eta_{21} P_{77},$$

$$\hat{\Sigma}_{55} = -Q_{122} + Q_{222},$$

$$\hat{\Sigma}_{77} = -X_1 + X_2,$$

$$\hat{\Sigma}_{88} = -P_{46}^T - P_{46} - Z_{122},$$

$$\hat{\Sigma}_{89} = -P_{56}^T - P_{47},$$

$$\hat{\Sigma}_{810} = -P_{66} + Z_{112}^T,$$

$$\hat{\Sigma}_{99} = -P_{57}^T - P_{57} - Z_{222},$$

$$\hat{\Sigma}_{911} = -P_{77} + Z_{212}^T,$$

**Proof:** The LKF candidate is constructed as follows:

$$V(x_t) = V_1(x_t) + V_2(x_t) + V_3(x_t) + V_4(x_t), \quad (4)$$

$$V_1(x_t) = \xi^T(t) P \xi(t), \quad (5)$$

$$V_2(x_t) = \int_{t-\eta_1}^t \tau^T(\alpha) Q_1 \tau(\alpha) d\alpha + \int_{t-\eta_2}^{t-\eta_1} \tau^T(\alpha) Q_2 \tau(\alpha) d\alpha, \quad (6)$$

$$V_3(x_t) = \int_{-\eta_1}^0 \int_{t+\beta}^t \tau^T(\alpha) T_1 \tau(\alpha) d\alpha d\beta + \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t \tau^T(\alpha) T_2 \tau(\alpha) d\alpha d\beta, \quad (7)$$

$$V_4(x_t) = \frac{\eta_1^2}{2} \int_{-\eta_1}^0 \int_{\beta}^0 \int_{t+\theta}^t \tau^T(\alpha) Z_1 \tau(\alpha) d\alpha d\theta d\beta + \frac{(\eta_2^2 - \eta_1^2)}{2} \int_{-\eta_2}^{-\eta_1} \int_{\beta}^0 \int_{t+\theta}^t \tau^T(\alpha) Z_2 \tau(\alpha) d\alpha d\theta d\beta, \quad (8)$$

wherein, augmented vectors  $\tau(\alpha)$  and  $\xi(t)$  are defined as:

$$\tau(\alpha) = \text{col}\{x(\alpha), \dot{x}(\alpha)\},$$

and:

$$\xi(t) = \text{col} \left\{ x(t), x(t - \eta_1), x(t - \eta_2), \int_{t-\eta_1}^t x(\alpha) d\alpha, \int_{t-\eta_2}^{t-\eta_1} x(\alpha) d\alpha, \int_{-\eta_1}^0 \int_{t+\beta}^t x(\alpha) d\alpha d\beta, \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t x(\alpha) d\alpha d\beta \right\}.$$

First, time derivative of  $V(x_t)$  is computed along the trajectories of Eqs. (1) as the following:

$$\begin{aligned} \dot{V}(x_t) = & 2\xi^T(t)P(t)\xi + \tau^T(t)Q_1\tau(t) \\ & - \tau^T(t - \eta_1)Q_1\tau(t - \eta_1) \\ & + \tau^T(t - \eta_1)Q_2\tau(t - \eta_1) \\ & - \tau^T(t - \eta_2)Q_2\tau(t - \eta_2) \\ & + \tau^T(t)(\eta_1T_1 + \eta_2T_2)\tau(t) \\ & - \int_{t-\eta_1}^t \tau^T(\alpha)T_1\tau(\alpha)d\alpha \\ & - \int_{t-\eta(t)}^{t-\eta_1} \tau^T(\alpha)T_2\tau(\alpha)d\alpha \\ & - \int_{t-\eta_2}^{t-\eta(t)} \tau^T(\alpha)T_2\tau(\alpha)d\alpha \\ & + \tau^T(t) \left( \frac{\eta_1^4}{4}Z_1 + \frac{(\eta_2^2 - \eta_1^2)^2}{4}Z_2 \right) \tau(t) \\ & - \frac{\eta_1^2}{2} \int_{-\eta_1}^0 \int_{t+\beta}^t \tau^T(\alpha)Z_1\tau(\alpha)d\alpha d\beta \\ & - \frac{(\eta_2^2 - \eta_1^2)}{2} \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t \tau^T(\alpha)Z_2\tau(\alpha)d\alpha d\beta. \end{aligned}$$

Note that for any of the matrices  $Y_0, Y_1, Y_2, M, X_0, X_1,$  and  $X_2$  with appropriate dimensions, the following

equalities hold:

$$\varepsilon_1(t) = 2\zeta^T(t)Y_0 \left( x(t) - x(t - \eta_1) - \int_{t-\eta_1}^t \dot{x}(\alpha) d\alpha \right) = 0, \tag{9}$$

$$\varepsilon_2(t) = 2\zeta^T(t)Y_1 \left( x(t - \eta_1) - x(t - \eta(t)) - \int_{t-\eta(t)}^{t-\eta_1} \dot{x}(\alpha) d\alpha \right) = 0, \tag{10}$$

$$\varepsilon_3(t) = 2\zeta^T(t)Y_2 \left( x(t - \eta(t)) - x(t - \eta_2) - \int_{t-\eta_2}^{t-\eta(t)} \dot{x}(\alpha) d\alpha \right) = 0, \tag{11}$$

$$\varepsilon_4(t) = 2\zeta^T(t)M (\dot{x}(t) - Ax(t) - A_1x(t - \eta(t))) = 0, \tag{12}$$

$$\varepsilon_5(t) = x^T(t)X_0x(t) - x^T(t - \eta_1)X_0x(t - \eta_1) - 2 \int_{t-\eta_1}^t \dot{x}^T(\alpha)X_0x(\alpha)d\alpha = 0, \tag{13}$$

$$\varepsilon_6(t) = x^T(t - \eta_1)X_1x(t - \eta_1) - x^T(t - \eta(t))X_1x(t - \eta(t)) - 2 \int_{t-\eta(t)}^{t-\eta_1} \dot{x}^T(\alpha)X_1x(\alpha)d\alpha = 0, \tag{14}$$

$$\varepsilon_7(t) = x^T(t - \eta(t))X_2x(t - \eta(t)) - x^T(t - \eta_2)X_2x(t - \eta_2) - 2 \int_{t-\eta_2}^{t-\eta(t)} \dot{x}^T(\alpha)X_2x(\alpha)d\alpha = 0, \tag{15}$$

in which:

$$\zeta(t) = \text{col}\{x(t), x(t - \eta_1), x(t - \eta_2), \dot{x}(t), \dot{x}(t - \eta_1), \dot{x}(t - \eta_2), x(t - \eta(t))\}.$$

Regarding Eqs. (9)-(15) and utilizing Lemma 1, the

upper bound of  $\dot{V}(x_t)$  is written as follows:

$$\begin{aligned}
 \dot{V}(x_t) \leq & 2\xi^T(t)P\xi(t) + \tau^T(t)Q_1\tau(t) \\
 & - \tau^T(t - \eta_1)Q_1\tau(t - \eta_1) \\
 & + \tau^T(t - \eta_1)Q_2\tau(t - \eta_1) \\
 & - \tau^T(t - \eta_2)Q_2\tau(t - \eta_2) \\
 & + \tau^T(t)(\eta_1T_1 + (\eta_2 - \eta_1)T_2)\tau(t) \\
 & - \int_{t-\eta_1}^t \tau^T(\alpha)T_1\tau(\alpha)d\alpha \\
 & - \int_{t-\eta(t)}^{t-\eta_1} \tau^T(\alpha)T_2\tau(\alpha)d\alpha \\
 & - \int_{t-\eta_2}^{t-\eta(t)} \tau^T(\alpha)T_2\tau(\alpha)d\alpha \\
 & + \tau^T(t) \left( \frac{\eta_1^4}{4}Z_1 + \frac{(\eta_2^2 - \eta_1^2)^2}{4}Z_2 \right) \tau(t) \\
 & - \left[ \begin{array}{c} \int_{-\eta_1}^0 \int_{t+\beta}^t x(\alpha)d\alpha d\beta \\ \eta_1 x(t) - \int_{t-\eta_1}^t x(\alpha)d\alpha \end{array} \right]^T \\
 & \cdot \left[ \begin{array}{cc} Z_{111} & Z_{112} \\ * & Z_{122} \end{array} \right] \\
 & \cdot \left[ \begin{array}{c} \int_{-\eta_1}^0 \int_{t+\beta}^t x(\alpha)d\alpha d\beta \\ \eta_1 x(t) - \int_{t-\eta_1}^t x(\alpha)d\alpha \end{array} \right] \\
 & - \left[ \begin{array}{c} \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t x(\alpha)d\alpha d\beta \\ (\eta_2 - \eta_1)x(t) - \int_{t-\eta_2}^{t-\eta_1} x(\alpha)d\alpha \end{array} \right]^T \\
 & \cdot \left[ \begin{array}{cc} Z_{211} & Z_{212} \\ * & Z_{222} \end{array} \right] \\
 & \cdot \left[ \begin{array}{c} \int_{-\eta_2}^{-\eta_1} \int_{t+\beta}^t x(\alpha)d\alpha d\beta \\ (\eta_2 - \eta_1)x(t) - \int_{t-\eta_2}^{t-\eta_1} x(\alpha)d\alpha \end{array} \right] + \sum_{i=1}^{i=7} \varepsilon_i(t). \tag{16}
 \end{aligned}$$

On the other hand, the following inequalities are true:

$$\begin{aligned}
 & -2\zeta^T(t)\tilde{Y}_0 \int_{t-\eta_1}^t \tau(\alpha)d\alpha \\
 & \leq \eta_1\zeta^T(t)\tilde{Y}_0 \begin{bmatrix} T_{111} & T_{112} + X_0 \\ * & T_{122} \end{bmatrix}^{-1} \tilde{Y}_0^T\zeta(t) \\
 & \quad + \int_{t-\eta_1}^t \tau^T(\alpha) \begin{bmatrix} T_{111} & T_{112} + X_0 \\ * & T_{122} \end{bmatrix} \tau(\alpha)d\alpha, \\
 \tilde{Y}_0 = & [0 \quad Y_0], \tag{17}
 \end{aligned}$$

$$\begin{aligned}
 & -2\zeta^T(t)\tilde{Y}_1 \int_{t-\eta(t)}^{t-\eta_1} \tau(\alpha)d\alpha \\
 & \leq \eta_{21}\zeta^T(t)\tilde{Y}_1 \begin{bmatrix} T_{211} & T_{212} + X_1 \\ * & T_{222} \end{bmatrix}^{-1} \tilde{Y}_1^T\zeta(t) \\
 & \quad + \int_{t-\eta(t)}^{t-\eta_1} \tau^T(\alpha) \begin{bmatrix} T_{211} & T_{212} + X_1 \\ * & T_{222} \end{bmatrix} \tau(\alpha)d\alpha, \\
 \tilde{Y}_1 = & [0 \quad Y_1], \tag{18}
 \end{aligned}$$

$$\begin{aligned}
 & -2\zeta^T(t)\tilde{Y}_2 \int_{t-\eta_2}^{t-\eta(t)} \tau(\alpha)d\alpha \\
 & \leq \eta_{21}\zeta^T(t)\tilde{Y}_2 \begin{bmatrix} T_{211} & T_{212} + X_2 \\ * & T_{222} \end{bmatrix}^{-1} \tilde{Y}_2^T\zeta(t) \\
 & \quad + \int_{t-\eta_2}^{t-\eta(t)} \tau^T(\alpha) \begin{bmatrix} T_{211} & T_{212} + X_2 \\ * & T_{222} \end{bmatrix} \tau(\alpha)d\alpha, \\
 \tilde{Y}_2 = & [0 \quad Y_2]. \tag{19}
 \end{aligned}$$

Now, the upper bound of  $\dot{V}(x_t)$  is restated as follows by substituting Relations (17)-(19) in Relation (16):

$$\begin{aligned}
 \dot{V}(x_t) \leq & \vartheta^T(t) \left\{ \Sigma + \eta_1\tilde{Y}_0 \begin{bmatrix} T_{111} & T_{112} + X_0 \\ * & T_{122} \end{bmatrix}^{-1} \tilde{Y}_0^T \right. \\
 & + \eta_{21}\tilde{Y}_1 \begin{bmatrix} T_{211} & T_{212} + X_1 \\ * & T_{222} \end{bmatrix}^{-1} \tilde{Y}_1^T \\
 & \left. + \eta_{21}\tilde{Y}_2 \begin{bmatrix} T_{211} & T_{212} + X_2 \\ * & T_{222} \end{bmatrix}^{-1} \tilde{Y}_2^T \right\} \vartheta(t), \tag{20}
 \end{aligned}$$

where,  $\tilde{Y}_0$ ,  $\tilde{Y}_1$ , and  $\tilde{Y}_2$  were defined previously in



**Table 1.** MADBs computed by different methods for Example 1 (with  $\eta_1 = 0$ ).

	Method						
	[27]	[7]	[16]	[28]	[26]	[21]	Proposed method
<b>MADB</b>	0.9412	1.0081	1.0081	1.0081	1.0432	1.0629	1.0762

**Table 2.** Admissible upper bound  $\eta_2$  for different values of  $\eta_1$ .

	Method						
	[31]	[30]	[29] $N = 2$	[29] $N = 4$	[23] $N = 2$	[23] $N = 4$	Proposed method
$\eta_1 = 1$	1.9008	1.8737	2.004	2.0273	2.0089	2.0448	2.0852
$\eta_1 = 2$	2.5663	2.5048	2.5650	2.5915	2.5829	2.6051	2.6767
$\eta_1 = 3$	3.3408	3.2591	3.2866	3.3010	3.2983	3.3098	3.3778
$\eta_1 = 4$	4.169	4.0744	4.0818	4.0855	4.0848	4.0877	4.123

system can be described by the following time-delay system as in [21]:

$$\dot{x}(t) = \begin{bmatrix} 0 & 1 \\ 0 & -0.1 \end{bmatrix} x(t) + \begin{bmatrix} 0 & 0 \\ -0.375 & -1.15 \end{bmatrix} x(t-\eta(t)). \quad (23)$$

In Table 1, the maximum allowable value of  $\eta_2$  obtained from the proposed method along with the results from rival methods is listed for comparison. Table 1 clearly shows that the proposed approach outperforms the methods presented in [7,16,21,26–28].

**Example 2.** Considering the system in Eqs. (1) with the following matrices [23]:

$$A = \begin{bmatrix} -2 & 0 \\ 0 & -0.9 \end{bmatrix}, \quad A_1 = \begin{bmatrix} -1 & 0 \\ -1 & -1 \end{bmatrix}.$$

Table 2 shows the maximum allowable delay upper bound for different values of delay lower bound  $\eta_1$ , obtained from the proposed approach and methods of [23,29–31]. As seen, the maximum bound of delay obtained by the proposed method is larger than the existing ones which verifies the superiority of the suggested delay-dependent condition.

Results of several recent papers are reported in Tables 1 and 2 to reveal that the improvement of stability conditions with regard to the nearby rival methods is gradual.

## 5. Conclusion

In this paper, a new approach has been proposed to analyze the asymptotic stability of the linear time invariant systems with time-varying delay. By constructing new augmented Lyapunov-Krasovskii functional and using free-weighting matrices, a novel delay-dependent stability condition has been derived in terms of LMIs. Numerical examples have been given to demonstrate that the proposed criterion is less conservative compared to some of the existing approaches in the literature.

## References

- Gu, K., Kharitonov, V.L. and Chen, J., *Stability of Time-Delay Systems*, Springer, Birkhäuser Boston (2003).
- Richard, J.P. “Time-delay systems: an overview of some recent advances and open problems”, *Automatica*, **39**(10), pp. 1667–1694 (2003).
- Gu, K. and Niculescu, S.I. “Survey on recent results in the stability and control of time-delay systems”, *Journal of Dynamic Systems, Measurement, and Control*, **125**(2), pp. 158–165 (2003).
- Shao, H. and Han, Q.-L. “Less conservative delay-dependent stability criteria for linear systems with interval time-varying delays”, *International Journal of Systems Science*, **43**(5), pp. 894–902 (2012).
- He, Y., Wang, Q.G., Lin, C. and Wu, M. “Delay-range-dependent stability for system with time-varying delay”, *Automatica*, **43**(2), pp. 371–376 (2007).
- Qian, W., Cong, S., Li, T. and Fei, S. “Improved stability conditions for systems with interval time-varying delay”, *International Journal of Control, Automation, and Systems*, **10**(6), pp. 1146–1152 (2012).
- Tang, B., Liu, G.P. and Gui, W.H. “Improvement of state feedback controller design for networked control systems”, *IEEE Transactions on Circuits and Systems-II: Express Briefs*, **55**(5), pp. 464–468 (2008).
- Wu, M., He, Y. and She, J.H., *Stability Analysis and Robust Control of Time-Delay Systems*, Berlin, Springer (2010).
- He, Y., Wang, Q.G., Lin, C. and Wu, M. “Augmented Lyapunov functional and delay-dependent stability criteria for neutral systems”, *International Journal of Robust and Nonlinear Control*, **15**(18), pp. 923–933 (2005).
- Yue, D., Han, Q.L. and Lam, J. “Networked-based robust control of systems with uncertainty”, *Automatica*, **41**(6), pp. 999–1007 (2005).
- Han, Q.-L. “A discrete delay decomposition approach to stability of linear retarded and neutral systems”, *Automatica*, **45**(2), pp. 517–524 (2009).



12. Zhang, X.-M. and Han, Q.-L. "A delay decomposition approach to delay-dependent stability for linear systems with time-varying delays", *International Journal of Robust and Nonlinear Control*, **19**(17), pp. 1922-1930 (2009).
13. Seuret, A. and Gouaisbaut, F. "Wirtinger-based integral inequality: Application to time-delay systems", *Automatica*, **49**, pp. 2860-2866 (2013).
14. Wu, M., He, Y. and She, J.H. "New delay-dependent stability criteria and stabilizing method for neutral systems", *IEEE Transactions on Automatic Control*, **49**(12), pp. 2266-2271 (2004).
15. Wu, M., He, Y., She, J.H. and Liu, G.P. "Delay-dependent criteria for robust stability of time-varying delay systems", *Automatica*, **40**(8), pp. 1435-1439 (2004).
16. He, Y., Wang, Q.G., Xie, L. and Lin, C. "Further improvement of free-weighting matrices technique for systems with time-varying delay", *IEEE Transactions on Automatic Control*, **52**(2), pp. 293-299 (2007).
17. Lin, C., Wang, Q.G. and Lee, T.H. "A less conservative robust stability test for linear uncertain time-delay systems", *IEEE Transactions on Automatic Control*, **51**(1), pp. 87-91 (2006).
18. Zhang, X., Gao, X. and Su, M. "Simplified stability criteria for delayed neutral systems", *Mathematical Problems in Engineering*, **2014**, ID 238487 (2014).
19. Parlakçı, M.N.A. "Robust stability of uncertain time-varying state-delayed systems", *IEE Proceedings of Control Theory and Applications*, **153**(4), pp. 469-477 (2006).
20. Sun, J., Liu, G.P. and Chen, J. "Delay-dependent stability and stabilization of neutral time-delay systems", *International Journal of Robust and Nonlinear Control*, **19**(12), pp. 1364-1375 (2009).
21. Sun, J., Liu, G.P., Chen, J. and Rees, D. "Improved stability criteria for linear systems with time-varying delay", *IET Control Theory and Applications*, **4**(4), pp. 683-689 (2010).
22. Zheng, M., Xiao, W. and Chen, Q. "Improved stability criteria for uncertain linear systems with interval time-varying delay", *Journal of Systems Science and Complexity*, **26**(2), pp. 175-186 (2013).
23. Tang, M., Wang, Y.W. and Wen, C. "Improved delay-range-dependent stability criteria for linear systems with interval time-varying delays", *IET Control Theory and Applications*, **6**(6), pp. 868-873 (2012).
24. Zhang, X.-M. and Han, Q.-L. "New stability criterion using a matrix-based quadratic convex approach", *IET Control Theory and Applications*, **8**(12), pp. 1054-1061 (2014).
25. Gahinet, P., Nemirovski, A., Laub, A.J. and Chilali, M., *LMI Control Toolbox User's Guide*, Natick, MA: Math Works (1995).
26. Yue, D., Tian, E., Wang, Z. and Lam, J. "Stabilization of systems with probabilistic interval input delays and its applications to networked control systems", *IEEE Transactions on Systems, Man, and Cybernetics, Part A: System and Human*, **39**(4), pp. 939-945 (2009).
27. Jiang, X. and Han, Q.L. "Delay-dependent robust stability for uncertain linear systems with interval time-varying delay", *Automatica*, **42**(6), pp. 1059-1065 (2006).
28. Jiang, X. and Han, Q.L. "New stability criteria for linear systems with interval time-varying delay", *Automatica*, **44**(10), pp. 2680-2685 (2008).
29. Zhu, X.L., Wang, Y. and Yang, G.H. "New stability criteria for continuous-time systems with interval time-varying delay", *IET Control Theory and Applications*, **4**(6), pp. 1101-1107 (2010).
30. Shao, H. "New delay-dependent stability criteria for systems with interval delay", *Automatica*, **45**(3), pp. 744-749 (2009).
31. Sun, J., Liu, G.P., Chen, J. and Rees, D. "Improved delay-range-dependent stability criteria for linear systems with time-varying", *Automatica*, **46**(2), pp. 466-470 (2010).

## Biographies

**Arash Farnam** received the BSc degree in Electrical Engineering from Tabriz University, Iran, in 2010, and the MSc degree in Electrical Engineering from Sahand University of Technology, Tabriz, Iran, in 2012. He is currently working toward the PhD degree in the SYSTeMS Research Group, Ghent University, Ghent, Belgium. His research interests include time-delay systems and networked control systems.

**Reza Mahboobi Esfanjani** received his BSc degree (with honours) in Electrical Engineering from the Department of Electrical Engineering, Sahand University of Technology, Tabriz, Iran in 2002. He received the MSc and PhD degrees from Amirkabir University of Technology in 2004 and 2009, respectively. He has been holding a faculty position at the Electrical Engineering Department, Sahand University of Technology, since 2010. His research interests are analysis and control of time-delay and networked systems.

**Milad Farsi** received his BSc degree in Electrical Engineering from Tabriz University, Tabriz, Iran, and MSc degree from Sahand University of Technology, Tabriz, Iran, in 2010 and 2013, respectively. His current research interests include time-delay systems and switched systems theory with applications into analysis and design of networked control systems and power electronic circuits.