



UNIVERSITI PUTRA MALAYSIA

**APPLICATION OF OPEN-ENDED COAXIAL SENSOR TO DETERMINE
OIL PALM FRUIT RIPENESS**

YOU KOK YEOW

IPM 2006 5

**APPLICATION OF OPEN-ENDED COAXIAL SENSOR TO DETERMINE OIL
PALM FRUIT RIPENESS**

By

YOU KOK YEOW

**Thesis Submitted to the School of Graduate Studies, Universiti Putra Malaysia,
in Fulfilment of the Requirement for the Degree of Doctor of Philosophy**

July 2006



Specially dedicated to:

My beloved

Father, Mother, and Sister,

Niece,

and Friends.



Abstract of thesis presented to the Senate of Universiti Putra Malaysia in fulfilment of the requirement for the degree of Doctor of Philosophy

APPLICATION OF OPEN-ENDED COAXIAL SENSOR TO DETERMINE OIL PALM FRUIT RIPENESS

By

YOU KOK YEOW

July 2006

Chairperson : Zulkifly Abbas, PhD

Institute : Mathematical Research

This thesis presents a critical study on the use of an open-ended coaxial sensor for the determination of both complex permittivity and moisture content of oil palm fruits of various degrees of fruit ripeness at $(25 \pm 1)^\circ\text{C}$. The sensor was studied based on the calculation of reflection coefficient using an integral admittance approach and finite element method (FEM).

In this work, the computation of reflection coefficient of the oil palm fruits was realized using MATLAB and FEMLAB GUI software for the admittance approach and finite element method (FEM), respectively. The results were compared with the measured reflection coefficient using the open-ended coaxial sensor in conjunction with a HP8720B vector network analyzer (VNA). The sensor operating between 1 GHz and 5 GHz was fabricated from a 4.1 mm outer diameter sub-miniature A type (SMA) coaxial



stub contact panel. The measuring end of the sensor was calibrated by a transmission line procedure.

The integral admittance formulation was simplified into a series expression. The local truncation errors of the series approximation were critically analyzed. The two-dimensional FEM was used to solve the rotationally symmetric region of the open-ended coaxial line. The FEM results are closed to the measurements data than calculated admittance formulation. The maximum absolute errors of FEM and measurement results for magnitude and phase reflection coefficient are less than 0.02 and 0.1 rad, respectively, compared with 0.05 and 0.2 rad of admittance formulation and measurement results, respectively. However, the results were in good agreement that the minimum thickness of a sample under test is 2 mm.

An inverse solution based on two admittance models (lumped-parameter admittance and integral admittance formulations) has been utilized to derive complex permittivity from measured reflection coefficient. The lumped-parameter admittance or closed form capacitance model is simpler in the calculation than integral admittance model. Unfortunately, it is not accurate for high operating frequencies (>5 GHz). However, the permittivity results from both models agree with measured data using HP 85070B coaxial probe and publish values (Cole-Cole model) ranging 1 GHz to 5 GHz.

A calibration equation has been developed based on the relationship between the measured moisture content obtained by the oven drying method and the phase of the reflection coefficient of the sensor. The moisture content predicted by the sensor was in



good agreement with those obtained using the standard oven drying method with its absolute error within 5 % moisture content, when tested on 145 different fruits samples.

A model detailing two dielectric relaxation process parameters was proposed in order to represent the permittivity of oil palm mesocarp based on measured data using HP 85070B coaxial probe from 0.13 GHz to 20 GHz. The model successfully estimated the complex permittivity for various ripeness stages of oil palm mesocarp as a function of frequency, moisture and ionic conductivity, as well as the bulk density.

A dielectric measurement software has been developed to control and acquire data from the VNA using Agilent VEE. The software is also used to calibrate measurement at the aperture plane of sensor and to calculate the complex permittivity from the measured reflection coefficient between 1 GHz and 5 GHz.

Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk ijazah Doktor Falsafah

**PENGGUNAAN PENGESAN SEPAKSI HUJUNG TERBUKA UNTUK
PENENTUAN KEMATANGAN BUAH KELAPA SAWIT**

Oleh

YOU KOK YEOW

Julai 2006

Pengerusi : Zulkifly Abbas, PhD

Institut : Penyelidikan Matematik

Tesis ini memperihalkan kajian kritis terhadap penggunaan pengesan sepaksi hujung terbuka untuk menentukan kedua-dua ketelusan kompleks dan kandungan kelengasan bagi buah kelapa sawit berbagai peringkat kematangan pada $(25 \pm 1)^\circ\text{C}$. Pengesan tersebut telah dikaji merujuk kepada kiraan pekali pantulan menggunakan pendekatan pengamiran admitans dan kaedah unsur terhingga (FEM).

Dalam kerja ini, pengkomputeran pekali pantulan bagi buah kelapa sawit telah dilakukan dengan menggunakan perisian MATLAB dan FEMLAB GUI masing-masing untuk pendekatan admitans dan kaedah unsur terhingga (FEM). Keputusannya telah dibandingkan dengan ukuran pekali pantulan daripada peranti deria sepaksi hujung terbuka yang bersambung dengan penganalisis rangkaian vektor HP8720B (VNA). Pengesan ini yang beroperasi antara 1 GHz hingga 5 GHz telah dibina daripada pucuk



panel sentuhan sepaksi jenis A 4.1 mm diameter luaran SMA. Pada hujung penyukat pengesan telah ditentukan dengan menggunakan tatacara garisan transmisi.

Formula pengamiran admitans telah dipermudahkan kepada ungkapan siri. Ralat pangkasan setempat bagi penghampiran siri tersebut telah dianalisis secara kritis. FEM dua dimensi telah digunakan untuk menyelesaikan rantau simetri putaran garisan sepaksi hujung terbuka. Keputusan FEM adalah hampir dengan data-data pengukuran daripada kiraan formula admitans. Ralat mutlak maksimum bagi keputusan FEM dan pengukuran untuk magnitud and fasa pekali pantulan adalah masing-masing kurang daripada 0.02 dan 0.1 rad, berbanding dengan 0.05 and 0.2 rad bagi formula admitans dan keputusan pengukuran. Bagaimanapun, keputusan adalah bersetuju bahawa ketebalan minimum bagi sampel yang diuji adalah 2 mm.

Penyelesaian songsang yang merujuk kepada dua bentuk model admitans (formula parameter-gumpalan admitans dan pengamiran admitans) telah digunakan untuk menentukan ketelusan kompleks daripada ukuran pekali pantulan. Parameter-gumpalan admitans atau model kapasitans bentuk tertutup adalah lebih mudah dalam kiraan daripada pengamiran admitans. Malangnya, model ini tidak jitu untuk frekuensi pengoperasian yang tinggi (>5 GHz). Bagaimanapun, keputusan ketelusan daripada kedua-dua model adalah setuju dengan data-data ukuran yang menggunakan pengesan sepaksi HP 85070B dan juga nilai-nilai yang dipaparkan (model Cole-Cole) dalam julat 1 GHz hingga 5 GHz.

Persamaan penentukuran telah dibina berasaskan kepada hubungan antara sukatan kandungan kelengasan kaedah piawai pengeringan oven dengan fasa pekali pantulan kaedah pengesan. Ramalan kandungan kelengasan oleh pengesan tersebut amat setuju dengan nilai-nilai diperolehi daripada kaedah pengeringan oven dengan ralat mutlaknya dalam lingkungan 5 % kandungan kelengasan apabila diuji terhadap 145 buah sampel yang berlainan.

Model hasil tambah dua proses saintaian dielektrik telah disyor supaya mewakili ketelusan mesocarp kelapa sawit berasaskan kepada data-data ukuran pengesan sepaksi HP 85070B dalam julat 0.13 GHz hingga 20 GHz. Model tersebut telah berjaya meramalkan ketelusan kompleks bagi mesocarp kelapa sawit yang berbagai peringkat kematangan sebagai fungsi kepada frekuensi, kelengasan dan kekonduksian ion, serta ketunpatan pukal.

Perisian pengukuran dielektrik telah dibina untuk mengawal dan memperolehi data-data daripada VNA dengan menggunakan Agilent VEE. Perisian ini juga digunakan supaya menenturkan pengukuran pada satah bukaan bagi pengesan tersebut dan mengira ketelusan kompleks daripada pengukuran pekali pantulan antara 1 GHz and 5 GHz.

ACKNOWLEDGEMENTS

The author wishes to thank his family members for their love, support and encouragement as well as for always being there for him.

The author extends his deepest gratitude to the chairman of the supervisory committee, Dr. Zulkifly Abbas, for his kindness, guidance, suggestions, and his willingness to help.

The author also wishes to thank the members of the supervisory committee, Prof. Dr. Abdul Halim Shaari, Dr. Jumiah Hassan and Dr. Nik Mohd Asri Nik Long for their advice, supervision and guidance.

Appreciation also extended to the staff in the Electromagnetic Lab for their assistance and help. I am deeply grateful to En. Huslee for his unreserved help during collected samples.

I also would like to thank Prof. Dr. Kaida Khalid for his experimental equipments.



I certify that an Examination Committee has met on 10 July 2006 to conduct the final examination of You Kok Yeow on his Doctor of Philosophy thesis entitled “Application of Open-Ended Coaxial Sensor to Determine Oil Palm Fruit Ripeness” in accordance with Universiti Pertanian Malaysia (Higher Degree) Act 1980 and Universiti Pertanian Malaysia (Higher Degree) Regulations 1981. The Committee recommends that the candidate be awarded the relevant degree. Members of the Examination Committee are as follows:

Zaidan Abdul Wahab, PhD

Associate Professor
Faculty of Science
Universiti Putra Malaysia
(Chairman)

Elias Saion, PhD

Associate Professor
Faculty of Science
Universiti Putra Malaysia
(Internal Examiner)

Azmi Zakaria, PhD

Associate Professor
Faculty of Science
Universiti Putra Malaysia
(Internal Examiner)

HASANAH MOHD. GHAZALI, PhD

Professor / Deputy Dean
School of Graduate Studies
Universiti Putra Malaysia

Date:



This thesis submitted to the Senate of Universiti Putra Malaysia has been accepted as fulfillment of the requirement for the degree of Doctor of Philosophy. The members of the Supervisory Committee are as follows:

Zulkifly Abbas, PhD

Lecturer
Faculty of Science
Universiti Putra Malaysia
(Chairman)

Abdul Halim Shaari, PhD

Professor
Faculty of Science
Universiti Putra Malaysia
(Member)

Jumiah Hassan, PhD

Lecturer
Faculty of Science
Universiti Putra Malaysia
(Member)

Nik Mohd. Asri Nik Long, PhD

Lecturer
Faculty of Science
Universiti Putra Malaysia
(Member)

AINI IDERIS, PhD

Professor / Dean
School of Graduate Studies
Universiti Putra Malaysia

Date:



DECLARATION

I hereby declare that the thesis is based on my original work except for quotations and citations which have been duly acknowledged. I also declare that it has not been previously or concurrently submitted for any other degree at UPM or other institutions.

YOU KOK YEOW

Date:



TABLE OF CONTENTS

	Page
DEDICATION	ii
ABSTRACT	iii
ABSTRAK	vi
ACKNOWLEDGEMENTS	ix
APPROVALS	x
DECLARATION	xii
LIST OF TABLES	xvi
LIST OF FIGURES	xix
LIST OF ABBREVIATIONS	xxv
CHAPTER	
1 INTRODUCTION	
1.1 Background of the Study	1.1
1.1.1 Oil Palm Fruit Bunch	1.2
1.1.2 Ripeness of Oil Palm Fruits	1.3
1.2 Scope and Problem Statements of the Study	1.5
1.2.1 Measure of Ripeness of Oil Palm Fruits	1.5
1.2.2 Measure of Ripeness of Oil Palm Fruits Using Microwave Sensor	1.6
1.2.3 Microwave Moisture Measurements	1.8
1.2.4 Open-Ended Coaxial Sensor	1.8
1.3 Objectives	1.11
1.4 Significant of the Study	1.12
1.5 Thesis Outline	1.13
2 LITERATURE REVIEW	
2.1 Introduction	2.1
2.2 Maxwell's Equations	2.2
2.3 Boundary Conditions	2.3
2.4 Wave Equations	2.4
2.5 Admittance Models	2.6
2.5.1 Reviews of Admittance Models	2.6
2.5.2 Quasi-Static Integral Models (Infinite media)	2.7
2.5.3 Closed Form Capacitance Models	2.23
2.5.4 Quasi-Static Integral Models (Stratified media)	2.24
2.5.5 Numerical Models	2.29
2.5.6 Comparison of Numerical Methods	2.41
2.6 Sensitivity Coefficient, S_{ϵ}^F of Open-Ended Coaxial Sensor	2.42
2.7 Principle of Dielectric Model	2.43
2.7.1 Dipolar Dielectric Model	2.44
2.7.2 Mixture Materials	2.49



2.8	Reviews of Oil Palm Fruits Ripeness Measurements Using Microwave Sensors	2.53
2.9	Conclusion	2.57
3	OPEN-ENDED COAXIAL SENSOR STUDIES	
3.1	Introduction	3.1
3.2	Admittance Equations	3.2
3.2.1	Series Approximation	3.2
3.2.2	Variation in Normalized Conductance and Susceptance with Probe Size and Excitation Frequency	3.7
3.2.3	Variation in Normalized Conductance and Susceptance with Materials Under Test and Excitation Frequency	3.9
3.2.4	Comparison of Various Admittance Equations	3.13
3.2.5	Eigenvalues of Higher Order Modes in Coaxial Line	3.17
3.3	Scalar Finite Element Analysis of Open-Ended Coaxial Probe	3.19
3.3.1	Functional Equation	3.19
3.3.2	Discretization	3.20
3.3.3	Variational Techniques	3.23
3.3.4	Functional in Matrix Form	3.24
3.3.5	Assembling of All Elements	3.25
3.3.6	Solution of the Connected Problem	3.28
3.3.7	Numerical Approximation	3.29
3.3.8	Final Interpretation	3.30
3.3.9	Results and Analysis	3.31
3.3.10	Error Analysis	3.34
3.4	Vector Finite Element Analysis of Open-Ended Coaxial Probe	3.37
3.4.1	Partial Difference Equation (PDE)	3.37
3.4.2	Discretization	3.39
3.4.3	Weighted Residual Techniques	3.39
3.4.4	Boundary Conditions	3.42
3.4.5	Final Interpretation	3.46
3.4.6	FEMLAB Program	3.47
3.4.7	Results and Analysis	3.48
3.4.8	Simulations Performance	3.53
3.5	Sample Configuration Treatment	3.56
3.6	Conclusion	3.59
4	DIELECTRIC AND MOISTURE MEASUREMENTS USING OPEN-ENDED COAXIAL SENSOR	
4.1	Introduction	4.1
4.2	Materials and Methods	4.1
4.2.1	Commercial HP 85070B Coaxial Sensor	4.1
4.2.2	Design Open-Ended Coaxial Sensor	4.3
4.2.3	One-Port Calibration of Aperture Coaxial Sensor	4.4
4.2.4	Measurements of Sample Thickness	4.5
4.2.5	Oil Palm Sample Preparation	4.6
4.2.6	Oven Drying Procedures	4.7



4.2.7	Measurement and Computational Procedures	4.8
4.3	Data Processing System (Data Acquisition)	4.9
4.4	Conclusion	4.14
5	RESULTS AND DISCUSSION	
5.1	Introduction	5.1
5.2	Proof and Design Rules of Measurements	5.2
5.2.1	On-line Measurements	5.2
5.2.2	Errors Analysis	5.7
5.2.3	Determination of Significant Thickness for Sample Under Test	5.13
5.2.4	Variation in Reflection Coefficient, Γ with Frequency for Different Moisture content, $m.c$	5.17
5.3	Formulation Moisture Content, $m.c$ as a Function of Phase Reflection Coefficient, ϕ and Frequency at 25°C	5.24
5.3.1	Indirect Method	5.24
5.3.2	Direct Method	5.29
5.4	Conversion of Measured Reflection Coefficient, Γ to Relative Complex Permittivity, ϵ_r Via Admittance Equations	5.37
5.4.1	Direct Solution	5.37
5.4.2	Inverse Solution	5.45
5.4.3	Sensitivity Analysis Between Reflection Coefficient, Γ and Relative Complex Permittivity, ϵ_r	5.59
5.4.4	Variation in Complex Permittivity, ϵ_r with Frequency for Different Moisture Content, $m.c$ of Oil Palm Mesocarp	5.63
5.4.5	Effective Relative Complex Permittivity, ϵ_{eff}^* of Finite Thickness Sample	5.65
5.5	Dielectric Properties of Oil Palm Mesocarp	5.70
5.5.1	Formulation Dielectric Properties, ϵ_r as a Function of Moisture Content, $m.c$ and Frequency at 25 °C	5.70
5.5.2	Improvement of Mixture Model for Oil Palm Mesocarp	5.79
5.6	Conclusion	5.85
6	SUMMARY AND FUTURE WORK	
6.1	Summary of the Study	6.1
6.2	Main Contributions	6.3
6.3	Suggestions for Further Studies	6.4
	REFERENCES	R.1
	APPENDICES	A.1
	BIODATA OF THE AUTHOR	V.1



LIST OF TABLES

Table		Page
1.1	Institute of Electrical and Electronic Engineers (IEEE) frequency spectrum	1.7
2.1	Various types of formulations of open-ended coaxial probe available in Literatures	2.7
2.2	Comparison between variational method and weighted residual method	2.31
2.3	Values of Havriliak-Negami (HN) parameters (N , M and τ_{HN}) corresponding to the fitting of the frequency-domain response function deduced for the stretched exponential (KWW) with β parameters (Alvarez <i>et al.</i> , 1991)	2.49
2.4	Comparison previous works features for oil palm fruits measurements using microwave sensors	2.56
3.1	The local truncation errors, e of the normalized conductance and susceptance with respect to the number of series terms (Suppose $\epsilon_r = 80$ and $\epsilon_c = 2.05$ at 20 GHz ; $Y_1 = \sqrt{\epsilon_r} / \left[\sqrt{\epsilon_c} \ln(b/a) \right]$, $Y_2 = \sqrt{\epsilon_r} / \left[\pi \sqrt{\epsilon_c} \ln(b/a) \right]$)	3.4
3.2	Physical and chemical properties of references liquids (Chelkowski, 1980 ; Grant <i>et al.</i> , 1989 ; Nyshadham <i>et al.</i> , 1992)	3.9
3.3	The potential for each of concentric ring, $V_i \cdot (2\pi\rho_i)$ at various radius, ρ_i	3.35
3.4	The total potential, V_{Area} charge, Q_{Area} and capacitance, C at the aperture area between inner and outer conductor	3.36
3.5	The comparison of capacitance, C at aperture coaxial probe obtained from literatures	3.36
3.6	Relative complex permittivity, ϵ_{fruit} of oil palm mesocarp contain various moisture content, $m.c$ for 3 GHz at 25 °C	3.52
3.7	The runtime and reflection coefficient, Γ of air are based on the number of mesh	3.53



3.8	Simulation values of magnitude and phase reflection coefficient for 4 lossy liquids based on Figure 3.17 (a), (b), (c), (d) and (e)	3.57
3.9	The percentage relative error of complex reflection coefficient, Γ by referring to the ideal sample configuration as shown in Figure 3.17(a)	3.58
5.1 (a)	The percentage of relative errors in FEM simulations by referring to measured data	5.8
(b)	Relation ship of % relative errors between dielectric properties, ϵ_r in FEM simulations and its simulations results ($ \Gamma $ and ϕ)	5.9
5.2	The values of m and c for 1 GHz, 2 GHz, 3GHz, 4 GHz and 5 GHz	5.25
5.3	The relationship between m and f is best represented by 4 th order polynomial, as well as the relationship between c and f is best represented by 3 rd order polynomial	5.26
5.4	The values m and c for 1 GHz, 2 GHz, 3GHz, 4 GHz and 5 GHz	5.31
5.5	The relationship between m and f is represented by 4 th order polynomial, as well as the relationship between c and f are best represented by 3 rd order polynomial	5.32
5.6	The predicted values of the % water content, $m.c$ at 12 areas of fruit sample using equation (5.3) ranging 1 GHz to 5 GHz	5.36
5.7	The appropriate values of weighted of objective functions (5.14a) and (5.14b)	5.48
5.8	Comparison mathematical calculation results between using complete admittance equation, $\tilde{Y} = \text{Re}(\tilde{Y}) + j \text{Im}(\tilde{Y})$ and incomplete admittance formulation, $\tilde{Y} = j \text{Im}(\tilde{Y})$	5.49
5.9 (a)	Characteristic $\epsilon_r' / \epsilon_r'' = 20$ occurred in prediction of dielectric constant, ϵ_r' using objective function (5.14a)	5.51
(b)	Characteristic $\epsilon_r' / \epsilon_r'' = 20$ occurred in prediction of loss factor, ϵ_r'' using objective function (5.14b)	5.51
5.10	Measured values of ϵ_{r1}' and ϵ_{r1}'' used in calculations of equation (5.19)	5.66
5.11	The estimated values of Debye and Cole-Cole parameters of oil palm	

	mesocarp for various percentage of water content, $m.c$ (%) at $(25 \pm 1)^\circ\text{C}$	5.76
5.12	The Debye and Cole-Cole parameters of oil palm mesocarp as a function of percentage water content, $m.c$ (%) at $(25 \pm 1)^\circ\text{C}$	5.77
5.13	The coefficient values of equations (5.27) and (5.29)	5.82
5.14	Relation ship between % water content, $m.c$ and dielectric constant, ϵ_r' of oil palm mesocarp for 3 GHz at $(25 \pm 1)^\circ\text{C}$	5.85



LIST OF FIGURES

Figure	Page
1.1 A tenera bunch halved to show (1) the stalk plus (2) spikelets and fruits, comprising (3) the mesocarp, (4) the shell and (5) the kernel	1.2
1.2 Average composition of tenera fruit bunch (Jacobsberg, 1974)	1.3
1.3 Variation in moisture content, <i>m.c</i> and oil content with weeks after anthesis (Abbas, 1994)	1.4
1.4 Various ripeness stages of oil palm fruits	1.5
2.1 Cylindrical coordinate of annular slot	2.10
2.2 Path of integration, <i>C</i> in complex ζ -plane	2.20
2.3 Open-ended coaxial line. (a) Geometry. (b) Equivalent circuit	2.23
2.4 Geometry of coaxial line and dielectric layers	2.25
2.5 FEM mesh of open-ended coaxial region (Gajda <i>et al.</i> , 1983)	2.32
2.6 Interface between different dielectric media in MoM (Gajda <i>et al.</i> , 1983)	2.38
2.7 FD-TD mesh and the graphical solution of open-ended coaxial line with an extended center conductor (Maloney <i>et al.</i> , 1990)	2.40
2.8 Ideal Debye's properties	2.45
2.9 10 × 40 magnification of the ripe palm fruit mesocarp cells containing oil body (Ariffin, 2005)	2.52
2.10(a) Microstrip waveguide (MWG) (Abbas, 1994)	2.53
(b) Multilayer conductor-backed coplanar waveguide (CBCPW) (Teoh, 1997)	2.54
(c) Rectangular dielectric waveguide (RDWG) (Mokhtar, 2004)	2.54
(d) Rectangular waveguide (RWG) (Ali, 2006)	2.54



(e) Annular slot waveguide (or monopole) (Lee, 2004)	2.55
(f) Open-ended coaxial waveguide (OECWG)	2.55
3.1 The relationship between local truncation errors, e of conductance and susceptance series and number of series term $(N+1)$. (For $a = 0.00065$ m, $\epsilon_r = 80$, $\epsilon_c = 2.05$ and $f = 20$ GHz)	3.5
3.2 The variation in deviation of normalized conductance, $\Delta(G/Y_o)$ and susceptance, $\Delta(B/Y_o)$ with number of series terms $(N + 1)$. (For $a=0.0006$ m, $\epsilon_r = 80$, $\epsilon_c = 2.05$ and $f = 20$ GHz)	3.6
3.3 The theoretical normalized conductance, $G(0)/Y_o$ and $B(0)/Y_o$ for water at 25 °C by considering various values of b/a probe with $a = 0.3$ mm and 0.65 mm, respectively	3.8
3.4 The relative permittivity, $\epsilon_r^* = \epsilon_r' - j\epsilon_r''$ of five samples corresponds to the aperture admittance, $\tilde{Y} = G(0)/Y_o + jB(0)/Y_o$ of the coaxial probe with $a = 0.65$ mm and $b = 2.05$ mm at room temperature	3.12
3.5 (a) The variation in theoretical normalized conductance, $G(0)/Y_o$ with frequency for five medium at 25 °C	3.15
(b) The variation in theoretical normalized susceptance, $B(0)/Y_o$ with frequency for five mediums at 25 °C	3.16
3.6 The eigenvalues λ_n are obtain from expression (2.42)	3.18
3.7 Triangular element used in the finite element method	3.20
3.8 Triangular element of used in the finite element method for open-ended coaxial line	3.27
3.9 The mesh and boundary conditions of open-ended coaxial configurations	3.31
3.10 Variation in circular ring potential ($V_{ring} = V_i \cdot (2\pi\rho_i)$) with radius, ρ_i of coaxial probe	3.33
3.11 The problem domain and electromagnetic fields near the aperture coaxial probe	3.37
3.12 Rotationally symmetric region of open-ended coaxial line	3.42

3.13	The finite element method (FEM) simulations chart	3.47
3.14 (a)	Variation in normalized conductance, G/Y_0 and susceptance, B/Y_0 , of $a = 0.3$ mm coaxial sensor with its respect ratio size of b/a for water at 25 °C	3.50
(b)	Variation in normalized conductance, G/Y_0 and susceptance, B/Y_0 , of $a = 0.65$ mm coaxial sensor with its respect ratio size of b/a for water at 25 °C	3.51
3.15	Variation in normalized conductance, G/Y_0 and susceptance, B/Y_0 , of $a = 0.65$ mm coaxial sensor for oil palm mesocarp at 3 GHz	3.54
3.16	The influence of number of elements mesh on the accuracy of simulation results	3.55
3.17	Sample Configuration Treatment	3.56
4.1	Commercial HP 85070B coaxial sensor	4.2
4.2	Experimental set-up	4.2
4.3	Schematic diagram of the open-ended coaxial probe	4.3
4.4	Transmission line of open-ended coaxial probe	4.6
4.5	Experimental set-up	4.7
4.6	Part of the fresh mesocarp of each fruit was sliced in the longitudinal direction to ensure good contact between the surface of the mesocarp and the open-ended coaxial probe	4.8
4.7	Measurement and Computational Procedures	4.9
4.8 (a)	The main panel in icon view for data acquisition and control of the VNA with PC	4.10
(b)	HP8720B object	4.11
(c)	Magnitude of S11 and Phase of S11 objects	4.12
(d)	Reflection Coefficient object	4.12
(e)	Save File object	4.12
(f)	Calibration and Calculation of Complex Permittivity Sample object	4.13

(g) Higher Order Modes object	4.14
5.1 (a) Variation in normalized conductance, $G(0)/Y_o$ with frequency at room temperature for air (free space) and four lossy liquids	5.3
(b) Variation in normalized susceptance, $B(0)/Y_o$ with frequency at room temperature for air (free space) and four lossy liquids	5.4
5.2 (a) Variation in magnitude reflection coefficient, $ \Gamma $ with frequency	5.5
(b) Variation in phase reflection coefficient, ϕ with frequency	5.6
5.3 (a) The contributions of absolute errors for reflection coefficient magnitude, $ \Delta\Gamma $ in FEM simulations (Using measured ϵ_r)	5.11
(b) The contributions of absolute errors for reflection coefficient phase, $ \Delta\phi $ in FEM simulations (Using measured ϵ_r)	5.12
5.4 Variation in magnitude and phase of reflection coefficient with medium thickness at room temperature for 4GHz	5.14 – 5.16
5.5 (a) Variation in reflection coefficient magnitude, $ \Gamma $ with percentage moisture content, $m.c$	5.18
(b) Variation in phase shift, ϕ with percentage moisture content, $m.c$	5.19
5.6 Variation of measured reflection coefficient with thickness of oil palm mesocarp and compare with FEM simulation results	5.21 – 5.23
5.7 Variation in % moisture content, $m.c$ for oil palm mesocarp obtained from oven drying method with corresponding phase of reflection coefficient, ϕ (rad) each of frequency, f (1 GHz, 2 GHz, 3 GHz, 4 GHz and 5 GHz)	5.27
5.8 (a) Relationship between coefficient m and corresponding frequency, f . (b) Relationship between coefficient c and corresponding frequency, f	5.28
5.9 The comparison between predicted and measure moisture content, $m.c$	5.33
5.10 Variation in sensitivity for various moisture content, $m.c$ with frequency	5.35

5.11	The sensor was tested on 12 areas of fruit sample, which are 4 top (U1, U2, U3 and U4) and 4 medium (M1, M2, M3 and M4), as well as 4 bottom areas (B1, B2, B3 and B4) of the fruit	5.36
5.12	Variation in capacitance, C at aperture open-ended coaxial probe with frequency	5.39
5.13	ariation in dielectric constant and loss factor with frequency for five mediums at $(25 \pm 1)^\circ\text{C}$	5.40 – 5.44
5.14	The structure chart of MATLAB program	5.52
5.15	Variation in dielectric constant, ϵ'_r of materials with frequency	5.53
5.16	Variation in loss factor, ϵ''_r of materials with frequency	5.54
5.17	Variation in residuals of objective function (5.14a) with frequency	5.57
5.18	Variation in residuals of objective function (5.14b) with frequency	5.58
5.19	The variations in sensitivity coefficient, S_ϵ^Γ with frequency for five mediums at $(25 \pm 1)^\circ\text{C}$	5.60
5.20	The influences of $ \Delta\Gamma/\Gamma $ on $ \Delta\epsilon_r/\epsilon_r $ within 1 GHz to 5 GHz for free space and four lossy liquids	5.62
5.21	The variations in dielectric constant, ϵ'_r and loss factor, ϵ''_r of oil palm mesocarp with frequency for various % moisture content at $(25 \pm 1)^\circ\text{C}$ (— HP85070B sensor ; ● Direct solution ; ☆ Inverse solution)	5.64
5.22	Variations in effective relative complex permittivity, ϵ_{eff} with thickness medium, which back by metallic plate [Solid line is obtained from equation (5.19)]	5.67 – 5.69
5.23	Variation in ϵ'_r with, ϵ''_r for various water content, $m.c$, which plotting slope is represented the relaxation time, τ of oil palm mesocarp at $(25 \pm 1)^\circ\text{C}$	5.75
5.24	The relationship between conductivity of oil palm mesocarp, σ and its moisture content, $m.c$	5.76



5.25	Variation in dielectric constant, ϵ_r' and loss factor, ϵ_r'' with frequency at room temperature (25 ± 1) ^o C for various water content, <i>m.c</i> (%) in oil palm mesocarp	5.78
5.26	Variation in real part and imaginary part of relative permittivity, ϵ_{oil} for palm oil with frequency	5.83
5.27	The variations in dielectric constant, ϵ_r' and loss factor, ϵ_r'' of oil palm mesocarp with % moisture content for 3 GHz at (25 ± 1) ^o C	5.84
6.1	Solution flow chart of analytical modeling	6.2
6.2	Solution flow chart of FEM simulation	6.2

