



UNIVERSITI PUTRA MALAYSIA

**IMPROVEMENT OF A DYNAMIC FREQUENCY HOPPING OPTICAL
CODE DIVISION MULTIPLE ACCESS SYSTEM USING POWER
CONTROL METHOD**

WAMIDH J. MAZEHR ALGALBI

FK 2009 93



**IMPROVEMENT OF A DYNAMIC FREQUENCY HOPPING OPTICAL CODE
DIVISION MULTIPLE ACCESS SYSTEM USING POWER CONTROL
METHOD**

By

WAMIDH J. MAZEHR ALGALBI

**Thesis Submitted to the School of Graduate Studies, Universiti Putra Malaysia, in
Fulfilment of Requirements for the Degree of Master of Science**

October, 2009



**Dedicated to
My dearest Family
For their extraordinary love and their endless care
Thank You**



Abstract of thesis presented to the Senate of Universiti Putra Malaysia in
fulfilment of the requirement for the degree of Master of Science

**IMPROVEMENT OF A DYNAMIC FREQUENCY HOPPING OPTICAL CODE
DIVISION MULTIPLE ACCESS SYSTEM USING POWER CONTROL
METHOD**

By

WAMIDH J. MAZEHR ALGALBI

October, 2009

Chairman: Makhfudzah Mokhtar, PhD

Faculty: Engineering

In this thesis, adaptive power control method is proposed to improve the performance of dynamic frequency hopping-optical code division multiple access (DFH-OCDMA) communication system. This method is based on solving the near-far problem of power misdistribution among simultaneous users. The DFH-OCDMA has an advantage of supporting more users compared to other OCDMA techniques such as Hadamard code, modified quadratic congruence code, modified frequency hopping code, and fast frequency hopping system. Nevertheless, the bit error rate (BER) was found to deteriorate rapidly with a slight change of received power compared to the other techniques. With the change of the received power (i.e. from -10 dBm to -12 dBm), the BER could be degraded from 10^{-9} to 10^{-6} . This phenomenon is strongly related to near-far problem, where users at longer path lengths will suffer higher BER compared to users at shorter path lengths. The unequal power distribution among users leads to unequal performance for them. This may cause to not all users can be supported in the



transmission system. Therefore, this study is aimed to search for a solution to increase the number of users under the DFH-OCDMA system with near-far problem.

A distributed power control algorithm was proposed to enhance the performance of the system and this was done by considering all possible noises such as the multiple access interference, phase induced intensity noise, and shot noise. The performance of the system was also observed at different issues of fibre impairments, including fibre attenuation, and optical components. The results gathered from the simulations showed that BER and signal-to-noise-ratio (SNR) for each user were significantly improved after using the power control. In specific, it is observed that the best capacity increased was 51% when the random path lengths for 110 users was between 1 to 40 km. Thus, the power control method is proven as an important enhancement to DFH-OCDMA performance. Moreover, the number of users increased in the DFH-OCDMA system with power control was 56 users while at prime code OCDMA and time hopping, only 20 users increment with power control. This result therefore shows better improvement of capacity in DFH-ODCMA compared to other Power Controlled-OCDMA.

Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk ijazah master Sains

**PEMBAIKAN SISTEM LOMPATAN FREKUENSI DINAMIK PENCAPAHAN
KOD PELBAGAI AKSES OPTIK MENGGUNAKAN KAWALAN KUASA
KAEDAH**

Oleh

WAMIDH J. MAZEHR ALGALBI

Oktober, 2009

Pengerusi: Makhfudzah Mokhtar, PhD

Fakulti: Kejuruteraan

Di dalam tesis ini, suatu kaedah kawalan kuasa adaptif telah diusulkan untuk memperbaiki prestasi sistem komunikasi lompatan frekuensi dinamik – multipleksi kod pelbagai akses optik (DFH-OCDMA). Kaedah ini berdasarkan penyelesaian masalah hampir-jauh bagi ketidakseimbangan kuasa di kalangan pengguna-pengguna serentak. DFH-OCDMA mempunyai kelebihan berbanding kaedah OCDMA lain seperti kod Hadamard, kod kongruens kuadratik terubahsuai, kod lompatan frekuensi terubahsuai, dan kod lompatan frekuensi cepat. Walaubagaimanapun, kadar ralat bit (BER) kod ini merosot lebih cepat dengan perubahan kuasa yang diterima berbanding kaedah-kaedah lain. Dengan mengubah kuasa penerima (iaitu daripada -10dBm kepada -12 dBm), akan mengakibatkan kemerosotan BER daripada 10^{-9} kepada 10^{-6} . Fenomena ini amat berkait rapat dengan masalah hampir-jauh, di mana pengguna yang berada pada panjang laluan yang lebih jauh akan mempunyai BER yang lebih tinggi berbanding pengguna yang berada pada panjang laluan yang lebih hampir. Ketidakseimbangan kuasa di kalangan

pengguna tersebut menjurus kepada prestasi yang berbeza kepada mereka. Ini akan menyebabkan tidak semua pengguna dapat disokong dalam sesebuah sistem penghantaran. Oleh itu, kajian ini bertujuan untuk mencari penyelesaian bagi menambah bilangan pengguna di bawah sistem DFH-OCDMA yang mempunyai masalah hampir-jauh.

Sebuah algoritma kawalan kuasa berselerak telah dicadangkan untuk memperbaiki prestasi sistem ini dengan mengambil kira semua punca hingar seperti interferens akses pelbagai, hingar intensiti berpunca fasa, dan hingar tertembak. Prestasi sistem dipantau dari segi isu-isu kecacatan gentian yang berbeza termasuk pengecilan dalam gentian, dan komponen optikal. Hasil simulasi telah menunjukkan bahawa BER dan nisbah-isyarat-kepada-hingar (SNR) bagi setiap pengguna telah diperelokkan secara signifikan setelah menggunakan kawalan kuasa. Secara terperinci, didapati bahawa penambahan kapasiti terbaik adalah sebanyak 51%, apabila panjang laluan rawak bagi 110 pengguna serentak berukuran antara 1 hingga 40 km. Oleh itu terbukti bahawa kawalan kuasa adalah penting bagi penambahan prestasi DFH-OCDMA. Malahan, bilangan pengguna yang bertambah dalam DFH-OCDMA dengan kawalan kuasa adalah sebanyak 56 manakala bagi kod prima OCDMA dan lompatan masa, hanya 20 pertambahan pengguna dengan kawalan kuasa. Keputusan ini seterusnya menunjukkan penambahbaikan kapasiti yang lebih tinggi dalam DFH-OCDMA berbanding kawalan kuasa OCDMA yang lain.

AKNOWLEDGEMENT

بِسْمِ اللَّهِ الرَّحْمَنِ الرَّحِيمِ

الْحَمْدُ لِلَّهِ رَبِّ الْعَالَمِينَ

First of all, I would like greater thank and gratitude to my believe Allah, for his help my and support. I would like to deeply thank my supervisor, Dr. Makhfudzah Mokhtar for her valuable support and guidance for me through my research studies at University Putra Malaysia.

I also want to thank Professor Dr. Mohammed Salem Elmusrati for his valuable ideas, comments and advices.

My thanks are also extended to my supervisory committee members Dr. Ahmad Fauzi Abas for his valuable comments and discussions. I would like also to thank all photonics lab members.

Thanks are also extended to all my brothers and sisters.

Finally, I would like to express my deepest gratitude to my wife Dr. Shafaa Al-glabi for her love, support, patience, and taking care of our baby Ahmad almostafa.

I certify that a Thesis Examination Committee has met on **23-10-2009** to conduct the final examination of **WAMIDH J. MAZEHR ALGALBI** on his thesis entitled “**IMPROVEMENT OF A DYNAMIC FREQUENCY HOPPING OPTICAL CODE DIVISION MULTIPLE ACCESS SYSTEM USING POWER CONTROL METHOD**” in accordance with the Universities and University Colleges Act 1971 and the Constitution of the Universiti Putra Malaysia [P.U. (A) 106] 15 March 1998. The Committee recommends that the student be awarded the Master of Science.

Members of the Thesis Examination Committee were as follows:

Raja Syamsul Azmir Raja Abdullah, PhD

Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Sabira Khatun, PhD

Associate Professor
Faculty of Engineering
Universiti Putra Malaysia
(Internal Examiner)

Salasiah Hitam, PhD

Faculty of Engineering
Universiti Putra Malaysia
(Internal Examiner)

Kaharudin Dimiyati, PhD

Professor
Faculty of Engineering
Universiti of Malaya
Malaysia
(External Examiner)

BUJANG KIM HUAT, PhD

Professor and Deputy Dean
School of Graduate Studies
Universiti Putra Malaysia

Date: 24 December 2009



This thesis was submitted to the Senate of Universiti Putra Malaysia and has been accepted as fulfilment of the requirement for the degree of Master Science. The members of the Supervisory Committee were as follows:

Makhfudzah Mokhtar, PhD
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

Ahmad Fauzi Abas, PhD-Ing
Faculty of Engineering
Universiti Putra Malaysia
(Member)

HASAN MOHD GHAZALI, PhD
Professor and Dean
School of Graduate Studies
Universiti Putra Malaysia

Date: 14 January 2010



DECLARATION

I declare that the thesis is my original work except for the quotations and citations, which have been duly acknowledged. I also declare that it has not been previously, and is not concurrently, submitted for any other degree at Universiti Putra Malaysia or at any other institution.

WAMIDH J. MAZEHR ALGALBI

Date:



TABLE OF CONTENTS

	Page
ABSTRACT	iii
ABSTRAK	v
ACKNOWLEDGMENTS	vii
APPROVAL	viii
DECLARATION	x
LIST OF TABLES	xiv
LIST OF FIGURES	xv
LIST OF ABBREVIATIONS	xviii
CHAPTER	
1 INTRODUCTION	
1.1 Background	1
1.2 Multiple Access Technique with Power Control Rule	2
1.3 The Quality of Service Parameters	3
1.4 Problem Statement and Motivation	5
1.5 Objectives of the Study	6
1.6 Contribution	7
1.7 Design Parameter	8
1.7.1 Fiber Length and the Attenuation.	9
1.7.2 Transmitted Power	10
1.7.3 Number of Simultaneous Users	11
1.8 Performance Parameters	11
1.8.1 Signal-to-Interference Ratio and Signal-to- -Noise Ratio	11
1.8.2 The Bit Error Rate (BER)	11
1.8.3 The Received Noise Power	12
1.9 Outline of Thesis	12
2 REVIEW ON OPTICAL CODE DIVISION MULTIPLE ACCESS TECHNOLOGIES AND POWER CONTROL METHODS	 13
2.1 Introduction	13
2.2 Multiple Access Techniques	13
2.2.1 Time Division Multiple Access (TDMA)	14
2.2.2 Wavelength Division Multiple Access (WDMA)	15
2.2.3 Optical Code Division Multiple Access(OCDMA)	16
2.3 Optical CDMA Codes family	18
2.3.1 Prime Codes	19
2.3.2 Optical Orthogonal Codes (OOC)	20
2.3.3 Hadamard Code	21
2.3.4 Dynamic Frequency Hopping –OCDMA Technique	22
2.4 Power Control Algorithm (PCA)	26



2.4.1	Types of Power Control Methods	26
2.4.2	Centralized Power Control (CPC)	27
2.4.3	Distribution Power Control Algorithm (DPCA)	30
2.4.4	Fully Distribution Power Control (FDPC)	31
2.5	Summary	33
3	APPLYING POWER CONTROL METHOD WITH DFH-OCDMA AT DIFFERENT PATHS	35
3.1	Introduction	35
3.2	The Power Control with Different Path Lengths	37
3.2.1	Three Groups at Constant L	39
3.2.2	Three Groups with variable L	41
3.3	Power Control Requirement with DFH-OCDMA	43
3.3.1	Centralization Power Control with DFH-OCDMA	44
3.3.2	Distribution Power Control with DFH-OCDMA	45
3.3.3	Quality of Service for the DFH-OCDMA System	47
3.4	Summary	50
4	ADAPTED PARAMETERS OF DFH-OCDMA FOR POWER CONTROL ALGORITHM	51
4.1	Introduction	51
4.2	Analysis of SNR with Adapted Noise Equations	51
4.2.1	Analysis of MAI to be Adapted with PC Algorithm	53
4.2.2	Analysis of PIIN to be Adapted with PC Algorithm	54
4.2.3	Analysis of Shot Noise to be Adapted with PC Algorithm	56
4.2.4	The SNR of the DFH-OCDMA with PCA	57
4.3	The Effect of the Constant Parameters on the DFH-OCDMA With PCA	58
4.3.1	The Effect the Total Number of Users- k on Constant Parameters	58
4.3.2	The Effect of the TOF Bandwidth on the Constant Parameters	59
4.4	Carrier to the Interference with the Transmitted Power Vector	59
4.4.1	Carrier to Interference Ratio (CIR)	60
4.4.2	The Relationship between the Transmitted Power Vector and Bit Rate	61
4.5	Path Loss Between the Transceiver of the Two Nodes	62
4.5.1	The Probability of Difference Paths in the End-End Connection	63
4.5.2	Analysis of Intersecting Points of the Two Users with PC	65
4.6	Analysis of the Received Power with Power Control Method	67
4.7	Summary	70



5	RESULTS IN APPLYING POWER CONTROL METHOD WITH DFH-OCDMA	71
5.1	Introduction	71
5.2	Description of the Numerical Simulation Set-up	71
5.3	Simulation of Various Distance between Two Adjacent Users	72
	5.3.1 Initial Transmitted Power at $P_t = 0$ dBm for Various Path Lengths	72
	5.3.2 Initial Transmitted Power at $P_t = -1$ dBm for Various Path Lengths	78
5.4	Simulation of Various Numbers of Users with a Fixed Distance between Two Adjacent Users	83
	5.4.1 Varying the Number of Users with the Difference in Sequence path at 0.2 km	84
	5.4.2 Varying the Number of Users with the Difference in Sequenced Path at 0.3 km	88
5.5	The SNR with and without Power Control Method	92
5.6	Reducing the Noises Using Power Control Method	100
5.7	Summary	102
6	Conclusion and Future work	103
6.1	Conclusion	103
6.2	Future work	104
	REFERENCES	106
	APPENDICES	113
	BIODATA OF STUDENT	118
	LIST OF PUBLICATIONS	119



LIST OF TABLES

Table		page
3.1	The Sensitivity of the DFH-OCDMA with the Change of the P_r Compared to other Techniques.	36
5.1	Typical Parameters Used in the Calculations	72
5.2	Procedure to Power Reduction for User 40 th	75
5.3	the Effect of Various Distance between Two Adjacent Users on the Capacity (Initial $P_t=0$ dBm)	77
5.4	A Comparison between the Difference in Path Length and the Capacity Increment ($P_t= -1$ dBm)	82
5.5	A Comparison between Number of Users and the Capacity Increment at $P_t= 1$ dBm and the Difference in Path Length 0.2 (km)	87
5.6	A Comparison between Number of Users and the Capacity Increment at $P_t= 1$ dBm and the Difference in Path Length 0.3 (km)	91



LIST OF FIGURES

Figure	Page
2.1 Basic Structure of Frame and Slot with TDMA	14
2.2 Basic WDM Systems	15
2.3 Basic Signal Encoders in CDMA System	17
2.4 Block Diagram of OCDMA Network	18
2.5 Basic Block Diagram for DFHOCDMA System	23
2.6 Encoder Output Signal for (a) DFH-OCDMA system Using Shifted Sine Code (b) FFH-OCDMA System Using Random Code of Weight 6.	23
2.7 Different Lengths for Simultaneous Users: (a) at Transmitter Side, (b) at Receiver Side.	28
3.1 Block Diagram to Study the Performance of the DFH-OCDMA with and without Power Control Method	36
3.2 Transmitted Signals from Broadband Source to Different Path Lengths	38
3.3 Distribution of K Users into 3 Groups with the Same Path for All Users at any Group	40
3.4 Distribution of K Users into 3 Groups with Unequal Path among Users in Each Group M and N	41
3.5 The Algorithm for the Proposed PC with the DFH-OCDMA	49
4.1 Diagram of Loss from Source to Distention	63
4.2 Cases of Noise (a) Noise-free at $S=E=T/2$ (b) Worst Case at $S=0, E=T/2$	66
4.3 The Area between S and $E, (F_i \cap F_j)$ Represents the Interference between Function F_i and F_j	66
4.4 Changing the Interference Area when the Power of User i Reduced while the Power of User j is Fixed	68
4.5 Flowchart of the PCA for All the Received Power with Eigenvalue Method	69



5.1	The Number of Supported Users was 110 with Power Control at BER threshold= 10^{-9} , while this was 73 without PC and the Distance between Two Adjacent Users was 0.2 km	73
5.2	The Number of Supported Users was 110with Power Control at BER threshold = 10^{-9} while this was 57 without PC and the Distance between Two Adjacent User was 0.4 Km,	74
5.3	The Number of Supported Users was 92 with PC at BER= 10^{-9} , while this was 52 without the PC, and the Distance between Two Adjacent Users was 0.5 km at $K=110$	75
5.4	The Number of Supported Users was 110 with Power Control at BER threshold= 10^{-9} , while this was 89 without PC and the Distance between Two Adjacent Users was 0.1 km	79
5.5	The Number of Supported Users was 110 with Power Control at BER threshold= 10^{-9} , while this was 71 without PC and the Distance between Two Adjacent Users was 0.2 km	79
5.6	The Number of Supported Users was 110 with Power Control (4 th iteration) at BER threshold= 10^{-9} , while this was 62 without PC and the Distance between Two Adjacent Users was 0.4 km	80
5.7	The Number of Supported Users was 92 with Power Control (5 th iteration) at BER threshold= 10^{-9} , while this was 60 without PC and the Difference in Sequenced Paths was 0.5 km	81
5.8	The Average BER against Different Distance between Adjacent Users (0.1-0.5 km) with $K=100$ Users	82
5.9	Supported 90 out of 90 Users in the System with PC at the Difference in the Path Sequence 0.2 km, while only 83 out of 90 users were Supported without any PC (BER threshold = 10^{-9})	84
5.10	Supported 100% Users in the System with PC at the Difference in the Path Sequence at 0.2 km , while only 77 out of 100 Users were Supported without the PC (BER threshold = 10^{-9})	85
5.11	Supported 100% Users in the System with PC at Difference in the Path Sequence 0.2 km, while only 72 out of 110 Users were Supported without PC (BER threshold = 10^{-9})	86
5.12	Supported 100% Users in the System with PC at Difference in the Path Sequence 0.3 km after 3 rd Iteration, while only 67 out of 120 Users were Supported without PC (BER threshold = 10^{-9})	87



5.13	Supported 100% Users in the System with PC at Difference in the Path Sequence of 0.3 km, while only 70 out of 90 Users were Supported without PC (BER threshold = 10^{-9})	88
5.14	Supported 100 Users in the System with PC at Difference in Path Sequence of 0.3 km, while only 68 out of 100 Users were Supported without the PC (BER threshold = 10^{-9})	89
5.15	Supported 100 Users in the System with PC at Difference in the path Sequence 0.3 km after 3 rd Iteration, while only 66 out of 110 Users were Supported without PC (BER threshold = 10^{-9})	90
5.16	Supported All Users in the System with PC at the Difference in Path Sequence of 0.3 km after 6 th Iteration, while only 65 out of 120 Users were Supported without PC (BER threshold = 10^{-9})	91
5.17	Supported 100% of the Active Users with PC at Some P_t not exceed -3dBm, while only 68% Users were Supported without PC at initial $P_t=1$ dBm	93
5.18	Supported Last 22 Users in Group C by Reducing the SNR of Groups A&B	94
5.19	Support All 110 Users with PC while only 74 out of 110 were Supported without PC	95
5.20	Supported 100% with PC, while without PC only 40 out of 50 Users at $P_t=-4.5$ dBm (BER threshold = 10^{-9})	97
5.21	Supported 100% with PC, while without PC only 58 out of 80 Users at $P_t=-3$ dBm (BER threshold = 10^{-9})	97
5.22	(a):Optimum Transmitted Power to Achieve the SNR in Figure 5.22(b)	98
5.22	(b) Supported 100% with PC while without PC, 54 out of 110 (BER threshold = 10^{-9})	98
5.23	Effect of Bit Rate on BER for $K=100$ users	99
5.24	Reduction in the Total Noises at the Numbers of Different Distances at Initial $P_t=-1$ dBm	100
5.25	Reduction in the Total Noises at the Numbers of Different Distances at Initial $P_t=3$ dBm 2 Km	101



LIST OF ABBREVIATIONS

ASE	Amplified Spontaneous Emission
BER	Bit Error Rate
BS	Base Station
CDMA	Code Division Multiple access
CPC	Centralized Power Control
DCF	Dispersion Compensating Fiber
DFH	Dynamic Frequency Hopping
DPC	Distributed Power Control
DS	Direct Sequence
FFH	Fast Frequency Hopping
Gbps	Giga bit per second
GF	Galois Field
IM/DD	Intensity Modulation/Direct Detection
LAN	Local Area Network
MAI	Multiple Access Interference
Mbps	Mega bit per second
MFH	Modified Frequency Hopping
MQC	Modified Quadratic Congruence
MS	Mobile station
OCDMA	Optical Code Division Multiple access
OOC	Optical Orthogonal Code
OOK	On-Off Keying



PC	Prime Code
PIIN	Phase Induced Intensity Noise
SIR	Signal to Interference Ratio
SAC	Spectral Amplitude Coding
SMF	Single Mode Fiber
SNR	Signal to Noise Ratio
TDM	Time Division Multiplexing
TDMA	Time division Multiple Access
TLS	Tunable Laser Source
TOF	Tunable Optical Filter
WDMA	Wavelength Division Multiple access



CHAPTER 1

INTRODUCTION

1.1 Background

Optical fibre is a medium in which communication signals are transmitted from one location to another, in the form of light guided through thin fibres of glass or plastic. These signals are digital pulses or continuously modulated analogue streams of light, representing information which can be regarded in the form of voice information, data information, computer information, video information, or any other types of information [1]-[2].

Optical fibres communication system is a promising candidate in providing the solution for tremendous growth of transmitted capacity demands in telecommunication and data communication services. It has been developed rapidly in the last two decades to meet the increasing demand in transmission capacity of the internet and multimedia applications. The main development has been done in the optical devices and technologies, while the systems still involve the use of simple modulation, detection, and multiplexing techniques. A few advanced optical communication techniques have also been proposed in the last decade to improve the performance of the system [2]-[4].

Optical fiber is generally chosen for systems which require higher bandwidth or span longer distances than electrical cabling can accommodate. The main benefits of fibre are due to the fact that it has exceptionally low loss, it allows long distances between

amplifiers or repeaters; and its inherently high data-carrying capacity, and as such, it requires thousands of electrical links to replace a single high bandwidth fibre cable.

1.2 Multiple Access Technique with Power Control Rule

In communication environment, a multiple access communication system is one of communication techniques. A multiple access is required for combining and separating traffics on a shared physical medium in case users are not at the same place, which is often well-known

There are three major types of multiple access, namely time division multiple access (TDMA), wavelength division multiple access (WDMA) [5] and optical code division multiple access (OCDMA).

The optical CDMA has several advantages over TDMA and WDMA; these include a complete utilization of the entire time frequency domain by each subscriber, the flexibility in network design and the security against interception, in addition to the lower multi-access interference (*MAI*).

There are several challenging points in researches and these can still be explored for a practical realization and development of the OCDMA. These include the multiple access interference (*MAI*) which is naturally present in almost all forms of the OCDMA, increasing the network capacity in terms of the number of concurrent users, as well as the codes which can support various traffic demands in small bandwidth and good bit error rate (BER) performance.

Based on the above discussion, the main source of noise for each user is the interference signals from other users. This interference limits the capacity in the fibre optic network. A number of methods have been proposed to reduce this interference such as using low cross-correlation codes [6], and applying power control method into the system [7].

Generally, power control methods adjusts the power level so that the signal-to-noise ratio is equal for all users, in spite of the different lengths between B.S and M.S, which will result in the determination of one B.S from many (usually the nearest B.S) that will supply the service to M.S [8],[9].

In the optical networks, the power control is used to adjust the carrier to the interference ratio (CIR), as a related with the fibre path loss [10]. The power control is used to support some of all simultaneous users when the quality of service (QoS) becomes lower than the boundary condition. The power control adjusts and optimizes the required power to achieve the target of QoS by controlling the transmitted power as a relationship with data rate and the number of users [11]. The QoS is determined by service utilization which is dependent on the bit rate (data stream).

1.3 The Quality of Service Parameters

In the field of computer networking and other packet-switched telecommunication networks, the QoS term refers to the resource reservation control mechanisms which are in addition to achieve the quality of service. The quality of service is the ability to provide different priorities to different applications [12], users, or data flows, or to

guarantee a certain level of performance to a data flow. For example, a required bit rate, delay, jitter, packet dropping probability and/or bit error rate which may be guaranteed. The QoS guarantees are important if the network capacity is insufficient (especially for real-time streaming multimedia applications such as voice over IP, online games and IP-TV, since these often require fixed bit rate and delay sensitive) and in networks where the capacity is a limited resource.

In the field of telephony, quality of service is defined in the ITU standard X.902 as "A set of quality requirements on the collective behaviour of one or more objects." The quality of service comprises requirements on all the aspects of a connection, such as the service response time, loss, signal-to-noise ratio, cross-talk, echo, interruptions, frequency response, loudness levels, and so on. A subset of telephony QoS is the grade of service (GoS) requirements, which comprises aspects of a connection related to the capacity and coverage of a network such as the guaranteed maximum blocking probability and outage probability. The QoS world network performance also includes the following concepts [13]:

- Dependability,
- Transmitted performance, and
- Charging correctness.

From the previous discussion, it is clear that the QoS indicator, by one or many parameters like the number of simultaneous users and data flows, is to guarantee a certain level of performance to a data flow. In this thesis, the *SNR* and *BER* were taken as the QoS to guarantee a certain level of performance to a data flow.

1.4 Problem Statement and Motivation

Dynamic Frequency Hoping-optical CDMA (DFH-OCDMA) system is one of the OCDMA techniques. As indicated in the earlier section, this technique has an advantage of having the highest number of simultaneous users among all OCDMA techniques. The highest number of simultaneous users is achieved and assumed as receiving fixed power which satisfies an adequate value of SNR [14]. Similarly in the DFH-OCDMA, the SNR and BER are respectively and seriously degraded with a minor change in the value of the received power. For example, a fix received power of $P_r = -10$ dBm is required to achieve the $BER = 10^{-9}$, a number of simultaneous users ($K=110$). With minor changes made to the received power value (-10 to -12) dBm indicated above, the BER is degraded from accepting the value above $BER = 10^{-7}$. Meanwhile, other techniques will have the approximately similar BER value [15]. Therefore, a rule to solve this high sensitivity in changing of the received power is therefore needed. This high sensitivity clearly appears or is derived with the near-far problem when some users received it from short-path lengths and from other long path lengths. This will result in a low SNR for the some users (i.e. usually the far users) [16]. Therefore, the use of power controlling method is proposed to solve the near-far problem in DFH-OCDMA. In other words, the power control is a key for many technologies which are used to adjust the received power with the target SNR as an optimum received power (not too high and too low values).

Many power control techniques have been proposed in the optical network, i.e. for both the transmitter (T_x) and receiver (R_x), so as to optimize the optical transmitted power. The optical power control for the OCDMA networks was discussed in [16] -