



UNIVERSITI PUTRA MALAYSIA

**IMPROVEMENTS IN DESIGN OF LOCAL FLUORESCENT
ELECTRONIC BALLASTS IN COMPLIANCE WITH THE RELATED
LOCAL AND INTERNATIONAL STANDARDS**

ZULKEFLI BIN YAACOB

FK 2001 61

**IMPROVEMENTS IN DESIGN OF LOCAL FLUORESCENT
ELECTRONIC BALLASTS IN COMPLIANCE WITH THE RELATED
LOCAL AND INTERNATIONAL STANDARDS**

By

ZULKEFLI BIN YAACOB

**Thesis Submitted in Fulfilment of the Requirement for the
Degree of Master of Science in the Faculty of Engineering
Universiti Putra Malaysia**

February 2001



Abstract of thesis presented to the Senate of Universiti Putra Malaysia in fulfilment of the requirement of the degree of Master of Science.

**IMPROVEMENTS IN DESIGN OF LOCAL FLUORESCENT
ELECTRONIC BALLASTS IN COMPLIANCE WITH THE RELATED
LOCAL AND INTERNATIONAL STANDARDS**

By

ZULKEFLI BIN YAACOB

February 2001

Chairman: Ir. Dr. Md. Yusof Ismail

Faculty: Engineering

The fluorescent electronic ballast has been in the market for a long time but has not created any great impact in the illumination industry due to its high initial cost of investment compared to the conventional magnetic ballast. With the advancement in power electronics and utilization of power semiconductor which is available commercially today, it is now possible to implement almost every type of desired conversion of current, voltage or frequency and availability of electronic components with higher power ratings. Thus, it is now possible to manufacture an economically priced, light weight, lower watt-loss and high quality with maximum performance electronic ballast which is compatible with all types of fluorescent luminaries.



This study is undertaken to improve the design of existing locally manufactured electronic ballasts. The study indicated that many of these commercial electronic ballasts only have partial or minimum compliance requirements or none at all to the related local and international standards, namely MS IEC 928, MS IEC 929 and EMC requirements as stipulated by SIRIM Berhad. From a survey on nine different ballast manufacturers, only seven manufacturers conducted two tests on MS IEC 928 and MS IEC 929 and only two manufacturers conducted a complete list of tests to ascertain whether their product comply with the related local and international standards. Since electronic ballast is listed as one of the electrical controlled items by the Department of Electricity and Gas Supply of Malaysia (DEGSM), it is crucial that the EMC test be imposed prior to ballast approval.

A directive was issued by the Malaysian government on the 3rd of July 1998 to implement energy conservation and to promote the use of energy efficient equipment specifically on lighting luminaries and lighting control systems. DEGSM noted the limitations of fluorescent ballast watt-loss hence, this study is undertaken to meet the implementation of energy conservation regulations/act in the near future.

The study discussed the advantages and disadvantages of electronic ballasts, their operation and performance characteristics and problems encountered during their normal operations, for instance, surges, starting current, power factor, watt-loss.

ambient temperature and environmental effects, lamp/ballast premature failures, harmonics and electromagnetic (EM) disturbances, efficiency and dimming.

Various samples of electronic ballast were collected and tested for compliances with local and international standards. It was found that many samples failed the tests on total harmonic distortion (THD) which exceeded the 25% limit.

From the test data collected on the study, the findings from the analysis on the operation, performance, design and construction of the typical electronic ballast were utilised in the construction of two improved versions of electronic ballast prototypes. The two improved versions were retested and both passed all the tests conducted on them with better results.

Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk ijazah Master Sains.

**PEMBAIKAN DALAM REKA BENTUK BALLAST ELEKTRONIK
PENDAFLUOR TEMPATAN DI DALAM MEMENUHI PIAWAI-PIAWAI
TEMPATAN DAN ANTARABANGSA YANG BERKAITAN**

Oleh

ZULKEFLI BIN YAACOB

Februari 2001

Pengerusi: Ir. Dr. Md. Yusof Ismail

Fakulti: Kejuruteraan

Ballast elektronik bagi kelengkapan lampu pendafluor telah lama berada di dalam pasaran tetapi tidak dapat memberi sebarang impak yang ketara di dalam industri pencahayaan disebabkan oleh kos pelaburan awal yang agak tinggi jika dibandingkan dengan ballast konvensional jenis magnetik. Dengan kemajuan di dalam bidang elektronik kuasa dan penggunaan semikonduktor kuasa secara komersial yang terdapat sekarang ini, ianya berupaya untuk melaksanakan hampir setiap jenis penukaran yang diinginkan bagi arus, voltan atau frekuensi dan kedapatannya komponen-komponen elektronik yang berkadaran kuasa tinggi. Maka dengan itu, buat masa ini, adalah berkemungkinan besar untuk menghasilkan ballast elektronik pada kos yang lebih ekonomik, ringan, berkehilangan watt rendah dan berkualiti tinggi pada pelaksanaan yang maksima bersesuaian dengan semua jenis kelengkapan lampu pendafluor.

Kajian ini adalah bertujuan untuk memperbaiki reka bentuk bagi ballast elektronik buatan tempatan sedia ada. Kajian menunjukkan bahawa kebanyakan ballast elektronik kommersil tidak mempunyai, hanya mempunyai sebahagian atau pematuhan minima ke atas keperluan berdasarkan piawai-piawai tempatan dan antarabangsa berkaitan seperti MS IEC 928, MS IEC 929 dan keperluan bagi kesesuaian elektromagnetik (EMC) sepertimana yang diperlukan oleh SIRIM Berhad. Daripada kajian yang telah dibuat ke atas 17 contoh yang dikumpulkan daripada sembilan pengeluar ballast elektronik yang berlainan, hanya tujuh pengeluar telah melakukan dua ujian bagi MS IEC 928 dan MS IEC 929 dan hanya dua pengeluar sahaja telah melakukan senarai lengkap ujian. Ini adalah penting kerana ballast elektronik adalah merupakan salah satu daripada barangan elektrik terkawal oleh Jabatan Bekalan Elektrik dan Gas Malaysia (JBEGM).

Kajian ini juga membincangkan tentang kebaikan dan keburukan tentang ballast elektronik, ciri-ciri operasi dan pelaksanaan dan juga masalah-masalah yang dihadapi semasa ianya beroperasi secara normal seperti penerpaan, arus mula, faktor kuasa, kehilangan watt, suhu sekeliling dan kesan keatas alam sekitar, kegagalan pra-matang bagi lampu/ballast, harmonik dan kesan gangguan elektromagnetik (EM), kecekapan dan pemalapan.

Pelbagai contoh ballast elektronik telah dikumpulkan dan diuji-kaji bagi memastikan pematuhan berdasarkan kepada keperluan dan telah didapati bahawa kebanyakan contoh yang diuji telah gagal bagi ujian "Jumlah Herotan Harmonik"

yang mana melebihi tahap 25%. Daripada data ujian yang dikumpulkan di atas kajian yang telah dibuat, analisa ke atas operasi, pelaksanaan, reka bentuk dan pembinaan bagi ballast biasa telah digunakan di dalam pembinaan dua versi contoh sulung ballast elektronik yang telah diperbaiki. Ianya telah diuji sebagaimana yang telah dilakukan keatas contoh-contoh yang telah dikumpulkan di mana keduanya telah didapati lulus kesemua ujian berkenaan dengan contoh sulung yang kedua telah memberikan keputusan yang lebih baik.

Pada bahagian akhir kajian, data-data telah terkumpul telah dijadualkan untuk perbincangan dan perbandingan secara keseluruhan dalam menentukan sama ada contoh-contoh dan contoh sulung tersebut telah dapat memenuhi keperluan piawai-piawai berkenaan secara sepenuhnya atau tidak. Kesimpulan ke atas kajian kemudiannya telah dibuat. Penyelidikan lanjut dan perakuan telah dicadangkan berdasarkan kepada pendekatan reka bentuk baru, topologi-topologi dan teknik-teknik bagi pembinaan ballast elektronik dengan merujuk kepada penyelidikan yang dijalankan oleh berbagai pereka ballast elektronik.

ACKNOWLEDGEMENTS

A great effort went into the writing-up of this thesis which has been a great experience and an enrichment of knowledge. I would like to thank the following people and organisations for their contributions, without which this thesis could never have been completed.

First and always, my family. My ever-patient and supportive wife and two daughters, who have made many sacrifices during the duration and understood my need to further my studies. Thank you for your sincere emotional support, patience and understanding.

Thank you also to Ir. Dr. Md. Yusof Ismail, my supervisor and co-supervisors, Ir. Dr. Norman Mariun, Dr. Megat Hamdan Megat Ahmad and Dr. Mohd. Sapuan Salit for their tireless effort, guidance and generous recommendations and insights throughout the process of the writing-up of the thesis.

Thank you also to the electronic ballast manufacturers for their cooperation in allowing me to utilise their available technical resources and testing facilities during the research and for the analysis conducted on the thesis.



I certify that an Examination Committee met on 6th Februari 2001 to conduct the final examination of Zulkefli Yaacob on his Master of Science thesis entitled “Improvements in Design of Local Fluorescent Electronic Ballasts in Compliance with Related Local and International Standards” in accordance with the Universiti Pertanian Malaysia (higher Degree) Act 1980 and Universiti Pertanian Malaysia (Higher Degree) Regulations 1981. The Committee recommends that the candidate be awarded the relevant degree. Members of the Examination Committee are as follows:


SHAMSUDDIN SULAIMAN, Ph. D.,
Associate Professor,
Faculty of Engineering
Universiti Putra Malaysia
(Chairman)

MD. YUSOF ISMAIL , Ph. D., P.Eng.,
Associate Professor,
Faculty of Engineering
Universiti Putra Malaysia
(Member)

NORMAN MARIUN, Ph. D., P.Eng.,
Associate Professor,
Faculty of Engineering
Universiti Putra Malaysia
(Member)

MEGAT MOHAMAD HAMDAN MEGAT AHMAD, Ph. D.,
Faculty of Engineering
Universiti Putra Malaysia
(Member)

MOHD. SAPUAN SALIT, Ph. D.,
Faculty of Engineering
Universiti Putra Malaysia
(Member)



MOHD. GHAZALI MOHAYIDIN, Ph. D.,
Professor/Deputy Dean of Graduate School,
Universiti Putra Malaysia.

Date:

This thesis submitted to the Senate of Universiti Putra Malaysia was accepted as fulfilment of the requirement for the degree of Master of Science.



MOHD. GHAZALI MOHAYIDIN, Ph.D.

Professor

Deputy Dean of Graduate School

Universiti Putra Malaysia

Date:

DECLARATION

I hereby declare that the thesis is based on my original work except for quotations and citations which have been duly acknowledged. I also declare that it has not been previously or concurrently submitted for any other degree at UPM or other institutions.



Name: ZULKEFLI BIN YAACOB

Date : 28/2/2001

TABLE OF CONTENTS

	Page	
ABSTRACT	ii	
ABSTRAK	v	
ACKNOWLEDGEMENTS	viii	
APPROVAL SHEET	ix	
DECLARATION	xi	
LIST OF TABLES	xiv	
LIST OF FIGURES	xv	
LIST OF ABBREVIATIONS	xix	
GLOSSARY OF TERMS	xxii	
CHAPTER		
I	INTRODUCTION	
1.1	Energy Consumption in Malaysia	1
1.2	Test Standards Practices by Other Countries	8
1.3	Recent Energy Efficiency Programs and Activities in Malaysia	8
1.4	Energy Using Products	11
1.5	Fluorescent Ballasts	12
1.6	Energy Efficient Lighting and Lighting Controls Strategies	14
1.7	Energy Conservation and Management	15
1.8	Objectives of the Study	18
II	LITERATURE REVIEW	
2.1	Fluorescent Luminaries	19
2.1.1	Fluorescent Lamps	19
2.1.2	Power Factor Capacitor	23
2.1.3	Glow Starter	24
2.1.4	Fluorescent Ballasts	25
2.2	Factors Effecting Performance of Fluorescent Luminaries	31
2.3	Testing of Electronic Ballasts by SIRIM Berhad	33
2.4	Advantages and Disadvantages of Electronic Ballasts for Fluorescent Lamps	35
2.5	Harmonic and its Impact on Electrical Safety	37
2.6	Electromagnetic Compatibility (EMC)	41
2.7	Effects of Electronic Ballast Operation and performance to Environment and on Utility Voltage Stability	42
2.8	Electromagnetic Interference (EMI) from High Frequency Ballasts	46



2.9	Overview on the Principles of Electronic Ballasts for Fluorescent Lamps.	50
2.10	Principles of Electronic Ballast Circuit Design	51
	2.10.1 Two-Stage Electronic Ballasts	52
	2.10.2 Single-Stage Electronic Ballasts	53
III	METHODOLOGY	
3.1	Introduction	64
3.2	Preliminary Design Approach	65
	3.2.1 Model Implementation in Circuit Simulators	66
	3.2.2 Fluorescent Lamps	67
	3.2.3 Electronic Ballast	81
IV	DESIGN AND CONSTRUCTION	
4.1	Typical Electronic Ballast Design	84
4.2	Analysis, Design and Experiment of High-Power Factor Electronic Ballast	86
4.3	Steady State Analysis and Design Issues	96
4.4	Lamp Power Control	106
4.5	Simulation and Experimental Results	108
4.6	Efficiency Improvement of Electronic Ballast	112
4.7	Design and Analysis of Dimming Electronic Ballast	117
V	RESULTS AND DISCUSSION	
5.1	Introduction	124
5.2	Test Standards and Procedures	125
5.3	Design and Construction of Electronic Ballast Prototypes	126
5.4	Test Results on Electronic Ballast Testing	127
5.5	Discussion on Results	132
5.6	Summary of the Study	136
5.7	Research Findings and Discussion	138
VI	CONCLUSION AND RECOMMENDATIONS	
6.1	Introduction	141
6.2	Conclusion	142
6.3	Recommendations and Further Works	144
	REFERENCES	149
	APPENDICES	
	A	155
	B	167
	BIODATA OF AUTHOR	223



LIST OF TABLES

Table		Page
1.1	Statistics of main utilities and licensees	7
1.2	Electrical power consumption on Peninsular Malaysia	7
1.3	Maximum allowable watt-loss for fluorescent ballasts by DEGSM	12
1.4	Minimum allowable coefficient of performance (COP) for electric fans by DEGSM	13
2.1	Multiplication factors for fluorescent lamp burning hours	22
2.2	Fluorescent ballast sound ratings	33
2.3	Variations of the voltage control charge pump	58
3.1	The V-I characteristics of Osram FO 32/741 T8 instant start fluorescent lamp	70
3.2	Simulation and measurement results of the lamp	74
3.3	Experimental results on efficiency improvement of electronic ballast	117
4.1	Comparison of the test results between selected ballast samples and prototypes	134
5.1	Comparison of the test results between selected 2 X 36 W electronic ballast samples and prototypes	151



LIST OF FIGURES

Figure		Page
2.1	Fluorescent Lamp	21
2.2	Energy Distribution for Fluorescent Lamp	22
2.3	Waveform Distortion Due to Harmonic Effects	38
2.4	General Fluorescent Lamp Characteristic	50
2.5	Block Diagram of an Electronic Ballast	51
2.6	Two-stage Electronic Ballast	53
2.7	Half-bridge with One Integrated Boost Converter	54
2.8	Half-bridge with Two Integrated Boost Converters	55
2.9	Mains Current without EMC Filter and DC Link Voltage of an Electronic Ballast with Boost Converter at 230 V _{ac}	55
2.10	Half-bridge with One Integrated Buck Boost Converter	56
2.11	Half-bridge with Two Integrated Buck Boost Converters	57
2.12	Half-bridge with Voltage Controlled Charge Pump	57
2.13	Mains Current from a Voltage Controlled Charge Pump Circuit	59
2.14	Half-bridge with Combined Current/Voltage Charge Pump	59
2.15	Improved Charge Pump Topology	60
2.16	Charge Pump with Additional Inductor	61
2.17	Improved Charge Pump with Additional Inductor	62
2.18	Another Current Controlled Charge Pump	63
3.1	A Measurement Circuit of Fluorescent Lamp	69



3.2	V-I Characteristics Plot of Osram FO 32W/741 T8 Instant Start Fluorescent Lamp	70
3.3	The Proposed PSpice Circuit for the Lamp Model	73
3.4	A Circuit for Testing the Proposed Lamp Model	73
3.5(a)	The Negative Dynamic Resistance Characteristics of the Lamp Obtained from Simulation	75
3.5(b)	The Negative Dynamic Resistance Characteristics of the Lamp Obtained from Experiment	75
3.6	A Simplified Schematic of the Half-bridge Resonant Ballast	76
3.7	The Plot of the Normalised Current Versus Operating Frequency with Various $Z_{o(n)}$ and $V_{H(n)}$ as Parameters	78
3.8(a), (c)	The Simulation Results of the System	80
3.8(b), (d)	The Experimental Results of the System	80
3.9	The Typical Ballast Circuit	82
3.10	Comparison of Power Input	83
3.11	Comparison of Light Output	83
4.1	The PF Correction Converter Block Diagram	88
4.2	The Required Output Characteristics of Box to Achieve PF Correction	88
4.3	High Power Factor AC/DC Converter	89
4.4	Characteristics of a Series Resonance Converter	89
4.5	High PF Correction AC/DC Converter	90
4.6	The Basic Charge Pump PF Correction AC/DC Converter	90
4.7	VS-CPPFC Electronic Ballast	91



4.8	The Simplified VS-CPPFC Converter	91
4.9	Switched Waveform of Figure 3.19	92
4.10	CPPFC Electronic Ballast	96
4.11	Equivalent Circuit of Figure 3.21	97
4.12	Eight Topological Stages	98
4.13	Key Waveforms of the Electronic Ballast	99
4.14	Symmetrical CPPFC Electronic Ballast	105
4.15	The Lamp Power Control Diagram	108
4.16	DC Bus Voltage Across the Bulk Capacitor, C_B During Preheat and Start-up Modes	109
4.17	The Simulated Switching Waveforms	110
4.18	The Experimental Switching Waveforms	110
4.19	The Measured Input Line Current Waveforms	111
4.20	The Measured Switching Waveforms of the Symmetrical CPPFC Electronic Ballast	111
4.21	Half-bridge Inverter Circuit Configuration	113
4.22	The Block Diagram of the Improved Efficiency Electronic Ballast	116
4.23	The Power Circuit for Dimming Electronic Ballast	119
4.24	Half-bridge Inverter Output Waveforms at $\omega_s > \omega_o$	120
5.1	The Block Diagram of Electronic Ballast Prototype No. 1	127
5.2	The Block Diagram of Electronic Ballast Prototype No. 2	127



5.3	The Schematic Diagram of Electronic Ballast Prototype No. 1	128
5.4	The Schematic Diagram of Electronic Ballast Prototype No. 2	129
5.5	Photograph of Electronic Ballast Prototype No. 1	130
5.6	Photograph of Electronic Ballast Prototype No. 2	130
6.1	CIC-CPPFC Conceptual Circuit	145
6.2	CIC-CPPFC Electronic Ballast	145
6.3	CIC-CPPFC Converter Diagram and its Waveforms	146



LIST OF ABBREVIATIONS

AC	Alternating Current
ANN	Artificial Neural Network
ANSI	American National Standards Institute
BSI	British Standard Institute
CBM	Certified Ballast Manufacturers Association
CCF	Current Crest Factor
CENELEC	European Committee for Electrotechnical Standardisation
CFL	Compact Fluorescent Lamp
CIC	Continuous Input Current
CISPR	International Special Committee on Radio Interference
CO	Carbon Monoxide
CO ₂	Carbon Dioxide
COP	Coefficient of Performance
CPPFC	Charge Pump Power Factor Correction
CS	Current Source
dB	Decibels
DC	Direct Current
DCM	Discontinuous Current Mode
DEGSM	The Department of Electricity and Gas Supply of Malaysia
DSM	Demand Side Management
ECM	Energy Centre of Malaysia (Pusat Tenaga Malaysia)
EEO	Energy Efficiency Officer
EM	Electromagnetic
EMC	Electromagnetic Compatibility
EMF	Electromotive Force
EMI	Electromagnetic Interference
ESD	Electrostatic Discharge
ESR	Equivalent Series Resistance
EUT	Equipment Under Test



FCC	Federal Communications Commission
FLEB	Fluorescent Lamp with Electronic Ballast
GDP	Gross Domestic Product
GTO	Gate Turn-off
HVAC	Heating, Ventilating and Air-conditioning
HF	High Frequency
HID	High Intensity Discharge
HPS	High Pressure Sodium
HVDC	High Voltage Direct Current
IC	Integrated Circuit
IEC	International Electrotechnical Commission
IEEE	Institution of Electrical and Electronics Engineers
IES	Illuminating Engineers Society
IGBT	Insulated Gate Bipolar Transistor
IPP	Independent Power Producer
ISO	International Organisation for Standardisation
KPBE	Ketua Pengarah Bekalan Elektrik (Director General of Electricity Supply)
LISN	Line Impedance Simulation Network
LLS	Lembaga Letrik Sabah (Sabah Electricity Board)
LPW	Lumen per Watt
MOSFET	Metal Oxide Semiconductor Field Effect Transistor
MS	Malaysian Standard
NEC	National Electrical Code
NEMA	National Electrical Manufacturers Association
NLPIP	National Lighting Product Information Program
NTC	Negative Temperature Coefficient
PCB	Printed Circuit Board
PF	Power Factor
PFC	Power Factor Correction
PLC	Power Line Carrier



PSpice	A member of SPICE family of Circuit Simulators
PWD	Public Works Department
PWM	Pulse Width Modulation
RCCB	Residual Current Circuit Breaker
RF	Radio Frequency
RFI	Radio Frequency Interference
RLO	Relative Light Output
RMS	Root Mean Square
SCR	Silicon Control Rectifier
SESCO	Sarawak Electricity Supply Corporation
SIRIM	Standards and Industrial Research Institute of Malaysia
SO ₂	Sulphur Dioxide
SPICE	Simulation Program with Integrated Circuit Emphasis
SLICE	Circuit simulator program developed by Harris Semiconductor
THD	Total Harmonic Distortion
TNB	Tenaga Nasional Berhad
UDCS	User Defined Controlled Source
UL	Underwriters Laboratories of USA
UPS	Uninterruptible Power Supply
US FDA	Food and Drug Administration of USA
UVLO	Under-voltage Lockout
VCO	Voltage Cut-out
VDC	DC Voltage Source
VS	Voltage Source



GLOSSARY OF TERMS

The following technical and lighting terminologies are frequently used with reference to the study. These are presented in alphabetical order and explained so that they are easy to understand. For a complete range of lighting terminology and precise definitions, please refer to the IES Lighting Handbook, 1981.

Active Filter	A filter which is switched in response to demand to attenuate or eliminate harmonic components and compensate for active power.
Advance, Firing Angle	The angle at which a thyristor starts conduction in advance of, and relative to, the instant when the thyristor forward voltage falls to zero in a converter. Used in relation to the inverting mode of operation.
Ambient temperature	The temperature of the general mass of air or cooling medium into which heat is finally transferred from a hot body.
Asymmetrical	Not uniform in characteristic or construction.
Avalanche	A chain reaction which occurs when minority carriers are accelerated by a high electric field, so liberating further carriers leading to a sharp increase in reverse current and breakdown.
Avalanche Diode	A diode which may temporarily be exposed to voltages of the order of the breakdown voltage.

Ballast	A device used with gaseous discharge lamps that provides necessary conditions to start and operate the lamps.
Ballast Factor	The percentage of light produced by a commercial ballast compared to a reference or standard ballast.
Bidirectional	Capable of current conduction in both directions, for example a triac.
Breakdown Voltage	The reverse voltage level at which the reverse current increases rapidly in a diode.
Bridge	Full-wave converter.
Chopping	A technique of rapidly switching on and off a source of voltage.
Clamping Voltage	Introduction of a voltage reference level to a pulsed or transient waveform to limit the peak value.
Closed-loop	A system in which information regarding the state of a controlled quantity is fed back to the controlling element.
Colour Rendering	An expression for the effect of a light source on the colour appearance of objects in comparison with their colour appearance under a reference light source.
Commutating Diode	A diode placed across a DC load to permit transfer of load current away from the source, and so allow the

thyristors in the DC source to turn off. In addition to permitting commutation of the source thyristors, the diode will prevent reversal of the load voltage.

Conducting Angle	The angle over which a device conducts.
Conduction Loss	The energy dissipated within the device during the on-state conduction.
Constant-current Inverter	An inverter fed from a DC source with a large series inductor, so that over each inverter cycle the source current remains almost constant.
Constant-voltage Inverter	An inverter fed from a DC source with a large parallel capacitor, so that over each inverter cycle the source voltage remains almost constant.
Converter	A circuit which convert AC to DC or vise versa.
Critical Damping	Damping which gives most rapid transient response without overshoot or oscillation.
Damping	Extraction of energy from an oscillating system.
D.C Link	Intermediate DC stage between two systems of different frequency.
Delay, Firing Angle	The retarded angle at which a thyristor starts conducting relative to that instant when the thyristor

