

University of Groningen

Robust state-feedback stabilization of discrete-time linear polytopic positive systems using LMIs

Esteves Rosa, Tábita; Morais, Cecília F.; Oliveira, Ricardo C.L.F.

IMPORTANT NOTE: You are advised to consult the publisher's version (publisher's PDF) if you wish to cite from it. Please check the document version below.

Document Version

Publisher's PDF, also known as Version of record

Publication date:
2019

[Link to publication in University of Groningen/UMCG research database](#)

Citation for published version (APA):

Esteves Rosa, T., Morais, C. F., & Oliveira, R. C. L. F. (2019). *Robust state-feedback stabilization of discrete-time linear polytopic positive systems using LMIs*. 67-68. Abstract from 38th Benelux Meeting on Systems and Control 2019, Lommel, Belgium.

Copyright

Other than for strictly personal use, it is not permitted to download or to forward/distribute the text or part of it without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license (like Creative Commons).

The publication may also be distributed here under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license. More information can be found on the University of Groningen website: <https://www.rug.nl/library/open-access/self-archiving-pure/taverne-amendment>.

Take-down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Downloaded from the University of Groningen/UMCG research database (Pure): <http://www.rug.nl/research/portal>. For technical reasons the number of authors shown on this cover page is limited to 10 maximum.

Robust state-feedback stabilization of discrete-time linear polytopic positive systems using LMIs

Tábitha E. Rosa*, Cecília F. Morais**, Ricardo C.L.F. Oliveira**

* University of Groningen, 9747 AG, Groningen, The Netherlands

** University of Campinas, 13083-852, Campinas-SP, Brazil

Email: t.esteves.rosa@rug.nl

1 Introduction

A class of systems that properly represents several real phenomena is called *positive systems*, where the state variables, inputs and outputs, can only assume non-negative values. This study field has some open problems since many of the well-established results for linear systems cannot be directly applied to positive systems. This abstract proposes a new state-feedback design condition for discrete-time linear polytopic positive systems via the extension of the techniques given in [2] and [3], that use linear matrix inequalities (LMIs) combined with scalar searches.

2 Results

Consider the following discrete-time linear polytopic positive system

$$x(k+1) = A(\alpha)x(k) + B(\alpha)u(k) \quad (1)$$

where $x(k) \in \mathbb{R}^n$ represents the state vector, $u(k) \in \mathbb{R}^m$ is the control input. The system matrices belong to a polytopic domain, i.e., they can be written as a convex combination of the N known vertices: $(A, B)(\alpha) = \sum_{i=1}^N \alpha_i (A_i, B_i)$, $\alpha \in \Lambda$, and α is a time-invariant parameter belonging to the unit simplex $\Lambda = \{\sum_{i=1}^N \alpha_i = 1, \alpha_i \geq 0, i = 1, \dots, N\}$. Furthermore, all entries of matrices $(A, B)(\alpha)$ are positive (internally positive system). In order to asymptotically stabilize and guarantee the positiveness of (1) in closed-loop, we consider the following robust state-feedback control law: $u(k) = Kx(k)$. The main result of this work is presented next.

Theorem 1 For given scalars $\gamma \neq 0$ and ε , if there exist matrices $P(\alpha) = P(\alpha)' > 0 \in \mathbb{R}^n$, $F(\alpha)$ and $G(\alpha) \in \mathbb{R}^{n \times n}$, $L \in \mathbb{R}^{m \times n}$ and a diagonal matrix $S \in \mathbb{R}^{n \times n}$, such that $A(\alpha)S + B(\alpha)L \geq 0$ and

$$\begin{bmatrix} \begin{pmatrix} A(\alpha)F(\alpha) + \\ F(\alpha)'A(\alpha)' - P(\alpha) \end{pmatrix} & * & * \\ \begin{pmatrix} (A(\alpha)G(\alpha) + \varepsilon B(\alpha)L)' \\ -F(\alpha) \end{pmatrix} & P(\alpha) - G(\alpha) - G(\alpha)' & * \\ (B(\alpha)L)' - \gamma F(\alpha) & \gamma(\varepsilon S - G(\alpha)) & \gamma(S + S') \end{bmatrix} < 0$$

hold $\forall \alpha \in \Lambda$, then $K = LS^{-1}$ assures the positiveness and the closed-loop asymptotic stability of (1).

The proof follows the same steps of Theorem 1 from [3] as well as the procedure to obtain the finite set of LMIs (programmable).

Supported by the Brazilian agencies CAPES, CNPq (Grant 408782/2017-0), and FAPESP (Grant 2017/18785-5) and the STW project 15472 of the STW Smart Industry 2016 program.

To illustrate the effectiveness of the technique, consider the following example which analyses the state-space system whose polytopic matrices have the following vertices

$$\begin{bmatrix} A_1 & A_2 \\ A_3 & A_4 \end{bmatrix} = \begin{bmatrix} 7.307 & 3.154 & 5.515 & 9.837 & 4.432 & 7.749 \\ 4.725 & 2.438 & 3.764 & 9.150 & 4.266 & 7.402 \\ 11.18 & 5.754 & 10.028 & 11.158 & 5.246 & 9.410 \\ \hline 9.321 & 4.313 & 7.727 & 11.371 & 5.684 & 9.426 \\ 9.287 & 4.289 & 7.688 & 11.632 & 5.665 & 9.567 \\ 11.47 & 5.554 & 9.581 & 6.928 & 3.268 & 5.698 \end{bmatrix}$$

$$\begin{bmatrix} B_1 \\ B_2 \\ B_3 \\ B_4 \end{bmatrix} = \begin{bmatrix} 3 & 2 & 5 \\ 4 & 4 & 5 \\ 4 & 4 & 5 \\ 5 & 5 & 3 \end{bmatrix}$$

The main goal is to compare Theorem 1 (T1) and other methods from the literature (LMIs (24), (25) and (27) from [1] adapted to handle the stabilization problem). In order to test T1, we consider $\gamma = -1 \times 10^5$ and the scalar search $\varepsilon \in [10^{-5}, 10]$, containing 7 logarithmically spaced values.

All three conditions from [1] were not able to provide stabilizing gains. Considering T1 with the mentioned scalar search, only $\varepsilon = 10^{-2}$ and 10^{-3} were able to provide feasible solutions, respectively providing the following controllers (truncated with 4 decimal digits)

$$\begin{bmatrix} K(\varepsilon = 10^{-2}) \\ K(\varepsilon = 10^{-3}) \end{bmatrix} = \begin{bmatrix} -2.2316 & -1.0491 & -1.8383 \\ -2.2314 & -1.0485 & -1.8378 \end{bmatrix}$$

These results validate the advantages of employing slack variables (matrices $F(\alpha)$ and $G(\alpha)$) and scalar searches in order to reduce the conservatism of the synthesis condition at the price of an increase in the computational burden. Finally, note that in Theorem 1 it is not necessary to impose that the Lyapunov matrix is constant or diagonal to obtain robust controllers that guarantee the positiveness and stability of the system.

References

- [1] Y. Ebihara, D. Peaucelle, and D. Arzelier. LMI approach to linear positive system analysis and synthesis. *Systems & Control Letters*, 63:50–56, 2014.
- [2] T.E. Rosa, C.F. Morais, and R.C.L.F. Oliveira. New robust LMI synthesis conditions for mixed gain-scheduled reduced-order DOF control of discrete-time LPV systems. *Int. J. Robust Nonlinear Control*, 28(18):6122–6145, 2018.
- [3] H. S. Vieira, R.C.L.F. Oliveira, and P.L.D. Peres. Robust stabilization and \mathcal{H}_∞ control by means of state-feedback for polytopic linear systems using lmis and scalar searches. In *American Control Conference (ACC), 2015*, pages 5966–5973, Chicago, IL, USA, 2015. IEEE.