

A Priori Error Bounds for Model Reduction of Interconnected Systems

Citation for published version (APA):

Janssen, L. A. L., Besselink, B., Fey, R., & van de Wouw, N. (2022). *A Priori Error Bounds for Model Reduction of Interconnected Systems*. Abstract from 41st Benelux Meeting on Systems and Control 2022, Brussels, Belgium.

Document license:

TAVERNE

Document status and date:

Published: 05/07/2022

Document Version:

Publisher's PDF, also known as Version of Record (includes final page, issue and volume numbers)

Please check the document version of this publication:

- A submitted manuscript is the version of the article upon submission and before peer-review. There can be important differences between the submitted version and the official published version of record. People interested in the research are advised to contact the author for the final version of the publication, or visit the DOI to the publisher's website.
- The final author version and the galley proof are versions of the publication after peer review.
- The final published version features the final layout of the paper including the volume, issue and page numbers.

[Link to publication](#)

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal.

If the publication is distributed under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license above, please follow below link for the End User Agreement:

www.tue.nl/taverne

Take down policy

If you believe that this document breaches copyright please contact us at:

openaccess@tue.nl

providing details and we will investigate your claim.

A priori error bounds for model reduction of interconnected systems

Lars Janssen, TU/e*

Email: l.a.l.janssen@tue.nl

Bart Besselink, RUG†

Email: b.besselink@rug.nl

Rob Fey, TU/e*

Email: r.h.b.fey@tue.nl

Nathan van de Wouw, TU/e*

Email: n.v.d.wouw@tue.nl

1 Introduction

Many complex models of dynamic (multi-)physical systems are naturally based on an interconnection of subsystems. The models of interconnected systems often have a high number of states, which makes controller synthesis, simulation and analysis computationally expensive. This motivates the need for model order reduction (MOR) techniques applicable to such systems. *Subsystem reduction*, where each of the subsystems is reduced individually, is a completely modular approach. Hence, the interconnection structure of the high-order model is preserved and the computationally challenging reduction of one very high-dimensional model is avoided by dividing the problem into multiple smaller problems. However, although subsystem reduction methods will lead to accurate reduced-order representations of the high-order subsystems, this does not directly mean that the reduced-order interconnected system is also accurate. Based on [1], we introduce a method which gives an a priori error bound on the frequency response of the reduced interconnected system based on the a priori error bounds of the reduced subsystems.

2 Preliminaries

We study systems of k linear time-invariant (LTI) subsystems that can be aggregated and represented by block-diagonal transfer function $G = \text{diag}(G_1, \dots, G_k)$. The subsystems are interconnected via matrix K . The external inputs u and outputs y are connected to the subsystems via external input and output matrix L and M , respectively. In subsystem reduction, each of the subsystems G_j is reduced to an approximate reduced-order subsystem \hat{G}_j and the aggregate is given by $\hat{G} = \text{diag}(\hat{G}_1, \dots, \hat{G}_k)$. The high-order interconnected system G_c and the reduced-order interconnected system \hat{G}_c with $\hat{y} = \hat{G}_c u$ (Figure 1), are then

$$G_c = MG(I - KG)^{-1}L, \quad \hat{G}_c = M\hat{G}(I - K\hat{G})^{-1}L. \quad (1)$$

3 Methodology

For balanced truncation, a widely used MOR method, an upper bound on the \mathcal{H}_∞ -norm of the difference between the high-order and reduced-order systems is available a priori.

*Dynamics and Control, Mechanical Engineering, Eindhoven University of Technology, P.O. Box 513, 5600 MB Eindhoven, The Netherlands

†Bernoulli Institute for Mathematics, Computer Science and Artificial Intelligence, University of Groningen, P.O. Box 407, 9700 AK Groningen, The Netherlands




Figure 1: Block diagrams of G_c (top left), \hat{G}_c (bottom left), and $G_c - \hat{G}_c$ represented by N_0, W and Δ (right).

In this work, we extend a priori knowledge of subsystem errors $\|G_j - \hat{G}_j\|_\infty$ to knowledge on $\|G_c - \hat{G}_c\|_\infty$. To do so, we define all subsystem reduction errors as an uncertain system $\Delta := G - \hat{G}$. Then, we can model $G_c - \hat{G}_c$ as a closed loop between N and Δ as shown in Figure 1. Here, the nominal system $N := N_0 W$ is a function of $N_0(G, K, L, M)$ and weighting matrix $W := \text{diag}(w_1 I, \dots, w_k I, w_c I)$. Using this framework, the structured singular value μ , a powerful tool from robust control, can be used. Namely, if N is internally stable, then

$$\left. \begin{aligned} \|G_c - \hat{G}_c\|_\infty &\leq w_c^{-1}, \text{ and} \\ \|G_j - \hat{G}_j\|_\infty &\leq w_j \forall j = 1, \dots, k \end{aligned} \right\} \Leftrightarrow \mu_\Delta(N) < 1. \quad (2)$$

Given that an error bound w_j is available a priori for each subsystem, this relation can be used to find an error bound w_c^{-1} on the interconnected system. A less conservative frequency-dependent version of (2) can be used at the cost of increased computation time. In [1], these bounds are illustrated using an example.

4 Conclusion

With (2), we can directly compute the impact of errors in subsystems to the error of the interconnected system. This result is also the first step towards determining a model accuracy specification for the individual subsystems guaranteeing a required overall system accuracy. Therefore, the method can be used as a significant means for the development of accurate modeling of interconnected systems within a completely modular setting.

References

- [1] Janssen, L.A.L. et al., "A Priori Error Bounds for Model Reduction of Interconnected Linear Systems using Robust Performance Analysis", ACC 2022 (accepted for publication).