

RECEIVED

SEP 23 1996

OSTI

LS-24 (ANL)  
G. K. Shenoy  
APRIL 18, 1985

ESTIMATION OF TOTAL RADIATIVE POWER  
FROM THE 6-GEV RING

Here we make an estimation of the total power radiated from a positron trajectory through the bending magnets, undulators and wigglers.

Bending Magnets

The power  $P_B$  per each bending magnet in the ring is given by

$$P_B \text{ (watts)} = 1.263 \times 10^3 B^2 \text{ (T}^2\text{)} E^2 \text{ (GeV}^2\text{)} I \text{ (Amp)} L \text{ (m)} \quad (1)$$

where

$$E = 6 \text{ GeV}$$

$$B = \text{field average over the magnet length} = 0.67 \text{ T}$$

$$I = \text{stored current} = 0.1 \text{ A}$$

$$L = \text{trajectory in each dipole magnet} = 2.95 \text{ m (Ref. LS-12)}$$

This gives  $P_B = 6021$  watts. Since there are 64 such dipoles in the ring, the total power radiated from dipoles is

$$P_B^T \text{ (watts)} = P_B \text{ (watts)} \times 64 = 385 \text{ kwatts}$$

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED.

Undulators

The total power radiated from a sinusoidal undulator is either given by

$$P_u \text{ (watts)} = 0.633 \times 10^3 E^2 \text{ (GeV}^2\text{)} I \text{ (Amp)} B_o^2 \text{ (T}^2\text{)} L \text{ (m)} \quad (2)$$

or by

$$P_u \text{ (watts)} = 7.25 E^2 \text{ (GeV}^2\text{)} I \text{ (Amp)} N K^2 / \lambda_o \text{ (cm)} \quad (3)$$

where  $N$  = number of undulator periods of length  $\lambda_o$  (cm),  $K$  is the deflection parameter given by  $0.934 B \text{ (T)} \lambda_o \text{ (cm)}$  and  $B_o$  is the peak magnetic field. For a conventional hybrid magnet  $B_o$  is given by

$$B_o \text{ (T)} = 3.33 \exp[-G/\lambda_o (5.47 - 1.8 G/\lambda_o)] \quad (4)$$

where  $G$  is the magnet gap in cm. In LS-22, we have discussed a spectrum of undulators suitable for the 6-GeV ring and discussed their parameters. The maximum power of 1555 watts was estimated for the undulator with  $\lambda_o = 4.8$  cm and  $G = 2.29$  cm. In this estimate, we will assume the power radiated by each of the undulators to be 2000 watts, although the actual power will be lower.

Wigglers

There will be definite need for wigglers on the 6-GeV ring, primarily to increase the critical energy of the emitted photon spectrum. The critical energy is given by

$$E_c \text{ (keV)} = 0.6651 B_o \text{ (T)} E_o^2 \text{ (GeV}^2\text{)} \quad (4)$$

**DISCLAIMER**

**Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.**

For the bending magnet it is 16.0 keV. For angiography application for example, we need to go above the iodine K-edge energy which is 33.169 keV. A wiggler with  $B_0 = 1.4$  T will have a spectrum with  $E_c = 33.5$  keV. If we design a wiggler with a wavelength of 10 cm, the value of K is 13 which gives us a smooth photon energy spectrum. If there are 20 such poles (or 10 periods), the length of the trajectory through the field will be  $L = 1.0$  m. Using Eq(2) or (3), we find the total radiated power from such a wiggler to be  $P_w = 4466$  watts. For the estimation of total power we will accept 5000 watts to be the contribution from each of the wigglers.

#### Distribution of Insertion Devices and Estimate of Total Power

The Accelerator Physicists demand symmetry in the distribution of IDs in the ring for its optimal operation. From the user point of view, there is no unique way to distribute the IDs at the present time. It is however clear that the 6-GeV ring will have more undulators than wigglers. From the point of view of power estimation, it is better to include about the same number of wigglers and undulators since the wigglers radiate more power.

Assuming that the users will have 28 of the 32 straight sections available to them, for the estimation of power, we assign 16 of them for the undulators and 12 for the wigglers. The total radiated power is the

$$P_T \text{ (watts)} = 64 \times P_B + 16 \times P_u + 12 \times P_w$$

which gives 476 kWatts.

In Table 1, power radiated from the ring for various ID configurations are given.

Table 1. Power Radiated from 6-GeV ring with 100mA current

Bending Magnet @6kW	Undulators @2kW	Wigglers @5kW	Total Power (kW)
64	28	0	440
64	0	28	524
64	16	12	476

Need for Re-estimates

The above estimates are based on design which includes conventional type of IDs in the ring and a stored current of only 100mA. It is sure that both these may change as the design progresses. Certainly, some users will think of rather unusual IDs (either of longer length or of larger magnetic fields to generate larger flux of photons of higher energy) which will radiate more power. A continuing reevaluation of this estimate is recommended.

**DISCLAIMER**

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.