



For the simple case discussed, very little additional equipment and complexity need be incorporated into current receiver configurations. In situations where several data and/or sync-modulated subcarriers are phase modulated onto a main carrier, an  $n$ -dimensional extension of this technique can be applied. The power in any of the subcarrier components can, in principle, be recovered as above. Also, cross modulation losses can be recovered and used for carrier tracking purposes. For example, several decision-directed subcarrier-data demodulators are employed in parallel. Each of these requires an input-delay element proportional to the reciprocal of the data in that channel. In order to form an estimate of the cross modulation component of interest, the outputs of the channels involved must be delayed by the complementary delay before multiplication. The delay in the carrier loop is then the sum of the delays corresponding to the reciprocals of the channel data ratio.

#### References:

1. Lindsey, W. C.: Optimal Design of One-Way and Two-Way Coherent Communication Links. IEEE Transactions on Communications Technology, Vol. COM-14, No. 4, August, 1966, p. 418.
2. Lindsey, W. C.: Determination of Modulation Indexes and Design of Two-Channel Coherent Communication Systems. IEEE Transactions on Communication Technology, Vol. COM-15, No. 2, April 1967, p. 229.
3. Lindsey, W. C.: Design of Block-Coded Communication Systems. IEEE Transactions on Communication Technology, Vol. COM-15, No. 4 August 1967, p. 524.

#### Patent status:

This invention has been patented by NASA (U.S. Patent No. 3,710,261). Inquiries concerning nonexclusive or exclusive license for its commercial development should be addressed to:

NASA Patent Counsel  
Mail Code 1  
NASA Pasadena Office  
4800 Oak Grove Drive  
Pasadena, California 91103

Source: William C. Lindsey and Marvin K. Simon of  
Caltech/JPL  
under contract to  
NASA Pasadena Office  
(NPO-11282)