

DCS-Neural-Network Program for Aircraft Control and Testing

Ames Research Center, Moffett Field, California

A computer program implements a dynamic-cell-structure (DCS) artificial neural network that can perform such tasks as learning selected aerodynamic characteristics of an airplane from wind-tunnel test data and computing real-time stability and control derivatives of the airplane for use in feedback linearized control. A DCS neural network is one of several types of neural networks that can incorporate additional nodes in order to rapidly learn increasingly complex relationships between inputs and outputs. In the DCS neural network implemented by the

present program, the insertion of nodes is based on accumulated error. A competitive Hebbian learning rule (a supervised-learning rule in which connection weights are adjusted to minimize differences between actual and desired outputs for training examples) is used. A Kohonen-style learning rule (derived from a relatively simple training algorithm, implements a Delaunay triangulation layout of neurons) is used to adjust node positions during training. Neighborhood topology determines which nodes are used to estimate new values. The network learns, start-

ing with two nodes, and adds new nodes sequentially in locations chosen to maximize reductions in global error. At any given time during learning, the error becomes homogeneously distributed over all nodes.

This program was written by Charles C. Jorgensen of Ames Research Center. Further information is contained in a TSP (see page 1).

Inquiries concerning rights for the commercial use of this invention should be addressed to the Technology Partnerships Division, Ames Research Center, (650) 604-2954. Refer to ARC-14555-1.

Dielectric Heaters for Testing Spacecraft Nuclear Reactors

Marshall Space Flight Center, Alabama

A document proposes the development of radio-frequency- (RF)-driven dielectric heaters for non-nuclear thermal testing of the cores of nuclear-fission reactors for spacecraft. Like the electrical-resistance heaters used heretofore for such testing, the dielectric heaters would be inserted in the reactors in place of nuclear fuel rods. A typical heater according to the proposal would consist of a rod of lossy dielectric material sized and shaped like a fuel rod and containing an electrically conductive rod along its center line. Exploiting the dielectric loss mechanism that is usually

considered a nuisance in other applications, an RF signal, typically at a frequency ≤ 50 MHz and an amplitude between 2 and 5 kV, would be applied to the central conductor to heat the dielectric material. The main advantage of the proposal is that the wiring needed for the RF dielectric heating would be simpler and easier to fabricate than is the wiring needed for resistance heating. In some applications, it might be possible to eliminate all heater wiring and, instead, beam the RF heating power into the dielectric rods from external antennas.

This work was done by William Herbert Sims of Marshall Space Flight Center, Leo Bitteker of the University of California, and Thomas Godfroy of the University of Michigan. Further information is contained in a TSP (see page 1).

This invention is owned by NASA, and a patent application has been filed. For further information, contact Sammy Nabors, MSFC Commercialization Assistance Lead, at sammy.a.nabors@nasa.gov. Refer to MFS-31823-1.

Using Doppler Shifts of GPS Signals To Measure Angular Speed Gyroscopes could be eliminated, reducing costs.

Goddard Space Flight Center, Greenbelt, Maryland

A method has been proposed for extracting information on the rate of rotation of an aircraft, spacecraft, or other body from differential Doppler shifts of Global Positioning System (GPS) signals received by antennas mounted on the body. In principle, the method should be capable of yielding low-noise estimates of rates of rotation. The method could eliminate the need for gyroscopes to measure rates of rotation.

The method is based on the fact that for a given signal of frequency f_i transmitted by a given GPS satellite, the dif-

ferential Doppler shift is attributable to the difference between those components of the instantaneous translational velocities of the antennas that lie along the line of sight from the antennas to the GPS satellite. On the basis of straightforward geometric considerations (see figure), it can be readily shown that the differential Doppler shift is related to the angular velocity (ω) of the rotating body by

$$f_{r1} - f_{r2} = 2f_i(\omega \times \mathbf{r}) \cdot \mathbf{a} / c,$$

where f_{r1} and f_{r2} are the instantaneous Doppler-shifted frequencies of the replicas of the f_i signal received by the two an-

tennas, \mathbf{r} is half of the baseline vector between the two antennas, \mathbf{a} is a unit vector along the line of sight from the antennas to the GPS satellite, and c is the speed of light.

It must be noted that the equation above can be solved to obtain only partial information about ω . However, if there are three or more antennas and if signals can be received from two or more GPS satellites, then one can form simultaneous independent equations for different pairs of antennas and different unit vectors that can be solved to obtain all of the components of ω .