

Title	遺伝情報学におけるセグメント法を用いたマルチプルアライメント (函数解析学の応用としての情報数理の研究)
Author(s)	村松, 重人; 大矢, 雅則
Citation	数理解析研究所講究録 (2001), 1186: 125-132
Issue Date	2001-01
URL	http://hdl.handle.net/2433/64657
Right	
Type	Departmental Bulletin Paper
Textversion	publisher

Quantum Logical Gate Based on Fock Space

Wolfgang Freudenberg*, Masanori Ohya† and Noboru Watanabe†

†Department of Information Sciences,
Science University of Tokyo

Noda City, Chiba 278-8510, Japan

Tel: 0471-24-1501 (Ext. 3319), Fax: 0471-24-1532

E-mail : watanabe@is.noda.sut.ac.jp

*Brandenburgische Technische Universität Cottbus,

Fakultät 1, Institut für Mathematik, PF 101344, D-03013 Cottbus,
Germany

Abstracts:

In usual computer, there exists a restriction of computational speed because of irreversibility of logical gate. In order to avoid this demerit, Fredkin and Toffoli [3] proposed a conservative logical gate. Based on their work, Milburn [4] introduced a physical model of reversible quantum logical gate using beam splittings and a Kerr medium. This model is called FTM (Fredkin - Toffoli - Milburn gate). FTM gate was described by the quantum channel and the efficiency of information transmission of the FTM gate was discussed in [10]. FTM gate is using a photon number state as an input state for control gate. The photon number state might be difficult to realize physically. In this paper, we introduced a new unitary operator related to the Kerr device on symmetric Fock space in order to avoid this difficulty.

Key words: quantum logical gate, channels, beam splittings, FTM gate, Fock space

1. Quantum channels

Let $(\mathbf{B}(\mathcal{H}_1), \mathfrak{S}(\mathcal{H}_1))$ and $(\mathbf{B}(\mathcal{H}_2), \mathfrak{S}(\mathcal{H}_2))$ be input and output systems, respectively, where $\mathbf{B}(\mathcal{H}_k)$ is the set of all bounded linear operators on a separable Hilbert space \mathcal{H}_k and $\mathfrak{S}(\mathcal{H}_k)$ is the set of all density operators on \mathcal{H}_k ($k = 1, 2$). Quantum channel Λ^* is a mapping from $\mathfrak{S}(\mathcal{H}_1)$ to $\mathfrak{S}(\mathcal{H}_2)$. Λ^* is linear if $\Lambda^*(\lambda\rho_1 + (1 - \lambda)\rho_2) = \lambda\Lambda^*(\rho_1) + (1 - \lambda)\Lambda^*(\rho_2)$ holds for any $\rho_1, \rho_2 \in \mathfrak{S}(\mathcal{H}_1)$

and any $\lambda \in [0, 1]$. Λ^* is completely positive (C.P.) if Λ^* is linear and its dual $\Lambda : \mathbf{B}(\mathcal{H}_2) \rightarrow \mathbf{B}(\mathcal{H}_1)$ satisfies

$$\sum_{i,j=1}^n A_i^* \Lambda(\overline{A_i^* A_j}) A_j \geq 0$$

for any $n \in \mathbf{N}$, any $\{\overline{A_i}\} \subset \mathbf{B}(\mathcal{H}_2)$ and any $\{A_i\} \subset \mathbf{B}(\mathcal{H}_1)$, where the dual map Λ of Λ^* is defined by

$$\text{tr} \Lambda^*(\rho) B = \text{tr} \rho \Lambda(B), \quad \forall \rho \in \mathfrak{S}(\mathcal{H}_1), \quad \forall B \in \mathbf{B}(\mathcal{H}_2). \quad (1.1)$$

Almost all physical transformation can be described by the CP channel [5], [7], [8]

Let \mathcal{K}_1 and \mathcal{K}_2 be two Hilbert spaces expressing noise and loss systems, respectively. Quantum communication process including the influence of noise and loss is denoted by the following scheme [6]: Let ρ be an input state in $\mathfrak{S}(\mathcal{H}_1)$, ξ be a noise state in $\mathfrak{S}(\mathcal{K}_1)$.

$$\begin{array}{ccc} \mathfrak{S}(\mathcal{H}_1) & \xrightarrow{\Lambda^*} & \mathfrak{S}(\mathcal{H}_2) \\ \gamma^* \downarrow & & \uparrow a^* \\ \mathfrak{S}(\mathcal{H}_1 \otimes \mathcal{K}_1) & \xrightarrow{\Pi^*} & \mathfrak{S}(\mathcal{H}_2 \otimes \mathcal{K}_2) \end{array}$$

The above maps γ^* , a^* are given as

$$\gamma^*(\rho) = \rho \otimes \xi, \quad \rho \in \mathfrak{S}(\mathcal{H}_1), \quad (1.2)$$

$$a^*(\sigma) = \text{tr}_{\mathcal{K}_2} \sigma, \quad \sigma \in \mathfrak{S}(\mathcal{H}_2 \otimes \mathcal{K}_2). \quad (1.3)$$

The map Π^* is a channel from $\mathfrak{S}(\mathcal{H}_1 \otimes \mathcal{K}_1)$ to $\mathfrak{S}(\mathcal{H}_2 \otimes \mathcal{K}_2)$ determined by physical properties of the device transmitting information. Hence the channel for the above process is given by

$$\Lambda^*(\rho) \equiv \text{tr}_{\mathcal{K}_2} \Pi^*(\rho \otimes \xi) = (a^* \circ \Pi^* \circ \gamma^*)(\rho) \quad (1.4)$$

for any $\rho \in \mathfrak{S}(\mathcal{H}_1)$. Based on this scheme, the noisy quantum channel [9] are constructed as follows:

Noisy quantum channel Λ^* with a noise state ξ is defined by

$$\Lambda^*(\rho) \equiv \text{tr}_{\mathcal{K}_2} \Pi^*(\rho \otimes \xi) = \text{tr}_{\mathcal{K}_2} V(\rho \otimes \xi) V^*, \quad (1.5)$$

where $\xi = |m_1\rangle\langle m_1|$ is the m_1 photon number state in $\mathfrak{S}(\mathcal{K}_1)$ and V is a mapping from $\mathcal{H}_1 \otimes \mathcal{K}_1$ to $\mathcal{H}_2 \otimes \mathcal{K}_2$ denoted by

$$V(|n_1\rangle \otimes |m_1\rangle) = \sum_j^{n_1+m_1} C_j^{n_1, m_1} |j\rangle \otimes |n_1 + m_1 - j\rangle,$$

$$C_j^{n_1, m_1} = \sum_{r=L}^K (-1)^{n_1+j-r} \frac{\sqrt{n_1! m_1! j! (n_1 + m_1 - j)!}}{r! (n_1 - j)! (j - r)! (m_1 - j + r)!} \alpha^{m_1 - j + 2r} (-\bar{\beta})^{n_1 + j - 2r} \quad (1.6)$$

K and L are constants given by $K = \min\{n_1, j\}$, $L = \max\{m_1 - j, 0\}$. In particular for the coherent input state $\rho = |\theta\rangle\langle\theta| \otimes |\kappa\rangle\langle\kappa| \in \mathfrak{S}(\mathcal{H}_1 \otimes \mathcal{K}_1)$, we obtain the output state of Π^* by

$$\Pi^*(|\theta\rangle\langle\theta| \otimes |\kappa\rangle\langle\kappa|) = |\alpha\theta + \beta\kappa\rangle\langle\alpha\theta + \beta\kappa| \otimes |-\bar{\beta}\theta + \alpha\kappa\rangle\langle-\bar{\beta}\theta + \alpha\kappa|,$$

where Π^* is called a generalized beam splitting. When the noise $\xi_0 = |0\rangle\langle 0|$ is given by the vacuum state, Λ_0^* is called an attenuation channel [5] and \mathcal{E}_0^* (or Π_0^*) is called a beam splitting. Based on liftings, the beam splitting was studied by Accardi - Ohya [1] and Fichtner - Freudenberg - Libsher [2].

2. Quantum logical gate on symmetric Fock space

Recently, we reformulate a quantum channel for the FTM gate and we rigorously study the conservation of information for FTM gate [10]. However, it might be difficult to realize the photon number state $|n\rangle\langle n|$ for the input of the Kerr medium physically.

In this section, we reformulate beam splittings on symmetric Fock space and we introduce a new operator on this space instead of the Kerr medium. We discuss the mathematical formulation of quantum logical gate by means of beam splittings and the new operator.

Let G be a complete separable metric space and \mathcal{G} be a Borel σ -algebra of G . ν is called a locally finite diffuse measure on the measurable space (G, \mathcal{G}) if ν satisfies the conditions (1) $\nu(K) < \infty$ for bounded $K \in \mathcal{G}$ and (2) $\nu(\{x\}) = 0$ for any $x \in G$. We denote the set of all finite integer - valued measures φ on (G, \mathcal{G}) by M . For a set $K \in \mathcal{G}$ and a natural number $n \in \mathbb{N}$, we put the set of φ satisfying $\varphi(K) = n$ as

$$M_{K,n} \equiv \{\varphi \in M; \varphi(K) = n\}.$$

Let \mathfrak{M} be a σ -algebra generated by $M_{K,n}$. F is the σ -finite measure on (M, \mathfrak{M}) defined by

$$F(Y) \equiv 1_Y(\varphi_0) + \sum_{n=1}^{\infty} \frac{1}{n!} \int_M 1_Y \left(\sum_{j=1}^n \delta_{x_j} \right) v^n(dx_1 \cdots dx_n),$$

where 1_Y is the characteristic function of a set Y , φ_0 is an empty configuration in M and δ_{x_j} is a Dirac measure in x_j . $\mathcal{M} \equiv L^2(M, \mathfrak{M}, F)$ is called a (symmetric) Fock space. We define an exponential vector $\exp_g : M \rightarrow \mathbb{C}$ generated by a given function $g : G \rightarrow \mathbb{C}$ such that

$$\exp_g(\varphi) \equiv \begin{cases} 1 & (\varphi = \varphi_0), \\ \prod_{x \in \varphi} g(x) & (\varphi \neq \varphi_0), \end{cases} \quad (\varphi \in M).$$

2.1. Generalized beam splittings on Fock space

Let α, β be measurable mappings from G to \mathbb{C} satisfying $\bar{\alpha}$

$$|\alpha(x)|^2 + |\beta(x)|^2 = 1, \quad x \in G.$$

We introduce an unitary operator $V_{\alpha, \beta} : \mathcal{M} \otimes \mathcal{M} \rightarrow \mathcal{M} \otimes \mathcal{M}$ defined by

$$\begin{aligned} (V_{\alpha, \beta} \Phi)(\varphi_1, \varphi_2) &\equiv \sum_{\hat{\varphi}_1 \leq \varphi_1} \sum_{\hat{\varphi}_2 \leq \varphi_2} \exp_{\alpha}(\hat{\varphi}_1) \exp_{\beta}(\varphi_1 - \hat{\varphi}_1) \exp_{-\bar{\beta}}(\hat{\varphi}_2) \exp_{\bar{\alpha}}(\varphi_2 - \hat{\varphi}_2) \\ &\quad \times \Phi(\hat{\varphi}_1 + \hat{\varphi}_2, \varphi_1 + \varphi_2 - \hat{\varphi}_1 - \hat{\varphi}_2) \end{aligned}$$

for $\Phi \in \mathcal{M} \otimes \mathcal{M}$ and $\varphi_1, \varphi_2 \in M$. Let $\mathcal{A} \equiv \mathbb{B}(\mathcal{H})$ be the set of all bounded operators on \mathcal{M} and $\mathfrak{S}(\mathcal{A})$ be the set of all normal states on \mathcal{A} . $\mathcal{E}_{\alpha, \beta} : \mathcal{A} \otimes \mathcal{A} \rightarrow \mathcal{A} \otimes \mathcal{A}$ defined by

$$\mathcal{E}_{\alpha, \beta}(C) \equiv V_{\alpha, \beta}^* C V_{\alpha, \beta}, \quad \forall C \in \mathcal{A} \otimes \mathcal{A}$$

is the lifting in the sense of Accardi and Ohya [1] and the dual map $\mathcal{E}_{\alpha, \beta}^*$ of $\mathcal{E}_{\alpha, \beta}$ given by

$$\mathcal{E}_{\alpha, \beta}^*(\omega)(\bullet) \equiv \omega(\mathcal{E}_{\alpha, \beta}(\bullet)), \quad \forall \omega \in \mathfrak{S}(\mathcal{A} \otimes \mathcal{A})$$

is the CP channel from $\mathfrak{S}(\mathcal{A} \otimes \mathcal{A})$ to $\mathfrak{S}(\mathcal{A} \otimes \mathcal{A})$. Using the exponential vectors, one can denote a coherent state θ^f by

$$\theta^f(A) \equiv \langle \exp_f, A \exp_f \rangle e^{-\|f\|^2}, \quad \forall f \in L^2(G, \nu), \quad \forall A \in \mathcal{A}.$$

In particular, for the input coherent states $\eta_0 \otimes \omega_0 = \theta^f \otimes \theta^g$, two output states $\omega_1(\bullet) \equiv \eta_0 \otimes \omega_0(\mathcal{E}_{\alpha,\beta}((\bullet) \otimes I))$ and $\eta_1(\bullet) \equiv \eta_0 \otimes \omega_0(\mathcal{E}_{\alpha,\beta}(I \otimes (\bullet)))$ are obtained by

$$\omega_1 = \theta^{\alpha f + \beta g}, \quad \eta_1 = \theta^{-\bar{\beta} f + \bar{\alpha} g}.$$

$\mathcal{E}_{\alpha,\beta}^*$ is called a generalized beam splitting on Fock space because it also hold the same properties satisfied by the generated beam splitting Π^* in Section 1.

Now we introduce a self-adjoint unitary operator \tilde{U} , which denotes a new device instead of the Kerr medium, defined by

$$\tilde{U}(\Phi)(\varphi_1, \varphi_2) \equiv (-1)^{|\varphi_1||\varphi_2|} \Phi(\varphi_1, \varphi_2)$$

for $\Phi \in \mathcal{M} \otimes \mathcal{M}$ and $\varphi_1, \varphi_2 \in G$, where $|\varphi_k| \equiv \varphi_k(G)$ ($k = 1, 2$). For the input state $\omega_1 \otimes \kappa \equiv \theta^f \otimes \frac{1}{\|\psi\|^2} \langle \psi, \bullet \psi \rangle$, the output state ω_2 of new device is

$$\omega_2(A) \equiv \omega_1 \otimes \kappa \left(\tilde{U}(A \otimes I) \tilde{U} \right) = \frac{1}{\|\psi\|^2} \int_M F(d\varphi) |\psi(\varphi)|^2 \theta^{(-1)^{|\varphi|^2} f}(A)$$

for any $A \in \mathcal{A}$, $\psi \in \mathcal{M}$ ($\psi \neq 0$) and $f \in L^2(G, \nu)$. If κ is given by the vacuum state θ^0 , then the output state ω_2 is equals to ω_1 and if κ is given by one particle state, that is, $\kappa = \frac{1}{\|\psi\|^2} \langle \psi, \bullet \psi \rangle$ with $\psi \downarrow_{M_1}$ (where M_1 is the set of one-particle states), then ω_2 is obtained by θ^{-f} . Let M_o (resp. M_e) be the set of $\varphi \in M$ which satisfies that $|\varphi|$ is odd (resp. even) and M be the union of M_o and M_e . The output states ω_2 of the new device is written by

$$\omega_2(A) = \lambda_1 \theta^{-f}(A) + \lambda_2 \theta^f(A) \quad \forall A \in \mathcal{A},$$

where λ_1 and λ_2 are given by

$$\begin{cases} \lambda_1 = \frac{1}{\|\psi\|^2} \int_{M_o} F(d\varphi) |\psi(\varphi)|^2, \\ \lambda_2 = \frac{1}{\|\psi\|^2} \int_{M_e} F(d\varphi) |\psi(\varphi)|^2. \end{cases}$$

Two output states $\omega_3(\bullet) \equiv \omega_2 \otimes \eta_2(\mathcal{E}_{\alpha_2, \beta_2}((\bullet) \otimes I))$ and $\eta_3(\bullet) \equiv \omega_2 \otimes \eta_2(\mathcal{E}_{\alpha_2, \beta_2}(I \otimes (\bullet)))$ of the total logical gate including two beam splittings $\mathcal{E}_{\alpha_k, \beta_k}^*$ with $(|\alpha_k|^2 + |\beta_k|^2 = 1)$ ($k = 1, 2$) and the new device instead of Kerr medium are obtained by

$$\begin{aligned} \omega_3 &= \lambda_1 \theta^{\alpha_2(-(\alpha_1 f + \beta_1 g)) + \beta_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)} + \lambda_2 \theta^{\alpha_2(\alpha_1 f + \beta_1 g) + \beta_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)}, \\ \eta_3 &= \lambda_1 \theta^{-\bar{\beta}_2(-(\alpha_1 f + \beta_1 g)) + \bar{\alpha}_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)} + \lambda_2 \theta^{-\bar{\beta}_2(\alpha_1 f + \beta_1 g) + \bar{\alpha}_2(-\bar{\beta}_1 f + \bar{\alpha}_1 g)}, \end{aligned}$$

where $\omega_2 = \lambda_1 \theta^{-(\alpha_1 f + \beta_1 g)} + \lambda_2 \theta^{\alpha_1 f + \beta_1 g}$ and $\eta_2 = \eta_1 = \theta^{-\beta_1 f + \alpha_1 g}$.

Based on the above settings, we could show that new logical gate performs the complete truth table. The further development of our study will be appear in [11].

References

- [1] L. Accardi and M. Ohya, Compound channels, transition expectations, and liftings, *Appl. Math. Optim.* Vol.39, 33-59, 1999.
- [2] K.H. Fichtner, W. Freudenberg and V. Liebscher, Beam splittings and time evolutions of Boson systems, *Fakultät für Mathematik und Informatik, Math/ Inf/96/ 39*, Jena, 105, 1996.
- [3] E. Fredkin and T. Toffoli, Conservative logic, *International Journal of Theoretical Physics* , **21** , pp. 219-253 1982.
- [4] G.J. Milburn, Quantum optical Fredkin gate, *Physical Review Letters* , **62**, 2124-2127, 1989.
- [5] M. Ohya, Quantum ergodic channels in operator algebras, *J. Math. Anal. Appl.* **84**, pp. 318 - 327, 1981.
- [6] M. Ohya, On compound state and mutual information in quantum information theory, *IEEE Trans. Information Theory*, **29**, pp. 770 - 777, 1983.
- [7] M. Ohya, Some aspects of quantum information theory and their applications to irreversible processes, *Rep. Math. Phys.*, **27**, pp. 19 - 47, 1989.
- [8] M. Ohya and D. Petz, *Quantum Entropy and Its Use*, Springer, 1993.
- [9] M. Ohya and N. Watanabe, Construction and analysis of a mathematical model in quantum communication processes, *Electronics and Communications in Japan, Part 1*, Vol.68, No.2, 29-34, 1985.
- [10] M. Ohya and N. Watanabe, On mathematical treatment of optical Fredkin - Toffoli - Milburn gate, *Physica D*, Vol.120, 206-213, 1998.
- [11] W. Freudenberg, M. Ohya and N. Watanabe, Generalized Fock space approach to Fredkin - Toffoli - Milburn gate, SUT preprint.