

# Operational Matrix Basic Spline Wavelets of Derivative for Linear Optimal Control Problem

Maha Delphi, Suha SHIHAB\*

Applied Sciences Department, University of Technology, Baghdad, Iraq Email: [alrawy1978@yahoo.com](mailto:alrawy1978@yahoo.com) or [100031@uotechnology.edu.iq](mailto:100031@uotechnology.edu.iq)

**Abstract:** The main importance goal in this paper is studying the interesting properties of basic spline wavelets functions (BSWFs) and derived some new basic formulations of them. The important operational matrix is devoted in two ways, the first one is the derivative of BSWFs in terms of the lower order of BSWFs while the second is the derivative of BSWFs in terms of the same order of BSWFs. The expression formula for the operational matrix is determined for different orders. In addition an useful formulas concerning the power function and BSMSFs are also presented. The polynomials and wavelets expansions together with operational matrices can be employed to solve problems in applied science and other fields of approximation theory. In this work, two optimal control problem are tested with the aid of operational matrix of derivative for BSWFs with satisfactory results.

**Keywords:** Basic spline wavelets; Operational matrix; Linear optimal control problem

## 1. Introduction

Wavelets have been successfully utilized in scientific and engineering problems. Basic spline scaling and wavelets functions play an important role in mathematics; they have been utilized in the solution of differential equations, integral equations and approximation theory. In particular basic spline wavelets have been applied in the approximation of linear and nonlinear Volterra and Fredholm integral equations<sup>[1-2]</sup>. One of the most important algorithms for treating many problems approximately is based on using operational matrix of derivatives. The advantages of operational matrices are to convert the original problem to a system of algebraic equations and then the differentiation will be eliminating with the aide of operational matrix of derivative. In a result, the complexity reduction can be obtained. About the applications of operational matrices, there are some papers for example<sup>[3-6]</sup>. In particular, some

researchers applied different basis polynomials and functions for solving optimal control problems, such as, shifted Chebyshev polynomials<sup>[7]</sup>, Chebyshev wavelets<sup>[8]</sup>, Legendre orthonormal basis<sup>[9]</sup>, Tayler wavelets<sup>[10]</sup>, interpolating scaling functions<sup>[11]</sup>, third kind Chebyshev wavelets<sup>[12]</sup>, Bernstein and orthonormal Bernstein polynomials<sup>[13-19]</sup>.

In this paper, novel approach based on BSMSFs operational matrices with their properties is applied for approximate solution of linear optimal control problem.

## 2. Basic spline Wavelets Functions

The basic spline wavelets functions  $\delta_{in}^m(t)$  can be constructed on the interval  $0 \leq t < 1$  as

$$\delta_{in}^m(t) = \begin{cases} (\sqrt{2})^k O B S_i^m(2^k t - n) & \frac{n}{2^k} \leq t < \frac{n+1}{2^k} \\ 0 & \text{otherwise} \end{cases} \quad (1)$$

where  $i = 0, 1, \dots, 2^{k-1}$  and the four arguments  $n, k, m, t$  are

- (1) The translation argument  $n = 0, 1, \dots, m$
- (2) The number of partitions on  $[0, 1]$ ,  $k$  is any positive integer
- (3) The normalized time  $t$
- (4) The order of orthonormal B-spline function on  $[0, 1]$  is  $m$ .

For  $k = 1, m = 1, n = 0, 1$  and  $i = 0, 1$

$$\delta_{00}^1 = \sqrt{6}(1 - 2t)$$

$$\delta_{01}^1 = \sqrt{2}(6t - 1), 0 \leq t \leq \frac{1}{2}$$

and

$$\delta_{10}^1 = \sqrt{6}(2 - 2t)$$

$$\delta_{11}^1 = \sqrt{2}(6t - 4), \frac{1}{2} \leq t \leq 1$$

For  $k = 1, m = 2, n = 0, 1, 2$  and  $i = 0, 1$

$$\delta_{00}^2 = \sqrt{10}(1 - 2t)^2$$

$$\delta_{01}^2 = \sqrt{6}(-20t^2 + 12t - 1), 0 \leq t \leq \frac{1}{2}$$

$$\delta_{02}^2 = \sqrt{2}(40t^2 - 16t + 1)$$

and

$$\delta_{10}^2 = \sqrt{10}(2 - 2t)^2$$

$$\delta_{11}^2 = \sqrt{6}(-20t^2 + 32t - 12), \frac{1}{2} \leq t \leq 1$$

$$\delta_{12}^2 = \sqrt{2}(40t^2 - 56t + 19)$$

For  $k = 1, m = 3, n = 0, 1, 2, 3$  and  $i = 0, 1$

$$\delta_{00}^3 = \sqrt{14}(1 - 2t)^3$$

$$\delta_{01}^3 = \sqrt{10}(1 - 2t)^2(14t - 1), 0 \leq t \leq \frac{1}{2}, t \leq \frac{1}{2}$$

$$\delta_{02}^3 = \sqrt{6}(1 - 2t)(84t^2 - 24t + 1)$$

$$\delta_{03}^3 = \sqrt{2}(280t^3 - 180t^2 + 30t - 1)$$

and

$$\delta_{10}^3 = \sqrt{14}(2 - 2t)^3$$

$$\delta_{11}^3 = \sqrt{10}(2 - 2t)^2(14t - 8), \frac{1}{2} \leq t \leq 1$$

$$\delta_{12}^3 = \sqrt{6}(2 - 2t)(84t^2 - 108t + 34)$$

$$\delta_{13}^3 = \sqrt{2}(280t^3 - 600t^2 + 420t + 96)$$

For  $k = 1, m = 2, n = 0, 1, 2$  and  $i = 0, 1$

$$\delta_{00}^4 = 3\sqrt{2}(1 - 2t)^4$$

$$\delta_{01}^4 = \sqrt{14}(1 - 2t)^3(18t - 1)$$

$$\delta_{02}^4 = \sqrt{10}(1 - 2t)^2(144t^2 - 32t + 1), 0 \leq t \leq \frac{1}{2}$$

$$\delta_{03}^4 = \sqrt{6}(1 - 2t)(672t^3 - 336t^2 + 42t - 1)$$

$$\delta_{04}^4 = \sqrt{2}(2016t^4 - 1792t^3 + 252t^2 - 48t + 1)$$

and

$$\delta_{10}^4 = 3\sqrt{2}(2 - 2t)^4$$

$$\delta_{11}^4 = \sqrt{14}(2 - 2t)^3(18t - 10)$$

$$\delta_{12}^4 = \sqrt{10}(2 - 2t)^2(144t^2 - 176t + 53), \frac{1}{2} \leq t \leq 1$$

$$\delta_{13}^4 = \sqrt{6}(1 - 2t)(672t^3 - 1344t^2 + 882t - 190)$$

$$\delta_{14}^4 = \sqrt{2}(2016t^4 - 5824t^3 + 596t^2 - 2652t +$$

### 3. Operational Matrix of Derivative for BSWFs

This section gives the constructing operational matrix of derivative for BSWFs.

For  $m = 2$

$$\delta_{00}^2 = -\frac{4\sqrt{5}}{\sqrt{3}}\delta_{00}^1$$

$$\delta_{01}^2 = 8\delta_{00}^1 - 4\sqrt{3}\delta_{01}^1, 0 \leq t \leq \frac{1}{2}$$

$$\delta_{02}^2 = -\frac{4}{\sqrt{3}}\delta_{00}^1 + 12\delta_{01}^1$$

and

$$\delta_{10}^2 = -\frac{4\sqrt{5}}{\sqrt{3}}\delta_{10}^1$$

$$\delta_{11}^2 = 8\delta_{10}^1 - 4\sqrt{3}\delta_{11}^1, \frac{1}{2} \leq t \leq 1$$

$$\delta_{12}^2 = -\frac{4}{\sqrt{3}}\delta_{10}^1 + 12\delta_{11}^1$$

One can write the above equations as

$$\delta^2(t) = D\delta^1(t)$$

where

$$\delta^2(t) = [\delta_{00}^2 \ \delta_{01}^2 \ \delta_{02}^2 \ \delta_{10}^2 \ \delta_{11}^2 \ \delta_{12}^2]^T$$

$$\delta^1(t) = [\delta_{00}^1 \ \delta_{01}^1 \ \delta_{10}^1 \ \delta_{11}^1]^T$$

and the operational matrix  $D$  is a  $6 \times 4$  matrix  $D =$

$$\begin{pmatrix} D_1 & 0 \\ 0 & D_1 \end{pmatrix}$$

$$\text{where } D_1 = \begin{pmatrix} -\frac{4\sqrt{5}}{\sqrt{3}} & 0 \\ 8 & -4\sqrt{2} \\ -\frac{4}{\sqrt{3}} & 12 \end{pmatrix}$$

For  $m = 2$

$$\delta_{00}^3 = -\frac{6\sqrt{7}}{\sqrt{5}}\delta_{00}^2$$

$$\delta_{01}^3 = 12\delta_{00}^2 - \frac{6\sqrt{5}}{\sqrt{3}}\delta_{01}^2, 0 \leq t \leq \frac{1}{2}$$

$$\delta_{02}^3 = -\frac{28\sqrt{3}}{3\sqrt{5}}\delta_{00}^2 + 10\delta_{01}^2 - \frac{20\sqrt{3}}{\sqrt{3}}\delta_{02}^2$$

$$\delta_{03}^3 = \frac{10}{\sqrt{5}}\delta_{00}^2 + 20\delta_{02}^2$$

and

$$\delta_{10}^3 = -\frac{6\sqrt{7}}{\sqrt{5}}\delta_{10}^2 \delta_{11}^3 = 12\delta_{10}^2 - \frac{6\sqrt{5}}{\sqrt{3}}\delta_{11}^2, \frac{1}{2} \leq t \leq 1$$

$$\delta_{12}^3 = -\frac{28\sqrt{3}}{3\sqrt{5}}\delta_{10}^2 + 10\delta_{11}^2 - \frac{20\sqrt{3}}{\sqrt{3}}\delta_{12}^2$$

$$\delta_{13}^3 = \frac{10}{\sqrt{5}}\delta_{10}^2 + 20\delta_{12}^2$$

One can write the above equations as

$$\delta^3(t) = D\delta^2(t)$$

where

$$\delta^3(t) = [\delta_{00}^3 \quad \delta_{01}^3 \quad \delta_{02}^3 \quad \delta_{03}^3 \quad \delta_{10}^3 \quad \delta_{11}^3 \quad \delta_{12}^3 \quad \delta_{13}^3]^T$$

$$\delta^2(t) = [\delta_{00}^2 \quad \delta_{01}^2 \quad \delta_{02}^2 \quad \delta_{10}^2 \quad \delta_{11}^2 \quad \delta_{12}^2]^T$$

In this case  $D_1 = \begin{pmatrix} -\frac{6\sqrt{7}}{\sqrt{5}} & 0 & 0 \\ 12 & -\frac{6\sqrt{5}}{\sqrt{3}} & 0 \\ -\frac{28\sqrt{3}}{3\sqrt{5}} & 10 & -\frac{20\sqrt{3}}{3} \\ \frac{10}{\sqrt{5}} & 0 & 20 \end{pmatrix}$

$m = 4$

and

$$\delta_{10}^4 = -\frac{24}{\sqrt{7}}\delta_{10}^3$$

$$\delta_{11}^4 = 16\delta_{10}^3 - \frac{8\sqrt{7}}{\sqrt{5}}\delta_{11}^3$$

$$\delta_{12}^4 = -\frac{68\sqrt{5}}{5\sqrt{7}}\delta_{10}^3 + 14\delta_{11}^3 - \frac{42\sqrt{5}}{5\sqrt{3}}\delta_{12}^3, \quad \frac{1}{2} \leq t \leq 1$$

$$\delta_{13}^4 = \frac{14\sqrt{3}}{\sqrt{7}}\delta_{10}^3 - \frac{8\sqrt{3}}{\sqrt{5}}\delta_{11}^3 + 12\delta_{12}^3 - 10\sqrt{3}\delta_{13}^3$$

$$\delta_{14}^4 = -\frac{511}{5\sqrt{7}}\delta_{10}^3 - \frac{179}{\sqrt{5}}\delta_{11}^3 - \frac{789}{5\sqrt{3}}\delta_{12}^3 - 33\delta_{13}^3$$

One can write the above equations as

$$\delta^4(t) = D\delta^3(t)$$

where

$$\delta^4(t) = [\delta_{00}^4 \quad \delta_{01}^4 \quad \delta_{02}^4 \quad \delta_{03}^4 \quad \delta_{04}^4 \quad \delta_{10}^4 \quad \delta_{11}^4 \quad \delta_{12}^4 \quad \delta_{13}^4 \quad \delta_{14}^4]^T$$

$$\delta^3(t) = [\delta_{00}^3 \quad \delta_{01}^3 \quad \delta_{02}^3 \quad \delta_{03}^3 \quad \delta_{10}^3 \quad \delta_{11}^3 \quad \delta_{12}^3 \quad \delta_{13}^3]^T$$

In this case, the matrix  $D_1$  is equal to

$$\begin{pmatrix} -\frac{24}{\sqrt{7}} & 0 & 0 & 0 \\ 16 & -\frac{8\sqrt{7}}{\sqrt{5}} & 0 & 0 \\ -\frac{68\sqrt{5}}{5\sqrt{7}} & 14 & -\frac{42\sqrt{5}}{5\sqrt{3}} & 0 \\ \frac{14\sqrt{3}}{\sqrt{7}} & -\frac{8\sqrt{3}}{\sqrt{5}} & 12 & -10\sqrt{3} \\ -\frac{511}{5\sqrt{7}} & -\frac{179}{\sqrt{5}} & -\frac{789}{5\sqrt{3}} & -33 \end{pmatrix}$$

#### 4. Operational Matrix of Derivative for BSWFs in terms of the Same Order of BSWFs

$$m = 1$$

$$\delta_{00}^1 = -3\delta_{00}^1 - \sqrt{3}\delta_{01}^1$$

$$\delta_{01}^1 = 3\sqrt{3}\delta_{00}^1 + \sqrt{3}\delta_{01}^1, \quad 0 \leq t \leq \frac{1}{2}$$

and

$$\delta_{10}^1 = -3\delta_{10}^1 - \sqrt{3}\delta_{11}^1$$

$$\delta_{11}^1 = 3\sqrt{3}\delta_{10}^1 + \sqrt{3}\delta_{11}^1, \quad \frac{1}{2} \leq t \leq 1$$

One can write the above equations as

$$\delta^1(t) = D\delta^1(t) \text{ where } D_1 = \begin{pmatrix} -3 & -\sqrt{3} \\ 3\sqrt{3} & 3 \end{pmatrix}$$

$m = 2$

$$\delta_{00}^2 = -5\delta_{00}^2 - \frac{\sqrt{5}}{\sqrt{3}}\delta_{01}^2$$

$$\delta_{01}^2 = \frac{35\sqrt{3}}{3\sqrt{5}}\delta_{00}^2 - 3\delta_{01}^2 - \frac{8\sqrt{3}}{3}\delta_{02}^2, \quad 0 \leq t \leq \frac{1}{2}$$

$$\delta_{02}^2 = -\frac{10}{\sqrt{5}}\delta_{00}^2 + \frac{14}{\sqrt{6}}\delta_{01}^2 + 8\delta_{02}^2$$

and

$$\delta_{10}^2 = -5\delta_{10}^2 - \frac{\sqrt{5}}{\sqrt{3}}\delta_{11}^2$$

$$\delta_{11}^2 = \frac{35\sqrt{3}}{3\sqrt{5}}\delta_{10}^2 - 3\delta_{11}^2 - \frac{8\sqrt{3}}{3}\delta_{12}^2, \quad \frac{1}{2} \leq t \leq 1$$

$$\delta_{12}^2 = -\frac{10}{\sqrt{5}}\delta_{10}^2 + \frac{14}{\sqrt{6}}\delta_{11}^2 + 8\delta_{12}^2$$

One can write the above equations as

$\delta^2(t) = D\delta^2(t)$ , where

$$D_1 = \begin{pmatrix} -5 & -\frac{\sqrt{5}}{\sqrt{3}} & 0 \\ \frac{35\sqrt{3}}{3\sqrt{5}} & -3 & -\frac{8\sqrt{3}}{3} \\ -\frac{10}{\sqrt{5}} & \frac{14}{\sqrt{3}} & 8 \end{pmatrix}$$

$$m = 3$$

$$\delta_{00}^3 = -7\delta_{00}^3 - \frac{\sqrt{7}}{\sqrt{5}}\delta_{01}^3$$

$$\delta_{01}^3 = \frac{77\sqrt{5}}{5\sqrt{7}}\delta_{00}^3 - 5\delta_{01}^3 - \frac{12\sqrt{5}}{5\sqrt{3}}\delta_{02}^3, \quad 0 \leq t \leq \frac{1}{2}$$

$$\delta_{02}^3 = -\frac{14\sqrt{3}}{\sqrt{7}}\delta_{00}^3 + \frac{14\sqrt{3}}{\sqrt{5}}\delta_{01}^3 - 3\delta_{02}^3 - 5\sqrt{3}\delta_{03}^3$$

$$\delta_{03}^3 = \frac{14}{\sqrt{7}}\delta_{00}^3 - \frac{10}{\sqrt{5}}\delta_{01}^3 + \frac{21}{\sqrt{3}}\delta_{02}^3 + 15\delta_{03}^3$$

and

$$\delta_{10}^3 = -7\delta_{10}^3 - \frac{\sqrt{7}}{\sqrt{5}}\delta_{11}^3$$

$$\delta_{11}^3 = \frac{77\sqrt{5}}{5\sqrt{7}}\delta_{10}^3 - 5\delta_{11}^3 - \frac{12\sqrt{5}}{5\sqrt{3}}\delta_{12}^3, \quad 0 \leq t \leq \frac{1}{2}$$

$$\delta_{12}^3 = -\frac{14\sqrt{3}}{\sqrt{7}}\delta_{10}^3 + \frac{14\sqrt{3}}{\sqrt{5}}\delta_{11}^3 - 3\delta_{12}^3 - 5\sqrt{3}\delta_{13}^3$$

$$\delta_{13}^3 = \frac{14}{\sqrt{7}}\delta_{10}^3 - \frac{10}{\sqrt{5}}\delta_{11}^3 + \frac{21}{\sqrt{3}}\delta_{12}^3 + 15\delta_{13}^3$$

One can write the above equations as

$\delta^3(t) = D\delta^3(t)$ , where

$$D_1 = \begin{pmatrix} -7 & \frac{\sqrt{7}}{\sqrt{5}} & 0 & 0 \\ \frac{77\sqrt{5}}{2\sqrt{7}} & -5 & -\frac{12\sqrt{5}}{5\sqrt{3}} & 0 \\ -\frac{14\sqrt{3}}{\sqrt{7}} & \frac{14\sqrt{3}}{\sqrt{5}} & -3 & -5\sqrt{3} \\ \frac{14}{\sqrt{7}} & -\frac{10}{\sqrt{5}} & \frac{21}{\sqrt{3}} & 15 \end{pmatrix}$$

$$m = 4$$

$$\delta_{00}^4 = -9\delta_{00}^4 - \frac{3}{\sqrt{7}}\delta_{01}^4$$

$$\delta_{01}^4 = \frac{45\sqrt{7}}{7}\delta_{00}^4 - 7\delta_{01}^4 - \frac{16\sqrt{7}}{7\sqrt{5}}\delta_{02}^4$$

$$\delta_{02}^4 = -6\sqrt{5}\delta_{00}^4 + \frac{86\sqrt{5}}{5\sqrt{7}}\delta_{01}^4 - 5\delta_{02}^4 - \frac{21\sqrt{5}}{5\sqrt{3}}\delta_{03}^4, 0 \leq t \leq \frac{1}{2}$$

$$\delta_{04}^4 = -\frac{786}{29}\delta_{00}^4 - \frac{16618}{145\sqrt{7}}\delta_{01}^4 - \frac{3494}{29\sqrt{5}}\delta_{02}^4 - \frac{5352}{145\sqrt{3}}\delta_{03}^4 + \frac{66}{29}\delta_{04}^4$$

and

$$\delta_{10}^4 = -9\delta_{10}^4 - \frac{3}{\sqrt{7}}\delta_{11}^4$$

$$\delta_{11}^4 = \frac{45\sqrt{7}}{7}\delta_{10}^4 - 7\delta_{11}^4 - \frac{16\sqrt{7}}{7\sqrt{5}}\delta_{12}^4$$

$$\delta_{12}^4 = -6\sqrt{5}\delta_{10}^4 + \frac{86\sqrt{5}}{5\sqrt{7}}\delta_{11}^4 - 5\delta_{12}^4 - \frac{21\sqrt{5}}{5\sqrt{3}}\delta_{13}^4$$

$$0 \leq t \leq \frac{1}{2}$$

$$\delta_{14}^4 = -\frac{786}{29}\delta_{10}^4 - \frac{16618}{145\sqrt{7}}\delta_{11}^4 - \frac{3494}{29\sqrt{5}}\delta_{12}^4 - \frac{5352}{145\sqrt{3}}\delta_{13}^4 + \frac{66}{29}\delta_{14}^4$$

One can write the above equations as

$$\delta^4(t) = D\delta^4(t), \text{ where}$$

$$\begin{pmatrix} -9 & -\frac{3}{\sqrt{7}} & 0 & 0 & 0 \\ \frac{45\sqrt{7}}{7} & -7 & -\frac{16\sqrt{7}}{7\sqrt{5}} & 0 & 0 \\ -6\sqrt{5} & \frac{86\sqrt{5}}{5\sqrt{7}} & -5 & -\frac{21\sqrt{5}}{5\sqrt{3}} & 0 \\ -\frac{786}{29} & -\frac{16618}{145\sqrt{7}} & -\frac{3494}{29\sqrt{5}} & -\frac{5352}{145\sqrt{3}} & \frac{66}{29} \end{pmatrix}$$

## 5. Powers in terms of (BSWFs)

The power of  $t$  can be rewritten in terms of BSWFs as follows

$$A = T \times B$$

when  $m = 1$

$$T = \begin{pmatrix} \frac{3}{2\sqrt{6}} & \frac{1}{2\sqrt{2}} & 0 & 0 \\ \frac{1}{4\sqrt{6}} & \frac{1}{4\sqrt{2}} & 0 & 0 \end{pmatrix} \text{ where } 0 \leq t \leq \frac{1}{2}$$

$$T = \begin{pmatrix} 0 & 0 & \frac{3}{2\sqrt{6}} & \frac{1}{2\sqrt{2}} \\ 0 & 0 & \frac{1}{\sqrt{6}} & \frac{1}{2\sqrt{2}} \end{pmatrix} \text{ where } \frac{1}{2} \leq t \leq 1$$

where  $A = (1 \ t)^T$  and  $B = (\delta_{00}^1 \ \delta_{01}^1 \ \delta_{10}^1 \ \delta_{11}^1)^T$

when  $m = 2$

$$\begin{pmatrix} \frac{5}{3\sqrt{10}} & \frac{1}{\sqrt{6}} & \frac{1}{3\sqrt{2}} & 0 & 0 & 0 \\ \frac{5}{24\sqrt{10}} & \frac{3}{8\sqrt{6}} & \frac{1}{6\sqrt{2}} & 0 & 0 & 0 \\ \frac{1}{24\sqrt{10}} & \frac{1}{8\sqrt{6}} & \frac{1}{12\sqrt{2}} & 0 & 0 & 0 \end{pmatrix}$$

where  $0 \leq t \leq \frac{1}{2}$

$$\begin{pmatrix} 0 & 0 & 0 & \frac{2}{3\sqrt{10}} & \frac{3}{4\sqrt{6}} & \frac{1}{3\sqrt{2}} \\ 0 & 0 & 0 & \frac{25}{24\sqrt{10}} & \frac{7}{8\sqrt{6}} & \frac{1}{3\sqrt{2}} \\ 0 & 0 & 0 & \frac{5}{3\sqrt{10}} & \frac{1}{\sqrt{6}} & \frac{1}{3\sqrt{2}} \end{pmatrix}$$

where  $\frac{1}{2} \leq t \leq 1$

where  $A = (1 \ t \ t^2)^T$  and  $B = (\delta_{00}^2 \ \delta_{01}^2 \ \delta_{02}^2 \ \delta_{10}^2 \ \delta_{11}^2 \ \delta_{12}^2)^T$

when  $m = 3$

$$\begin{pmatrix} \frac{7}{4\sqrt{14}} & \frac{5}{4\sqrt{10}} & \frac{3}{4\sqrt{6}} & \frac{1}{4\sqrt{2}} & 0 & 0 & 0 & 0 \\ \frac{7}{40\sqrt{14}} & \frac{3}{8\sqrt{10}} & \frac{13}{40\sqrt{6}} & \frac{1}{8\sqrt{2}} & 0 & 0 & 0 & 0 \\ \frac{7}{240\sqrt{14}} & \frac{5}{48\sqrt{10}} & \frac{11}{80\sqrt{6}} & \frac{1}{16\sqrt{2}} & 0 & 0 & 0 & 0 \\ \frac{1}{160\sqrt{14}} & \frac{1}{32\sqrt{10}} & \frac{9}{160\sqrt{6}} & \frac{1}{32\sqrt{2}} & 0 & 0 & 0 & 0 \end{pmatrix}$$

where  $0 \leq t \leq \frac{1}{2}$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & \frac{7}{4\sqrt{14}} & \frac{5}{4\sqrt{10}} & \frac{3}{4\sqrt{6}} & \frac{1}{4\sqrt{2}} \\ 0 & 0 & 0 & 0 & \frac{21}{20\sqrt{14}} & \frac{1}{\sqrt{10}} & \frac{7}{10\sqrt{6}} & \frac{1}{4\sqrt{2}} \\ 0 & 0 & 0 & 0 & \frac{77}{120\sqrt{14}} & \frac{19}{24\sqrt{10}} & \frac{13}{20\sqrt{6}} & \frac{1}{4\sqrt{2}} \\ 0 & 0 & 0 & 0 & \frac{2}{5\sqrt{14}} & \frac{5}{8\sqrt{10}} & \frac{3}{5\sqrt{6}} & \frac{1}{4\sqrt{2}} \end{pmatrix}$$

where  $\frac{1}{2} \leq t \leq 1$

where  $A = (1 \ t \ t^2 \ t^3)^T$

and  $B = (\delta_{00}^3 \ \delta_{01}^3 \ \delta_{02}^3 \ \delta_{03}^3 \ \delta_{10}^3 \ \delta_{11}^3 \ \delta_{12}^3 \ \delta_{13}^3)^T$

## 6. Numerical Examples

The application problems in this work are

### Example 1

This example clarifies the following concepts

Find the optimal state and optimal control based on

minimizing the performance index =  $\int_0^1 (x(t) - \frac{1}{2}u(t)^2) dt, 0 \leq t \leq 1$   
 subject to  $u(t) = \dot{x}(t) + x(t)$  with the condition  $x(0) = 0, x(1) = \frac{1}{2}(1 - \frac{1}{e})^2$

The exact solution for the state  $x(t)$  and the control  $u(t)$  is  
 $x(t) = 1 - 0.5e^{t-1} - 0.8160603e^{-t}$   
 $u(t) = 1 - e^{t-1}$   
 and  $J_{exact} = 0.08404562020$

**Example 2**

Consider the linear control system, which consists of minimizing  $J = \frac{1}{2} \int_0^1 (3x(t)^2 + u(t)^2) dt$  subject to  $u(t) = \dot{x}(t) + x(t), x(0) = 0, x(1) = 2$  and  $J_{exact} = 6.1586$ .

**Example 1** is solved using BSWFs as follows

Let the initial approximation of  $x(t)$  is  
 $X^1(t) = x^0 + (x^1 - x^0) (\frac{1}{4\sqrt{6}} \delta_{00}^1 + \frac{1}{4\sqrt{2}} \delta_{01}^1 + \frac{1}{\sqrt{6}} \delta_{10}^1 + \frac{1}{2\sqrt{6}} \delta_{11}^1)$

That is,

$$x^1(t) = \frac{0.199788}{\sqrt{6}} \delta_{10}^1 + \frac{0.099894}{\sqrt{6}} \delta_{11}^1 \text{ or } x^1(t) = d_1 \delta^1(t)$$

$$\dot{x}^1(t) = 0.049947\sqrt{6} \delta_{10}^1 + \frac{0.09989}{\sqrt{2}} \delta_{11}^1 \text{ or } \dot{x}^1(t) = r_1 \delta^1(t)$$

$$u^1(t) = 0.083245\sqrt{6} \delta_{10}^1 + \frac{0.199788}{\sqrt{2}} \delta_{11}^1 \text{ or } u^1(t) = w_1(\delta^1(t) + \dot{\delta}^1(t))$$

where  $d_1 = [0 \quad 0 \quad \frac{0.199788}{\sqrt{6}} \quad \frac{0.099894}{\sqrt{2}}]^T$ ,  
 $r_1 = [0 \quad 0 \quad 0.049947\sqrt{6} \quad \frac{0.09989}{\sqrt{2}}]^T$   
 $w_1 = [0 \quad 0 \quad 0.083245\sqrt{6} \quad \frac{0.199788}{\sqrt{2}}]^T$   
 and  $\delta^1(t) = [\delta_{00}^1 \quad \delta_{01}^1 \quad \delta_{10}^1 \quad \delta_{11}^1]$   
 $\dot{\delta}^1(t) = [\dot{\delta}_{00}^1 \quad \dot{\delta}_{01}^1 \quad \dot{\delta}_{10}^1 \quad \dot{\delta}_{11}^1]^T$

Now the second approximation of  $x$  and  $u$   
 $x^2 = d_1 \delta^1 + a_2 (\delta^2 - \dot{\delta}^1)$

where  $a_2$  is the unknown parameter, here  $a_2 = -0.409139$ , then  $x^2(t)$  and  $u^2(t)$  can be written as  
 $x^2(t) = d_1 \delta^1(t) + d_2 \delta^2(t)$  where

and  $u^2 = w_1(\delta^1 + \dot{\delta}^1) + w_2(\delta^2 + \dot{\delta}^2)$   
 where

$$d_2 = \left[ \frac{0.06818983}{\sqrt{6}} \quad \frac{0.10228475}{\sqrt{4}} \quad \frac{0.03409492}{\sqrt{2}} \quad \frac{0.15342713}{\sqrt{10}} \quad \frac{0.05114238}{2\sqrt{6}} \right]^T$$

$$w_2 = \left[ 0 \quad 0 \quad 0.083245\sqrt{6} \quad \frac{0.199788}{\sqrt{2}} \right]^T$$

$$w_2 = \left[ \frac{0.57961358}{\sqrt{10}} \quad \frac{0.2045695}{\sqrt{6}} \quad \frac{0.01704749}{\sqrt{10}} \quad \frac{0.03409492}{\sqrt{2}} \quad \frac{0.25571188}{\sqrt{6}} \quad \frac{0.13637967}{\sqrt{2}} \right]^T$$

Similarly, the third approximation for  $x(t)$  and  $u(t)$  can be found

$$x^3(t) = x^2(t) + a_3 (\delta^3(t) - \delta^2(t))$$

Here  $a_3 = 0.011654$  and  $x^3(t) = d_1 \delta^1(t) + d_2 \delta^2(t) + d_3 \delta^3(t)$

where

$$d_3 = \left[ -\frac{0.00026707}{\sqrt{6}} \quad -\frac{0.00084977}{\sqrt{10}} \quad -\frac{0.00094689}{\sqrt{6}} \quad -\frac{0.00036419}{\sqrt{2}} \quad -\frac{0.00281638}{\sqrt{14}} \quad -\frac{0.00194233}{\sqrt{10}} \quad -\frac{0.0005827}{\sqrt{6}} \right]^T$$

$$u^2 = w_1(\delta^1 + \dot{\delta}^1) + w_2(\delta^2 + \dot{\delta}^2) + w_3(\delta^3 + \dot{\delta}^3)$$

where

$$u_3 = \left[ -\frac{0.00332625}{\sqrt{6}} \quad -\frac{0.00594831}{\sqrt{10}} \quad \frac{0.02410921}{\sqrt{6}} \quad -\frac{0.00109256}{\sqrt{2}} \quad -\frac{0.00485583}{\sqrt{14}} \quad \frac{0.00242792}{\sqrt{10}} \quad -\frac{0.005827}{\sqrt{6}} \right]^T$$

The value of  $J$  are shown in **Table 1**.

Iteration	Our method	Error
1	0.08401526011	3.036×10-5
2	0.08402496173	2.065×10-5
3	0.08402530645	2.031×10-5

**Table 1.** The results of  $J$  for example 1 using BSWFs

**Example 2** is solved using BSWFs as follows

Let the initial approximation of  $x(t)$  is

$$X^1(t) = x^0 + (x^1 - x^0) (\frac{1}{4\sqrt{6}} \delta_{00}^1 + \frac{1}{4\sqrt{2}} \delta_{01}^1 + \frac{1}{\sqrt{6}} \delta_{10}^1 + \frac{1}{2\sqrt{6}} \delta_{11}^1)$$

Therefore;

$$x^1(t) = \frac{1}{\sqrt{6}} \delta_{10}^1 + \frac{1}{2\sqrt{6}} \delta_{11}^1 \text{ or } x^1 = d_1 \delta^1$$

$$\dot{x}^1 = \frac{1}{\sqrt{6}} \delta_{10}^1 + \frac{1}{2\sqrt{6}} \delta_{11}^1 \text{ or } \dot{x}^1 = r_1 \delta^1$$

$$u^1 = \frac{5\sqrt{6}}{6} \delta_{10}^1 + \frac{2}{\sqrt{2}} \delta_{11}^1 \text{ or } u^1(t) = w_1(\delta^1(t) + \dot{\delta}^1(t))$$

where  $d_1 = [0 \quad 0 \quad \frac{2}{\sqrt{6}} \quad \frac{1}{\sqrt{2}}]^T$ ,  $r_1 =$

$$[0 \quad 0 \quad \frac{\sqrt{6}}{2} \quad \frac{1}{\sqrt{2}}]^T, w_1 = [0 \quad 0 \quad \frac{5\sqrt{6}}{6} \quad \frac{2}{\sqrt{2}}]^T$$

and  $\delta^1(t) = [\delta_{00}^1 \quad \delta_{01}^1 \quad \delta_{10}^1 \quad \delta_{11}^1]$ ,  $\dot{\delta}^1(t) =$

$$[\delta_{00}^1 \quad \delta_{01}^1 \quad \delta_{10}^1 \quad \delta_{11}^1]^T$$

Now the second approximation of  $x$  and  $u$

$$x^2 = d_1\delta^1 + a_2(\delta^2 - \delta^1)$$

where  $a_2$  is the unknown parameter, here  $a_2 = 1.4286$ , then  $x^2(t)$  and  $u^2(t)$  can be written as

$$x^2(t) = d_1\delta^1(t) + d_2\delta^2(t)$$

where

$$d_2 = \left[ \begin{array}{ccc} -\frac{2381}{10000\sqrt{10}} & -\frac{7143}{20000\sqrt{6}} & -\frac{2381}{20000\sqrt{2}} \\ & -\frac{0.535725}{\sqrt{10}} & -\frac{7143}{20000\sqrt{6}} \end{array} \right]^T$$

and the control variable can be evaluated to be

$$u^2(t) = w_1(\delta^1 + \delta^1) + w_2(\delta^2 + \delta^2)$$

where

$$w_1 = \left[ \begin{array}{ccc} 0 & 0 & \frac{5\sqrt{6}}{6} \\ & & \frac{2}{\sqrt{2}} \end{array} \right]^T$$

$w_2$

$$= \left[ \begin{array}{ccc} \frac{2.02385}{\sqrt{10}} & -\frac{7143}{10000\sqrt{6}} & +\frac{2381}{40000\sqrt{2}} \\ -\frac{2381}{20000\sqrt{10}} & \frac{7143}{8000\sqrt{6}} & \frac{2381}{50000\sqrt{2}} \end{array} \right]^T$$

Similarly, the third approximation for  $x(t)$  and  $u(t)$  can be found

$$x^3(t) = x^2(t) + a_3(\delta^3(t) - \delta^2(t))$$

Here  $a_3 = 0.3888$  and  $x^3(t) = d_1\delta^1(t) + d_2\delta^2(t) + d_3\delta^3(t)$

where

$$d_3 = \left[ \begin{array}{ccc} -\frac{891}{10000\sqrt{14}} & -\frac{567}{20000\sqrt{10}} & -\frac{0.03159}{\sqrt{6}} \\ & -\frac{243}{20000\sqrt{2}} & -\frac{2349}{25000\sqrt{14}} \\ & -\frac{81}{1250\sqrt{10}} & -\frac{243}{1250\sqrt{6}} \end{array} \right]^T$$

$$u^2(t) = w_1(\delta^1 + \delta^1) + w_2(\delta^2 + \delta^2) + w_3(\delta^3 + \delta^3)$$

where

$$w_3 = \left[ \begin{array}{ccc} -\frac{0.11097}{\sqrt{14}} & -\frac{3969}{20000\sqrt{10}} & +\frac{0.80433}{\sqrt{6}} \\ & -\frac{729}{20000\sqrt{2}} & -\frac{81}{500\sqrt{14}} \\ & -\frac{81}{1000\sqrt{10}} & -\frac{243}{1250\sqrt{6}} \end{array} \right]^T$$

For optimal values of the performance index  $J$  corresponding to  $n = 1$ ,  $n = 2$ ,  $n = 3$  that is when  $x(t) = x^1$ ,  $u(t) = u^1$ ,  $x(t) = x^2$ ,  $u = u^2$ ,  $x = x^3$ ,  $u = u^3$  respectively, one refers to Table 2. Also, the value of  $J$  is shown in Table 2.

Iteration	Our method	Error
1	6.19047619	0.0319
2	6.177513228	0.0189
3	6.174827155	0.0167

**Table 2.** The results of cost functional  $J$  of example 2 using BSWFs.

Note the exact value of  $J$  is  $J = 6.1586$ .

## 7. Discussion

The solution of optimal control problems were obtained using basic spline wavelets based on operational matrix of derivative. The algorithm is comparable in terms of accuracy depending on the exact errors if the exact value of the performance index is known.

## References

1. S. A. Yousefi, B-polynomial multiwavelets approach for the solution of Abel's integral equation, *International Journal of Computer Mathematics*, 87 (2) (2013) 310-316.
2. A. K. Nasab, A. Kılıçman, E. Babolian, Wavelet analysis method for solving linear and nonlinear singular boundary value problems, *Applied Mathematical Modelling*, 37 (8) (2013) 5876-5886.
3. I. Hashim, M. Alshbool, Solving directly third-order ODEs using operational matrices of Bernstein polynomials method with applications to fluid flow equations, *Journal of King Saud University-Science*, (2018) in press.
4. K. Parand, S. A. Kaviani, Application of the exact operational matrices based on the Bernstein polynomials, *Journal of Mathematics and Computer Science*, 6 (2013) 36-59.
5. T. Ismaeelpour, A.A. Hemmat, H. Saeedi, B-spline operational matrix of fractional integration, *Optik*, 130 (2017) 291-305.
6. Shihab S., Sarhan M., New Operational Matrices of Shifted Fourth Chebyshev wavelets, *Elixir International Journal-Applied Mathematics*, 69 (1) (2014) 23239-23244.
7. H. Hassani, J.A. Tenreiro Machado, E. Narathiwat, Generalized shifted Chebyshev polynomials for fractional optimal control problems, *Commun. Nonlinear Sci. Numer. Simul.* 75 (2019) 50-61.
8. I. Malmir, Novel Chebyshev wavelets algorithms for optimal control and analysis of general linear delay models, *Appl. Math. Model.* 69 (2019) 621-647.
9. A. Lotfi, S.A. Yousefi, M. Dehghan, Numerical solution of a class of fractional optimal control problems via the Legendre orthonormal basis combined with the operational matrix and the

- Gauss quadrature rule, *J. Comput. Appl. Math.* 250 (2013) 143–160.
10. The Taylor wavelets method for solving the initial and boundary value problems of Bratu-type equations, *Appl. Numer. Math.* 128 (2) (2018) 216–205
  11. Z. Foroozandeh, M. Shamsi, Solution of nonlinear optimal control problems by the interpolating scaling functions, *Acta Astronaut.* 72 (2012) 21–26.
  12. Shihab, H. R. Al-Rubaie, an Approximate solution of some continuous time Linear-Quadratic optimal control problem via Generalized Laguerre Polynomial, *Journal of Pure and Applied Sciences*, 22 (1) (2010) 85-97.
  13. J. A. Eleiwy, S. N. Shihab, Chebyshev Polynomials and Spectral Method for Optimal Control Problem, *Engineering and Technology Journal*, 27 (14) (2009) 2642-2652.
  14. S. N. Shihab, Mohammed Abdelhadi Sarhan, Convergence analysis of shifted fourth kind Chebyshev wavelets, *IOSR Journal of Mathematics*, 10 (2), 54-58.
  15. Suha Al-Rawi, NUMERICAL SOLUTION OF INTEGRAL EQUATIONS USING TAYLOR SERIES, *Journal of the College of Education*, 5, 51-60.
  16. Suha Al-Rawi, F. A. Al-Heety, S. S. Hasan, A new Computational Method for Optimal Control Problem with B-spline Polynomials, *Engineering and Technology Journal* 28 (18), 5711-5718, 2010.
  17. S. N. Shihab, T. N. Naif, On the orthonormal Bernstein polynomial of order eight, *open Science Journal of Mathematics and Application*, 2 (2) (2014) 15-19.
  18. Maha Delphi, Suha SHIHAB, Operational Matrix Basic Spline Wavelets of Derivative for linear Optimal Control Problem, *Electronics Science Technology and Application* 6 (2), 18-24.
  19. Suha Al-Rawi, On the Solution of Certain Fractional Integral Equations, *Kirkuk University Journal for Scientific Studies* 1 (2), 125-136 (2006).