

NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Office, NASA, Code KT, Washington, D.C. 20546.





The problem:

In applications where ambient temperatures vary widely, certain precision electronic components such as crystal oscillators and zener diodes require active temperature control.

The solution:

A simple, inexpensive circuit has been developed which provides this temperature control.

How it's done:

The circuit, shown in the figure, will control the temperature of an oven within $\pm 1^{\circ}$ C when the ambient temperature ranges from -50° C up to the oven temperature. In addition, if resistor R_2 is selected to provide adequate drive to transistor Q_1 , the input voltage can vary from 10 to 37 V. Because transistor Q_1 is saturated when it conducts, no heat sink is required.

Resistor R_1 sets the trip-point hysteresis at 2° C with the circuit values shown. If the heater current is less than 150 mA, it can be supplied directly from the μ A723 integrated circuit by connecting the element between pin 6 and common.

Note:

Requests for further information may be directed to: Technology Utilization Officer Goddard Space Flight Center Code 207.1 Greenbelt, Maryland 20771 Reference: B73-10052

Patent status:

NASA has decided not to apply for a patent.

Source: S. W. Billingsley Goddard Space Flight Center (GSC-11466)

Category 02