



Progress in Applied Mathematics

Vol. 3, No. 2, 2012, pp. 35-38

DOI: 10.3968/j.pam.1925252820120302.1145

ISSN 1925-251X [Print]

ISSN 1925-2528 [Online]

[www.cscanada.net](http://www.cscanada.net)[www.cscanada.org](http://www.cscanada.org)

## The Energy of Convolution of 2-Dimension Exponential Random Variables Base on Haar Wavelet

XIA Xuewen<sup>1,\*</sup>; DAI Ting<sup>2</sup><sup>1</sup>Hunan Institute of Engineering, Xiangtan, 411104, China; Hunan Normal University, Changsha, 410082, China.<sup>2</sup>Hunan Institute of Engineering, Xiangtan, 411104, China.

\*Corresponding author.

Address: Hunan Institute of Engineering, Xiangtan, 411104, China; Hunan Normal University, Changsha, 410082, China

Received June 11, 2011; accepted March 20, 2012

### Abstract

In this paper, through wavelet methods, we obtain the energy of convolution of two-dimension exponential random variables and analyze its some properties of wavelet alternation, and we obtain some new results.

### Key words

Exponential random variables; Wavelet alternation; Convolution; Energy

XIA Xuewen, DAI Ting (2012). The Energy of Convolution of 2-Dimension Exponential Random Variables Base on Haar Wavelet. *Progress in Applied Mathematics*, 3(2), 35-38. Available from: URL: <http://www.cscanada.net/index.php/pam/article/view/j.pam.1925252820120302.1145> DOI: <http://dx.doi.org/10.3968/j.pam.1925252820120302.1145>

## 1. INTRODUCTION

The stochastic system is very important in many aspects. With the rapid development of computerized scientific instruments comes a wide variety of interesting problems for data analysis and signal processing. In fields ranging from Extragalactic Astronomy to Molecular Spectroscopy to Medical Imaging to computer vision, One must recover a signal, curve, image, spectrum, or density from incomplete, indirect, and noisy data. Wavelets have contributed to this already intensely developed and rapidly advancing field.

Recently, some persons have studied wavelet problems of stochastic processes or stochastic system (see [1]-[17]).

## 2. BASIC DEFINITION

**Definition 1** Let  $x_i, i = 1, \dots, n$ , be independent exponential random variables with respective rates  $\lambda_i, i = 1, \dots, n$ , and suppose that  $\lambda_i \neq \lambda_j, (i \neq j)$ , The random variable  $\sum_{i=1}^n x_i$  is said to be a hypoexponential random variable. To compute its probability density function, let us start with the case  $n=2$ , now,

$$\begin{aligned} x(t) = f_{x_1 + x_2}(t) &= \int_0^t f_{x_1}(s)f_{x_2}(t-s)ds = \int_0^t \lambda_1 e^{-\lambda_1 s} \lambda_2 e^{-\lambda_2(t-s)} ds \\ &= \lambda_1 \lambda_2 e^{-\lambda_2 t} \int_0^t e^{-(\lambda_1 - \lambda_2)s} ds = \frac{\lambda_1}{\lambda_1 - \lambda_2} \lambda_2 e^{-\lambda_2 t} + \frac{\lambda_1}{\lambda_2 - \lambda_1} \lambda_1 e^{-\lambda_1 t} \end{aligned} \quad (1)$$

**Definition 2** Let  $x(t)$  ( $t \in R$ ) is a function or stochastics processes, its wavelet transform is

$$w(s, x) = \frac{1}{s} \int_R x(t) \varphi\left(\frac{x-t}{s}\right) dt \quad (2)$$

Where,  $\varphi$  is continue wavelet.

**Definition 3** Let  $\varphi(x)$  is

$$\varphi(x) = \begin{cases} 1, & 0 \leq x < \frac{1}{2} \\ -1, & \frac{1}{2} \leq x < 1 \\ 0, & \text{other} \end{cases} \quad (3)$$

we call  $\varphi(x)$  is Haar wevelet.

Then, we have

$$\varphi\left(\frac{t-b}{a}\right) = \begin{cases} 1, & b \leq t \leq \frac{1}{2}a + b \\ -1, & \frac{1}{2}a + b \leq t \leq a + b \end{cases} \quad (4)$$

$$\varphi\left(\frac{t_1 - b - c}{a}\right) = \begin{cases} 1, & b + c \leq t_1 \leq \frac{a}{2} + b + c \\ -1, & \frac{a}{2} + b + c \leq t_1 \leq a + b + c \end{cases} \quad (5)$$

### 3. ENERGY

We have

$$\begin{aligned} w(s, x) &= \frac{1}{s} \int_R x(t) \varphi\left(\frac{x-t}{s}\right) dt = \frac{1}{s} \int_b^{\frac{1}{2}a+b} x(t) dt - \frac{1}{s} \int_{\frac{1}{2}a+b}^{a+b} x(t) dt \\ w(s, x+c) &= \frac{1}{s} \int_{b+c}^{\frac{a}{2}+b+c} x(t) dt - \frac{1}{s} \int_{\frac{a}{2}+b+c}^{a+b+c} x(t) dt \end{aligned} \quad (6)$$

Use (6), we have

$$\begin{aligned} w(s, x) &= \frac{1}{s} \int_b^{\frac{1}{2}a+b} \left( \frac{\lambda_1}{\lambda_1 - \lambda_2} \lambda_2 e^{-\lambda_2 t} + \frac{\lambda_2}{\lambda_2 - \lambda_1} \lambda_1 e^{-\lambda_1 t} \right) dt \\ &\quad - \frac{1}{s} \int_{\frac{1}{2}a+b}^{a+b} \left( \frac{\lambda_1}{\lambda_1 - \lambda_2} \lambda_2 e^{-\lambda_2 t} + \frac{\lambda_2}{\lambda_2 - \lambda_1} \lambda_1 e^{-\lambda_1 t} \right) dt = I_1 + I_2 \quad (7) \\ I_1 &= \frac{1}{s} \frac{\lambda_1}{\lambda_1 - \lambda_2} \lambda_1 \int_b^{\frac{1}{2}a+b} e^{-\lambda_2 t} dt + \frac{1}{s} \frac{\lambda_2}{\lambda_2 - \lambda_1} \lambda_1 \int_b^{\frac{1}{2}a+b} e^{-\lambda_1 t} dt \\ &= \frac{1}{s} \frac{\lambda_1^2}{(\lambda_2 - \lambda_1) \lambda_2} [e^{-\lambda_2(\frac{1}{2}a+b)} - e^{-\lambda_2 b}] + \frac{1}{s} \frac{\lambda_1 \lambda_2}{(\lambda_2 - \lambda_1) \lambda_1} [e^{-\lambda_1(\frac{1}{2}a+b)} - e^{-\lambda_1 b}] \\ I_2 &= -\frac{1}{s} \frac{\lambda_1}{\lambda_1 - \lambda_2} \lambda_2 \int_{\frac{1}{2}a+b}^{a+b} e^{-\lambda_2 t} dt - \frac{1}{s} \frac{\lambda_2}{\lambda_2 - \lambda_1} \lambda_1 \int_{\frac{1}{2}a+b}^{a+b} e^{-\lambda_1 t} dt \\ &= \frac{1}{s} \frac{\lambda_1}{(\lambda_1 - \lambda_2)} [e^{-\lambda_2(a+b)} - e^{-\lambda_2(\frac{1}{2}a+b)}] + \frac{1}{s} \frac{\lambda_2}{(\lambda_1 - \lambda_2)} [e^{-\lambda_1(\frac{1}{2}a+b)} - e^{-\lambda_1 b}] \end{aligned}$$

Then

$$w(s, x) = I_1 + I_2 = \frac{1}{s} \frac{\lambda_1^2}{\lambda_2(\lambda_2 - \lambda_1)} [e^{-\lambda_2(\frac{1}{2}a+b)} - e^{-\lambda_2 b}] + \frac{2}{s} \frac{\lambda_2}{(\lambda_1 - \lambda_2)} [e^{-\lambda_1(\frac{1}{2}a+b)} - e^{-\lambda_1 b}]$$

$$+ \frac{1}{s} \frac{\lambda_1}{(\lambda_1 + \lambda_2)} [e^{-\lambda_2(a+b)} - e^{-\lambda_2(\frac{a}{2}+b)}]$$

w (s,x) is the energy of probability density of random series system, use (7) we can obtain the energy of probability density of delay. The relational function is

$$R(c) = \int_R x(t)\varphi(\frac{t-b}{a})dt \int_R x(t_1)\varphi(\frac{t_1-b-c}{a})dt_1$$

Use (1)(4)(5), we can obtain its value.

We have

$$w(s, x + c) = J_1 + J_2$$

$$J_1 = \frac{1}{s} \int_{b+c}^{\frac{a}{2}+b+c} \times(t)dt = \frac{1}{s} \int_{b+c}^{\frac{1}{2b}+b+c} (\frac{\lambda_1}{\lambda_1 - \lambda_2} \lambda_2 e^{-\lambda_2 t} + \frac{\lambda_2}{\lambda_2 - \lambda_1} \lambda_1 e^{-\lambda_1 t})dt$$

$$J_2 = -\frac{1}{s} \int_{\frac{a}{2}b+c}^{a+b+c} (\frac{\lambda_1}{\lambda_1 - \lambda_2} \lambda_2 e^{-\lambda_2 t} + \frac{\lambda_2}{\lambda_2 - \lambda_1} \lambda_1 e^{-\lambda_1 t})dt$$

then

$$\begin{aligned} J_1 &= \frac{1}{s} \frac{\lambda_1 \lambda_2}{\lambda_2 - \lambda_1} - \int_{b+c}^{\frac{1}{2a}+b+c} e^{-\lambda_2 t} dt + \frac{1}{s} \frac{\lambda_1 \lambda_2}{\lambda_2 - \lambda_1} \int_{b+c}^{\frac{2}{2a}b+c} e^{-\lambda_1 t} dt \\ &= \frac{1}{s} \frac{\lambda_1}{(\lambda_2 - \lambda_1)} [e^{-\lambda_2(\frac{1}{2a}+b+c)} - e^{-\lambda_2(b+c)}] + \frac{1}{s} \frac{\lambda_2}{(\lambda_1 - \lambda_2)} [e^{-\lambda_1(\frac{1}{2a}+b+c)} - e^{-\lambda_1(b+c)}] \end{aligned}$$

$$\begin{aligned} J_2 &= -\frac{1}{s} \frac{\lambda_1 \lambda_2}{\lambda_1 - \lambda_2} \int_{\frac{a}{2}b+c}^{a+b+c} e^{-\lambda_2 t} dt - \frac{\lambda_1 \lambda_2}{s(\lambda_2 - \lambda_1)} \int_{\frac{a}{2}b+c}^{a+b+c} e^{-\lambda_1 t} dt \\ &= \frac{1}{s} \frac{\lambda_1}{(\lambda_1 - \lambda_2)} [e^{-\lambda_2(a+b+c)} - e^{-\lambda_2(\frac{a}{2}+b+c)}] + \frac{1}{s} \frac{\lambda_2}{(\lambda_2 - \lambda_1)} [e^{-\lambda_1(a+b+c)} - e^{-\lambda_1(\frac{a}{2}+b+c)}] \end{aligned}$$

Where,w (s ,x +c) is the energy of probability density of delay.

## REFERENCES

- [1] Cambancs (1994). Wavelet Approximation of Deterministic and Random Signals. *IEEE Tran. on Information Theory*, 40(4), 1013-1029.
- [2] Flandrin (1992). Wavelet Analysis and Synthesis of Fractional Brownian Motion. *IEEE Tran. on Information Theory*, 38(2), 910-916.
- [3] Krim (1995). Multire Solution Analysis of a Class of Nonstationary Processes. *IEEE Tran. on Information Theory*, 41(4), 1010-1019
- [4] Haobo Ren (2002). Wavelet Estimation for Jumps on a Heterosedastic Regression Model. *Acta Mathematica Scientia*, 22(2), 269-277.
- [5] Xuewen Xia (2005). Wavelet Analysis of the Stochastic System with Coular Stationary Noise. *Engineering Science*, (3), 43-46.
- [6] Xuewen Xia (2008). Wavelet Density Degree of Continuous Parameter AR Model. *International Journal Nonlinear Science*, 7(4).
- [7] Xuewen Xia & Kai Liu (2007). Wavelet Analysis of Browain Motion. *World Journal of Modelling and Simulation*, (3).

- [8] I. Daubechies (1993). Different Perspective on Wavelets. In *Proceedings of Symposia in Applied Mathematics, Vol. 46, 1993*.
- [9] M. Rosenblatt (1974). *Random Processes*. New York: Springer.
- [10] S. Mallat & W. Hwang (1992). Singularity Dectection and Processing with Wavelets. *IEEE Trans. on Information Theory*, 38, 617-643.
- [11] J. Zhang & G. Walter (1994). A Wavelet Based K-L-like Expansion for Wide-Sense Stationary Process. *IEEE Trans. Sig. Proc.*.
- [12] Xuewen Xia & Ting Dai (2009). Wavelet Density Degree of a Class of Wiener Processes. *International Journal Nonlinear Science*, 8(3).
- [13] Y. Meyer (1990). *Ondelettes et Operatears*. Hermann.
- [14] Xuewen Xia (2010). Haar Wavelet Density of the Linear Regress Processes with Rondon Coefficient. *In Proceedings of the Third International Conference on Modeling and Simulation, 2010(5)*.
- [15] Xuewen Xia (2010). The Haar Wavelet Density of the Two Order Polynomial Stochastic Processes. *In Proceedings of the Third International Conference on Modeling and Simulation, 2010(3)*.
- [16] Xuewen Xia (2011). The Study of Wiener Processes with  $N(0,1)$ -Random Trend Peocesses Based on Wavelet. *Journal Information and Computing Science*, (2).
- [17] Xuewen Xia (2011). The Study of a Class of the Fractional Brownian Motion Based on Wavelet. *Inter. J. of Nonlinear Science*, (3).