# Dartmouth College Dartmouth Digital Commons

**Computer Science Technical Reports** 

**Computer Science** 

9-1-2006

# **Digital Image Ballistics from JPEG Quantization**

Hany Farid Dartmouth College

Follow this and additional works at: https://digitalcommons.dartmouth.edu/cs\_tr

Part of the Computer Sciences Commons

#### **Dartmouth Digital Commons Citation**

Farid, Hany, "Digital Image Ballistics from JPEG Quantization" (2006). Computer Science Technical Report TR2006-583. https://digitalcommons.dartmouth.edu/cs\_tr/291

This Technical Report is brought to you for free and open access by the Computer Science at Dartmouth Digital Commons. It has been accepted for inclusion in Computer Science Technical Reports by an authorized administrator of Dartmouth Digital Commons. For more information, please contact dartmouthdigitalcommons@groups.dartmouth.edu.

# **Digital Image Ballistics from JPEG Quantization**

Hany Farid Department of Computer Science Dartmouth College Hanover NH 03755

# Abstract

Most digital cameras export images in the JPEG file format. This lossy compression scheme employs a quantization table that controls the amount of compression achieved. Different cameras typically employ different tables. A comparison of an image's quantization scheme to a database of known cameras affords a simple technique for confirming or denying an image's source. Similarly, comparison to a database of photo-editing software can be used in a forensic setting to determine if an image was edited after its original recording.

### 1 Introduction

When performing a forensic analysis on a digital image, it is often useful to be able to determine its source (e.g., a digital camera, a digital video camera, or a photo-editing software). Since the JPEG image format has emerged as a virtual standard, most devices and software encode images in this format. This lossy compression scheme allows for some flexibility in how much compression is achieved. Manufacturers typically configure their devices differently to balance compression and quality to their own needs and tastes. This difference, embodied in the JPEG quantization table, can be used to identify the source of an image.

In related work [3], the authors describe a technique to identify a specific camera based on sensor noise. Here, a much cruder identification will be made – at best, that of identifying the camera make and model. One benefit of this approach is that it can be applied to any device or software that employs JPEG compression.

# 2 JPEG Compression

JPEG <sup>1</sup> is a standard lossy compression scheme [1, 6]. Given a three channel color image (RGB), compression proceeds as follows. The RGB image is first converted into luminance/chrominance space (YCbCr). The two chrominance channels (CbCr) are typically subsampled by a factor of two relative to the luminance channel (Y). Each channel is then partitioned into  $8 \times 8$  pixel blocks. These values are converted from unsigned to signed integers (e.g., from [0, 255] to [-128, 127]). Each block is converted to frequency space using a 2-D discrete cosine transform (DCT). Depending on the specific frequency and channel, each DCT coefficient, *c*, is then quantized by an amount *q*:

$$\hat{c} = \operatorname{round}(c/q).$$
 (1)

This stage is the primary source of information loss. A final entropy encoding is then employed.

With some variations, the above sequence of steps are employed by JPEG encoders in digital cameras and photo-editing software. The primary source of variation in these encoders is the choice of quantization that subsequently controls the compression rates and artifacts. The quantization is specified as a table of 192 values – a set of  $8 \times 8$  values associated with each frequency, for each of three channels (YCbCr). For low compression rates, these values tend towards a value of 1, and increase for higher compression rates. Shown in Figure 1, for example, is the quantization table employed by a Nikon Coolpix 2500 digital camera. Shown,

|   | 2  | 1  | 1  | 1  | 1  | 1  | 2  | 1  |
|---|----|----|----|----|----|----|----|----|
|   | 1  | 1  | 2  | 2  | 2  | 2  | 2  | 4  |
|   | 3  | 2  | 2  | 2  | 2  | 5  | 4  | 4  |
|   | 3  | 4  | 6  | 5  | 6  | 6  | 6  | 5  |
|   | 6  | 6  | 6  | 7  | 9  | 8  | 6  | 7  |
| 1 | 9  | 7  | 6  | 6  | 8  | 11 | 8  | 9  |
|   | 10 | 10 | 10 | 10 | 10 | 6  | 8  | 11 |
|   | 12 | 11 | 10 | 12 | 9  | 10 | 10 | 10 |
|   |    |    |    |    |    |    |    |    |
| 1 | 2  | 2  | 2  | 2  | 2  | 2  | 5  | 3  |
|   | 3  | 5  | 10 | 7  | 6  | 7  | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   |    |    |    |    |    |    |    |    |
|   | 2  | 2  | 2  | 2  | 2  | 2  | 5  | 3  |
|   | 3  | 5  | 10 | 7  | 6  | 7  | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |
|   | 10 | 10 | 10 | 10 | 10 | 10 | 10 | 10 |

**Figure 1:** A sample JPEG quantization table employed by a Nikon Coolpix 2500 digital camera.

from top to bottom, are the luminance and chrominance channel tables. As is typical, the quantization for the luminance channel is less than for the two chrominance channels, and the quantization level is less for the lower frequency components.

With 192 entries, and values ranging typically from 1 to 25 there are  $10^{268}$  possible quantization tables – in practice, this number is much smaller because the entries are not chosen independent of one another.

#### 3 Ballistics

A single image from each of 204 digital cameras was collected, Table 5<sup>2</sup>. While some cameras have only a single JPEG quality setting, many others have multiple quality settings. In this current analysis, only a single image at the highest quality was examined.

The JPEG quantization table was extracted from each image and compared for uniqueness. On average, each camera matched 1.43 other cameras. 62 of the 204 cameras had a unique table. The remaining cameras fall into equivalence classes of sizes between 2 and 28, Table 5. In the majority of cases, it is cameras from the same manufacturer that share the same quantization tables. In many cases, only two or three cameras are indistinguishable – the Canon PowerShot family is the

<sup>&</sup>lt;sup>1</sup>The Joint Photographic Experts Group (JPEG) developed an image file format known as the JPEG File Interchange Format (JFIF), which is most commonly abbreviated as JPEG.

<sup>&</sup>lt;sup>2</sup>Most of the images were downloaded from the digital photography review site http://www.dpreview.com. The metadata of each downloaded image was checked to make sure that the image was not subsequently edited in a photo-editing software, which would have compromised the original JPEG quantization table.

exception, where 28 cameras have identical quantization tables. And in several cases, different makes and models share the same quantization table, with the largest diversity finding Kodak, Nikon, Olympus, Pentax, and Sony cameras in the same equivalence class.

While the JPEG quantization is clearly not perfectly unique, it is reasonably effective at narrowing the source of an image to a single camera make and model or to a small set of possible cameras (on average, this set size is 1.43).

#### 3.1 Software Ballistics

Photo-editing software packages (e.g., Adobe Photoshop, Corel Paint Shop, Microsoft Digital Image Suite, etc.) employ different JPEG quantization tables. Photoshop, unarguably the most popular such package, provides 13 levels of compression (12: lowest compression & highest quality - 0: highest compression & lowest quality). An image was saved at each of these levels for Photoshop CS2 (the most recent version), Photoshop CS, Photoshop 7, Photoshop 4 and Photoshop 3. The quantization tables at each compression level were different from one another. Moreover, at each compression level the tables were the same for all five versions of Photoshop<sup>3</sup>. More importantly, the tables differed from each the 204 digital cameras listed in Table 5. An image can therefore be linked to a specific software (or possibly a set of software packages).

Similar in spirit to forensic techniques for detecting double JPEG compression [2, 4], the presence of quantization tables unique to a photo-editing software can be used to determine that an image was previously viewed and saved from within a photo-editing software. The reliability of such a claim will, of course, require the uniqueness of the software tables to hold over a larger set of cameras.

#### 3.2 Video Ballistics

The MPEG video standard (MPEG-1 and MPEG-2) employs two basic schemes for compression to reduce both spatial redundancy within individual video frames and temporal redundancy across video frames [5]. In a MPEG encoded video sequence, there are three types of frames: intra (I), predictive (P) and bi-directionally predictive (B), each offering varying degrees of compression. These frames typically occur in a periodic sequence. A common sequence, for example, is:

 $I_1 B_2 B_3 P_4 B_5 B_6 P_7 B_8 B_9 P_{10} B_{11} B_{12} I_{13} B_{14} \cdots,$ 

where the subscripts are used to denote time.

*I*-frames are encoded using the JPEG compression scheme described in Section 2. *P*-frames are encoded

using motion estimation. The motion between a *P*-frame and its preceding *I*- or *P*-frame is estimated. A motion estimated version of the next frame is generated by warping the *P*-frame according to the estimated motion. The error between this predicted frame, and the actual frame is then computed. Both the motion vectors and the motion errors are encoded and transmitted – the motion errors are encoded using JPEG compression. The encoding of a *B*-frame is similar to that of a *P*-frame except that motion estimation for these frames employ past, future, or both of its neighboring *I*- or *P*-frames.

In an MPEG video sequence, the *I*-frames and the motion errors for the *P*- and *B*-frames are each JPEG encoded. As such, the quantization tables for these frames may be used to identify the source of a video recording.

# 4 Discussion

By choosing a JPEG quantization table camera manufacturers and software developers are able to balance the amount of compression and the quality of their images. In so doing, a signature of sorts is embedded within each JPEG image. This simple observation allows for a rather crude form of digital image ballistics, whereby the source of an image can be confirmed or denied.

In order for this ballistic technique to be more effective and reliable, it is important to collect data from an ever-increasing number of cameras and software. In addition, it is important to consider the quantization tables for each JPEG quality setting afforded by a specific device or software.

In collaboration with other ballistic and forensic tools, this technique should prove useful for the forensic examination of digital images and video.

# 5 Acknowledgments

Thanks to Paul McJones and Sean Parent of Adobe Systems for their assistance extracting the JPEG quantization tables from older versions of Adobe Photoshop. Thanks to Jeff Woodward for writing the batch processing scripts for extracting JPEG quantization tables.

This work was supported by a Guggenheim Fellowship, a gift from Adobe Systems, Inc., a gift from Microsoft, Inc., a grant (FA8750-06-C-0011) from the United States Air Force, and under a grant (2000-DT-CX-K001) from the U.S. Department of Homeland Security, Science and Technology Directorate (points of view in this document are those of the authors and do not necessarily represent the official position of the U.S. Department of Homeland Security or the Science and Technology Directorate).

<sup>&</sup>lt;sup>3</sup>More recent versions of Photoshop afford more JPEG compression levels. The quantization tables found in older versions, however, are the same as in the most recent versions of Photoshop.

# References

- Digital compression and coding of continuoustone still images, Part 1: Requirements and guidelines. ISO/IEC JTC1 Draft International Standard 10918-1, 1991.
- [2] J. Lukas and J. Fridrich. Estimation of primary quantization matrix in double compressed JPEG images. In *Digital Forensic Research Workshop*, Cleveland, Ohio, August 2003.
- [3] J. Lukas, J. Fridrich, and M. Goljan. Digital camera identification from sensor noise. *IEEE Transactions on Information Security and Forensics*, 1(2):205–214, 2006.
- [4] A.C. Popescu and H. Farid. Statistical tools for digital forensics. In 6th International Workshop on Information Hiding, Toronto, Cananda, 2004.
- [5] T. Sikora. Digital Consumer Electronics Handbook, chapter MPEG-1 and MPEG-2 Digital Video Coding Standards. McGraw-Hill, 1997.
- [6] G.K. Wallace. The JPEG still picture compression standard. *IEEE Transactions on Consumer Electronics*, 34(4):30–44, 1991.

| Canon           | PowerShot A510  | Canon           | PowerShot A520  | Canon           | PowerShot A620     |
|-----------------|-----------------|-----------------|-----------------|-----------------|--------------------|
| Canon           | IXUS 50         | Canon           | PowerShot S2 IS | Canon           | PowerShot S70      |
| Canon           | IXUS 55         | Canon           | IXUS 700        | Canon           | IXUS 750           |
| Canon           | IXUS 800 IS     | Canon           | PowerShot A20   | Canon           | PowerShot A70      |
| Canon           | PowerShot A700  | Canon           | PowerShot A95   | Canon           | EOS 10D            |
| Canon           | EOS-1D          | Canon           | EOS-1D Mark II  | Canon           | EOS-1DS            |
| Canon           | Canon           | Canon           | EOS 20D         | Canon           | EOS 300D           |
| Canon           | EOS 30D         | Canon           | EOS 350D        | Canon           | EOS 5D             |
| Canon           | EOS D30         | Canon           | EOS D60         | Canon           | PowerShot G1       |
| Canon           | PowerShot G2    | Canon           | PowerShot G3    | Canon           | PowerShot G5       |
| Canon           | PowerShot G6    | Canon           | PowerShot Pro1  | Canon           | PowerShot Pro90 IS |
| Canon           | PowerShot S10   | Canon           | IXUS            | Canon           | IXUS v             |
| Canon           | PowerShot S1 IS | Canon           | PowerShot S20   | Canon           | PowerShot S30      |
| Canon           | IXUS 300        | Canon           | IXUS 330        | Canon           | PowerShot S40      |
| Canon           | IXUS 400        | Canon           | PowerShot S45   | Canon           | PowerShot S50      |
| Canon           | PowerShot S60   | Canon           | IXUS II         | Canon           | IXUS 40            |
| Casio           | EX-P700         | Casio           | EX-Z3           | Casio           | EX-Z750            |
| Casio           | OV-3000EX       | Casio           | OV-4000         | Epson           | PhotoPC 3000Z      |
| Fuji            | FinePix40i      | Fuji            | FinePix4700     | Fuji            | FinePix4900        |
| Fuji            | FinePix6800     | Fuji            | FinePix6900     | Fuji            | FinePix F810       |
| Fuji            | FinePix E550    | Fuji            | FinePix F10     | Fuji            | FinePix F30        |
| Fuji            | FinePix F601    | Fuji            | FinePix F700    | Fuji            | FinePix S1Pro      |
| Fuii            | FinePix S2Pro   | Fuji            | FinePix S3Pro   | Fuii            | FinePix S500       |
| Fuii            | FinePix S5500   | Fuii            | FinePix S602    | Fuii            | FinePix S7000      |
| Fuii            | FinePix S9500   | Fuii            | FinePix2700     | Fuii            | MX-2900ZOOM        |
| Hewlett-Packard | PhotoSmart C812 | Hewlett-Packard | PhotoSmart C850 | Hewlett-Packard | PhotoSmart C935    |
| Hewlett-Packard | PhotoSmart R707 | Kodak           | DC290           | Kodak           | DC3200             |
| Kodak           | DC4800          | Kodak           | DCS Pro 14N     | Kodak           | DX4900             |
| Kodak           | DX7590          | Kodak           | P850            | Kodak           | P880               |
| Kodak           | V610            | Kodak           | Z650            | Kodak           | Z740               |
| Konica Minolta  | MAXXIIM 7D      | Konica Minolta  | DiMAGE A200     | Konica Minolta  | DiMAGE A2          |
| Konica Minolta  | DiMAGE 72       | Konica Minolta  | DiMAGE 75       | Kvocera         | FC-S3              |
| Lieca           | DICILUX 2       | Minolta         | DiMACE 5        | Minolta         | DiMACE 7           |
| Minolta         | DiMAGE 7Hi      | Minolta         | DiMAGE 7i       | Minolta         | DIMAGE A1          |
| Minolta         | DiMAGE F100     | Minolta         | DiMAGE S304     | Minolta         | DiMAGE S404        |
| Minolta         | DIMAGE X        | Nikon           | F2500           | Nikon           | F3100              |
| Nikon           | E4500           | Nikon           | E2300           | Nikon           | E5000              |
| Nikon           | E5200           | Nikon           | E4000           | Nikon           | E5700              |
| Nikon           | E3200           | Nikon           | E775            | Nikon           | E3700              |
| Nikon           | E700            | Nikon           | E8400           | Nikon           | E7700              |
| Nikon           | E000<br>E880    | Nikon           | E8800           | Nikon           | E885               |
| Nikon           | E000<br>F950    | Nikon           | E0000<br>F990   | Nikon           | E005               |
| Nikon           | COOL PIX P3     | Nikon           | D1              | Nikon           | D100               |
| Nikon           | D1H             | Nikon           | D200            | Nikon           | D2H                |
| Nikon           | D111<br>D2X     | Nikon           | D50             | Nikon           | D70                |
| Olympus         | C20207          | Olympus         | C2100UZ         | Olympus         | C3030Z             |
| Olympus         | C3040Z          | Olympus         | C407 D407       | Olympus         | C5050Z             |
| Olympus         | X-2 C-507       | Olympus         | C70Z C7000Z     | OlympusD        | C70011Z            |
| Olympus         | C8080WZ         | Olympus         | F-1             | Olympus         | E-10               |
| Olympus         | E-20            | Olympus         | E-300           | Olympus         | E-330              |
| Olympus         | E-500           | Olympus         | SP310           | Olympus         | SP500UZ            |
| Olympus         | 11D800 S800     | Olympus         | u-miniD         | Panasonic       | DMC-FX01           |
| Panasonic       | DMC-FZ30        | Panasonic       | DMC-FX7         | Panasonic       | DMC-FX9            |
| Panasonic       | DMC-FZ20        | Panasonic       | DMC-F73         | Panasonic       | DMC-F75            |
| Panasonic       | DMC-LX1         | Panasonic       | DMC-L72         | Panasonic       | DMC-T71            |
| Pentax          | Ontio A10       | Pentay          | ist D           | Pentay          | ist DS             |
| Pentax          | Optio 330       | Pentax          | Optio 430       | Pentax          | Optio 550          |
| Pontav          | Optio 3507      | Pontax          | Optio S         | Pontax          | Optio 550          |
| Ricoh           | CR              | Sameung         | Digimax V700    | Sigma           | SD10               |
| Sony            | MVC-CD200       | Sonv            | MVC-CD300       | Sonv            | DSC-D700           |
| Sony            | DSC-F505V       | Sony            | DSC-F707        | Sony            | DSC-F717           |
| Sony            | DSC-F828        | Sony            | DSC-F88         | Sony            | DSC-H1             |
| Sony            | DSC-H2          | Sony            | DSC-H5          | Sony            | DSC-L1             |
| Sony            | DSC-P1          | Sony            | DSC-P150        | Sony            | DSC-P200           |
| Sony            | DSC-P5          | Sony            | DSC-P71         | Sony            | DSC-P9             |
| Sony            | DSC-R1          | Sony            | DSC-S70         | Sony            | DSC-S75            |
| Sony            | DSC-585         | Sony            | DSC-S90         | Sony            | DSC-V1             |
| Sony            | DSC-V3          | Sony            | DSC-W7          | Sony            | DSLR-A100          |
| <i>j</i>        | 200.0           | , <i>2011</i> , | 200.17          | 2011            |                    |

Table 1: Make and model of 204 cameras.

| 28            | Canon PowerShot A510 - Canon PowerShot A520 - Canon PowerShot A620 - Canon IXUS 50 - Canon PowerShot S2 IS -    |  |  |  |  |  |
|---------------|---|--|--|--|--|--|
|               | Canon PowerShot S70 - Canon IXUS 55 - Canon IXUS 700 - Canon IXUS 750 - Canon IXUS 800 IS - Canon PowerShot A20 |  |  |  |  |  |
|               | - Canon PowerShot A70 - Canon PowerShot A700 - Canon PowerShot G2 - Canon PowerShot G3 - Canon PowerShot G5     |  |  |  |  |  |
|               | - Canon PowerShot G6 - Canon PowerShot Pro1 - Canon IXUS v - Canon IXUS 300 - Canon IXUS 330 - Canon PowerShot  |  |  |  |  |  |
|               | S40 - Canon IXUS 400 - Canon PowerShot S45 - Canon PowerShot S50 - Canon PowerShot S60 - Canon IXUS II - Canon  |  |  |  |  |  |
|               | IXUS 40   |  |  |  |  |  |
| 23            | Kodak P850 - Nikon E5400 - Olympus C2100UZ - Olympus C3030Z - Olympus C40Z,D40Z - Olympus C5050Z - Olym-        |  |  |  |  |  |
|               | pusD C700UZ - Olympus C8080WZ - Pentax Optio 550 - Pentax Optio 750Z - Sony DSC-F505V - Sony DSC-F707 - Sony    |  |  |  |  |  |
|               | DSC-F717 - Sony DSC-H1 - Sony DSC-H2 - Sony DSC-H5 - Sony DSC-P150 - Sony DSC-P200 - Sony DSC-R1 - Sony         |  |  |  |  |  |
|               | DSC-S90 – Sony DSC-V1 – Sony DSC-V3 – Sony DSC-W7   |  |  |  |  |  |
| 16            | Canon EOS 10D – Canon EOS 20D – Canon EOS 300D – Canon EOS 30D – Canon EOS 350D – Canon EOS D30 – Canon         |  |  |  |  |  |
|               | EOS D60 – Sony MVC-CD200 – Sony MVC-CD300 – Sony DSC-P1 – Sony DSC-P5 – Sony DSC-P71 – Sony DSC-P9 – Sony       |  |  |  |  |  |
|               | DSC-S70 – Sony DSC-S75 – Sony DSC-S85   |  |  |  |  |  |
| 8             | Konica Minolta DiMAGE Z2 – Minolta DiMAGE F100 – Nikon E2500 – Nikon E4500 – Nikon E5000 – Nikon E5700 – Nikon  |  |  |  |  |  |
|               | E8800 – Nikon E990  |  |  |  |  |  |
| 7             | Nikon D100 – Nikon D1H – Nikon D200 – Nikon D2H – Nikon D50 – Nikon D70 – Panasonic DMC-FX01                    |  |  |  |  |  |
| 6             | Kodak P880 – Nikon D2X – Olympus C3040Z – Olympus C70Z,C7000Z – Olympus SP310 – Olympus SP500UZ                 |  |  |  |  |  |
| 6             | Konica Minolta DiMAGE A2 – Minolta DiMAGE 5 – Minolta DiMAGE 7 – Minolta DiMAGE 7i – Minolta DiMAGE S304 –      |  |  |  |  |  |
|               | Minolta DiMAGE S404   |  |  |  |  |  |
| 5             | Kodak DC4800 – Kodak DX4900 – Kodak V610 – Kodak Z650 – Kodak Z740  |  |  |  |  |  |
| 5             | Nikon E4800 – Nikon E775 – Nikon E8400 – Nikon E8700 – Sigma SD10   |  |  |  |  |  |
| 4             | Canon IXUS – Casio EX-P700 – Casio EX-Z750 – Pentax Optio S   |  |  |  |  |  |
| 3             | Minolta DiMAGE X – Nikon E7900 – Nikon E950   |  |  |  |  |  |
| 3             | Nikon E3100 – Nikon E880 – Nikon E995   |  |  |  |  |  |
| 3             | Olympus E-300 – Olympus E-330 – Olympus E-500   |  |  |  |  |  |
| 3             | Panasonic DMC-FX7 – Panasonic DMC-FZ20 – Panasonic DMC-FZ5  |  |  |  |  |  |
| 2             | Canon EOS-ID – Canon EOS-IDS  |  |  |  |  |  |
| 2             | Canon EOS-IDS Mark II – Canon EOS 5D  |  |  |  |  |  |
| 2             | Canon Powershot G2 – Canon Powershot Pro90 IS   |  |  |  |  |  |
| 2             | Epson PhotoPC 3000Z – Konica Minoita DIMAGE A200  |  |  |  |  |  |
| 2             | Fuji FinePiX S7000 – Fuji FinePiX2700   |  |  |  |  |  |
| 2             | Hewlett-Packard PhotoSmart C650 – Hewlett-Packard PhotoSmart C955   |  |  |  |  |  |
| 2             | Minota DIMAGE / H1 – MINOTA DIMAGE AT   |  |  |  |  |  |
| 2             | Nikoli ESZUD – Nikoli COOLITA FS<br>Panaconia DMC EZ20 – Panaconia DMC LV1                                      |  |  |  |  |  |
| $\frac{2}{2}$ | Pantay ist D_Pantay ist D_S   |  |  |  |  |  |
| 2             | Sony DSC-F828 – Sony DSC-F88  |  |  |  |  |  |
| 4             | 5011y 25C-1 020 - 5011y 25C-1'00  |  |  |  |  |  |

**Table 2:** Each entry corresponds to cameras with identical JPEG quantization tables.