



# **University of Groningen**

Analytical calculation of Sobol s	sensitivity indices	for Gaussian P	rocesses with	a squared
exponential covariance function				•

Milias Argeitis, Andreas; Kurdyaeva, Tamara

IMPORTANT NOTE: You are advised to consult the publisher's version (publisher's PDF) if you wish to cite from it. Please check the document version below.

Publication date: 2018

Link to publication in University of Groningen/UMCG research database

Citation for published version (APA):

Milias Argeitis, A., & Kurdyaeva, T. (2018). Analytical calculation of Sobol sensitivity indices for Gaussian Processes with a squared exponential covariance function.

Other than for strictly personal use, it is not permitted to download or to forward/distribute the text or part of it without the consent of the author(s) and/or copyright holder(s), unless the work is under an open content license (like Creative Commons).

The publication may also be distributed here under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license. More information can be found on the University of Groningen website: https://www.rug.nl/library/open-access/self-archiving-pure/taverneamendment.

**Take-down policy**If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Downloaded from the University of Groningen/UMCG research database (Pure): http://www.rug.nl/research/portal. For technical reasons the number of authors shown on this cover page is limited to 10 maximum.

Download date: 05-06-2022

# Analytical calculation of Sobol sensitivity indices for Gaussian Processes with a squared exponential covariance function

# Notation and modeling assumptions

- Column vector of random inputs:  $\mathbf{X} = [X_1...X_d]^T \in \mathbb{R}^d, \ \mathbf{X}' = [X_1'...X_d']^T \in \mathbb{R}^d,$
- Column subvector of **X** without  $X_s$  element:  $\mathbf{X}_{-s} = [X_1 \dots X_{s-1} \ X_{s+1} \dots X_d]^T \in \mathbb{R}^{d-1}$
- Column vector consists of elements  $\mathbf{X}'_{-s}$  and  $X_s$ :  $\hat{\mathbf{X}} = [X'_1 \dots X_s \dots X'_d]^T \in \mathbb{R}^d$
- Random inputs  $X_s$ , s = 1, ..., d are mutually independent and each input follows a standard uniform distribution:  $X_s \sim \mathcal{U}(0, 1), \ s = 1, ..., d$
- Function F represents a black-box model of interest: Y = F(X), where Y is the model output
- Observed *n* training data points are denoted by  $\widetilde{X} = (\widetilde{\mathbf{x}}^{(1)}, \dots, \widetilde{\mathbf{x}}^{(n)})$
- Test  $n_*$  data points are denoted by  $X_* = (\mathbf{x}_*^{(1)}, \dots, \mathbf{x}_*^{(n_*)})$
- Vector of function F values at n training points  $\widetilde{X}$ :  $\widetilde{\mathbf{y}} = \left[\widetilde{y}^{(1)}, \dots, \widetilde{y}^{(n)}\right]^T$ ,  $\widetilde{y}^{(i)} = F\left(\widetilde{\mathbf{x}}^{(i)}\right)$ , i = 1, ..., n
- Gaussian process (GP) parametrization  $f(x) \sim \mathcal{GP}(0, k(\mathbf{x}, \mathbf{x}'))$

$$k(\mathbf{x}, \mathbf{x}') = \sigma_f^2 \prod_{j=1}^d \exp\left(-\frac{(x_j - x_j')^2}{2 l_j^2}\right) = * \left| h_j = \frac{1}{2} l_j^{-2} \right|$$
$$= \sigma_f^2 \prod_{j=1}^d \exp\left(-h_j (x_j - x_j')^2\right)$$
(1)

• Posterior GP distribution  $f_*|\widetilde{X},\widetilde{y},X_* \sim \mathcal{N}(m(X_*),\nu(X_*))$ , where

$$m(X_*) = K(X_*, \widetilde{X}) \left[ K(\widetilde{X}, \widetilde{X}) + \sigma^2 I \right]^{-1} \widetilde{\mathbf{y}}, \tag{2}$$

$$\nu(X_*) = K(X_*, X_*) - K(X_*, \widetilde{X}) \left[ K(\widetilde{X}, \widetilde{X}) + \sigma^2 I \right]^{-1} K(\widetilde{X}, X_*), \tag{3}$$

where the additive term  $\sigma^2 I$  reflects the fact that the function values are corrupted by additive noise with variance  $\sigma^2$ . Even if  $\sigma^2 = 0$  (as is the case when the function is exactly evaluated), a small noise term is typically inserted to regularize the inversion of the covariance matrix  $K(\widetilde{X}, \widetilde{X})$ .

- $K = K(\widetilde{X}, \widetilde{X})$
- $k_{pq}$  for p = 1, ..., n and q = 1, ..., n denotes the entries of the matrix  $\left[K + \sigma^2 I\right]^{-1}$
- $w_p, p = 1, ..., n$  are the elements of the vector  $\left[K + \sigma^2 I\right]^{-1} \widetilde{\mathbf{y}}$
- Expectations and variances with respect to the GP posterior distribution are denoted as  $\mathbb{E}_*$  and  $\mathbb{V}$ ar\*, respectively
- $erf(\cdot)$  denotes the error function.

#### Sobol indices

The estimate of the Sobol indices for the output Y with respect to the input  $X_s$ 

$$\hat{S}_{s} = \frac{\mathbb{E}_{*}\{\text{Var}\{E(Y|X_{s})\}\}}{\mathbb{E}_{*}\{\text{Var}(Y)\}}, \ s = 1, ..., d.$$
(4)

# **Inference for variance in numerator** $\mathbb{E}_*\{Var\{E(Y|X_s)\}\}$

Let us first calculate the numerator in the formula for estimates of Sobol indices (4).

$$\mathbb{E}_{*}\{\operatorname{Var}\{E(Y|X_{s})\}\} = \mathbb{E}_{*}\{E(E(Y|X_{s}))^{2}\} - \mathbb{E}_{*}\{E(Y)\}^{2} =$$

$$= \mathbb{E}_{*}\{E(E(Y|X_{s}))^{2}\} - \mathbb{V}\operatorname{ar}_{*}\{E(Y)\} - (\mathbb{E}_{*}\{E(Y)\})^{2} =$$

$$= I - II - III$$
(5)

# First component *I* from (5): $\mathbb{E}_{*}\{E(E(Y|X_s))^2\}$

We derive the formulas for every component of (5) separately. The first term I requires the computation of the following integrals:

$$\mathbb{E}_{*}\{E(E(Y|X_{s}))^{2}\} = E\left[\mathbb{V}\text{ar}_{*}\{E(Y|X_{s})\} + (\mathbb{E}_{*}\{E(Y|X_{s})\})^{2}\right] =$$

$$= \int_{0}^{1} \int_{[0,1]^{d-1}} \int_{[0,1]^{d-1}} v(\mathbf{x}, \hat{\mathbf{x}}) d\mathbf{x}_{-s} d\mathbf{x}'_{-s} dx_{s} + \int_{0}^{1} \int_{[0,1]^{d-1}} \int_{[0,1]^{d-1}} m_{*}(\mathbf{x}) m_{*}(\hat{\mathbf{x}}) d\mathbf{x}_{-s} d\mathbf{x}'_{-s} dx_{s} =$$

$$= L + M. \tag{6}$$

For the simplification we also provide the derivation of the formulas for the individual terms L and M in (6) separately.

$$L = \int_{0}^{1} \int_{[0,1]^{d-1}} \int_{[0,1]^{d-1}} v(\mathbf{x}, \hat{\mathbf{x}}) d\mathbf{x}_{-s} d\mathbf{x}'_{-s} dx_{s} \stackrel{3}{=}$$

$$= \int_{0}^{1} \int_{[0,1]^{d-1}} \int_{[0,1]^{d-1}} K(\mathbf{x}, \hat{\mathbf{x}}) d\mathbf{x}_{-s} d\mathbf{x}'_{-s} dx_{s} - \int_{0}^{1} \int_{[0,1]^{d-1}} \int_{[0,1]^{d-1}} K(\mathbf{x}, \tilde{\mathbf{X}}) \left(K + \sigma^{2}\right)^{-1} K(\tilde{\mathbf{X}}, \hat{\mathbf{x}}) d\mathbf{x}_{-s} d\mathbf{x}'_{-s} dx_{s} =$$

$$= \int_{0}^{1} Z_{-s}(\hat{\mathbf{x}}) dx_{s} - \int_{0}^{1} \left[ z_{-s}^{T}(\mathbf{x}) \left(K + \sigma^{2}\right)^{-1} z_{-s}(\hat{\mathbf{x}}) \right] dx_{s}$$

$$(7)$$

Now we divide the calculation of the integrals into several parts to make it easier to follow

$$z_{-s}(\mathbf{x}) = \int_{[0,1]^{d-1}} K(\mathbf{x}, \tilde{X}) d\mathbf{x}_{-s} \Big|_{0}^{1} = \sigma_{f}^{2} \exp\left(-h_{s}(x_{s} - \tilde{x}_{s})^{2}\right) \prod_{j=-s} \int_{0}^{1} \exp\left(-h_{j}(x_{j} - \tilde{x}_{j})^{2}\right) dx_{j} =$$

$$= \sigma_{f}^{2} \exp\left(-h_{s}(x_{s} - \tilde{x}_{s})^{2}\right) \prod_{j=-s} I_{j}$$
(8)

Next we evaluate the integral defined as  $I_i$  in (8)

$$I_{j} = \int_{0}^{1} \exp\left(-h_{j}(x_{j} - \tilde{x}_{j})^{2}\right) dx_{j} = * \left|a_{j} = \sqrt{h_{j}}(x_{j} - \tilde{x}_{j})\right| = \frac{1}{\sqrt{h_{j}}} \int_{-\sqrt{h_{j}}\tilde{x}_{j}}^{\sqrt{h_{j}}(1 - \tilde{x}_{j})} \exp\left(-a_{j}^{2}\right) da_{j} = \frac{\sqrt{\pi}}{2} \frac{1}{\sqrt{h_{j}}} \left(\operatorname{erf}\left(\sqrt{h_{j}}(1 - \tilde{x}_{j})\right) + \operatorname{erf}\left(\sqrt{h_{j}}\tilde{x}_{j}\right)\right) = \sqrt{\frac{\pi}{2}} l_{j} \left(\operatorname{erf}\left(\frac{1}{\sqrt{2}l_{j}}(1 - \tilde{x}_{j})\right) + \operatorname{erf}\left(\frac{1}{\sqrt{2}l_{j}}\tilde{x}_{j}\right)\right)$$

$$(9)$$

We can substitute the exact formula of  $I_j$  (9) into the final formula of  $z_{-s}$  in (8)

$$z_{-s}(\mathbf{x}) = \sigma_f^2 \exp\left(-\frac{1}{2l_s^2}(x_s - \tilde{x_s})^2\right) \prod_{j=-s} \sqrt{\frac{\pi}{2}} l_j \left(\operatorname{erf}\left(\frac{1}{\sqrt{2}l_j}(1 - \tilde{x_j})\right) + \operatorname{erf}\left(\frac{1}{\sqrt{2}l_j}\tilde{x_j}\right)\right)$$
(10)

Finally we calculate the first double integral in (7) which was marked as  $Z_{-s}$ 

$$Z_{-s} = \int_{[0,1]^{d-1}} \int_{[0,1]^{d-1}} K(\mathbf{x}, \hat{\mathbf{x}}) d\mathbf{x}_{-s} d\mathbf{x}'_{-s} = \sigma_f^2 \prod_{j=-s} \int_0^1 \left[ \int_0^1 \exp\left(-h_j(x_j - x'_j)^2\right) dx_j \right] dx'_j = \sigma_f^2 \prod_{j=-s} \int_0^1 I_j dx'_j = \sigma_f^2 \prod_{j=-s} \sqrt{\frac{\pi}{2}} I_j \int_0^1 \left( \operatorname{erf}\left(\frac{1}{\sqrt{2}I_j} (1 - x'_j)\right) + \operatorname{erf}\left(\frac{1}{\sqrt{2}I_j} x'_j\right) \right) dx'_j = \sigma_f^2 \prod_{j=-s} J_j$$
(11)

We present the exact analytic calculation of the  $J_i$  integral in (11)

$$J_{j} = \sqrt{\frac{\pi}{2}} l_{j} \left[ \int_{0}^{1} \operatorname{erf} \left( \frac{1}{\sqrt{2} l_{j}} (1 - x'_{j}) \right) dx'_{j} + \int_{0}^{1} \operatorname{erf} \left( \frac{1}{\sqrt{2} l_{j}} x'_{j} \right) dx'_{j} \right] =$$

$$= * \left| b_{j} = \frac{1}{\sqrt{2} l_{j}} (1 - x'_{j}), c_{j} = \frac{1}{\sqrt{2} l_{j}} x'_{j} \right| =$$

$$= \sqrt{\frac{\pi}{2}} l_{j} \left[ -\sqrt{2} l_{j} \int_{1/\sqrt{2} l_{j}}^{0} \operatorname{erf}(b_{j}) db_{j} + \sqrt{2} l_{j} \int_{0}^{1/\sqrt{2} l_{j}} \operatorname{erf}(c_{j}) dc_{j} \right] =$$

$$= 2 \sqrt{\pi} l_{j}^{2} \int_{0}^{1/\sqrt{2} l_{j}} \operatorname{erf}(t_{j}) dt_{j} =$$

$$= * \left| u = \operatorname{erf}(t_{j}), dv = dt_{j}, du = \frac{2}{\sqrt{\pi}} \exp(-t_{j}^{2}) dt_{j}, v = t_{j} \right| =$$

$$= 2 \sqrt{\pi} l_{j}^{2} \left[ \operatorname{erf}(t_{j}) t_{j} \Big|_{0}^{1/\sqrt{2} l_{j}} - \frac{2}{\sqrt{\pi}} \int_{0}^{1/\sqrt{2} l_{j}} \exp(-t_{j}^{2}) t_{j} dt_{j} \right] =$$

$$= 2 \sqrt{\pi} l_{j}^{2} \left[ \frac{1}{\sqrt{2} l_{j}} \operatorname{erf} \left( \frac{1}{\sqrt{2} l_{j}} \right) + \frac{1}{\sqrt{\pi}} \exp(-t_{j}^{2}) \Big|_{0}^{1/\sqrt{2} l_{j}} \right] =$$

$$= 2 \sqrt{\pi} l_{j}^{2} \left[ \frac{1}{\sqrt{2} l_{j}} \operatorname{erf} \left( \frac{1}{\sqrt{2} l_{j}} \right) + 2 l_{j}^{2} \left( \exp\left( -\frac{1}{2 l_{j}^{2}} \right) - 1 \right)$$

$$(12)$$

Then we can write down a closed form to compute  $Z_{-s}$  in (11)

$$Z_{-s} = \sigma_f^2 \prod_{j=-s} \left[ 2\sqrt{\frac{\pi}{2}} l_j \operatorname{erf}\left(\frac{1}{\sqrt{2}l_j}\right) + 2l_j^2 \left( \exp\left(-\frac{1}{2l_j^2}\right) - 1 \right) \right]$$
(13)

Finally, the analytic formula for L in (7) is simplified to the following form

$$L = \sigma_f^2 \prod_{j=-s} J_j - \sigma_f^4 \sum_{p=1}^n \sum_{q=1}^n \left[ k_{pq} \prod_{j=-s} I_j(\mathbf{x}_p) \prod_{j=-s} I_j(\mathbf{x}_q) \int_0^1 \exp\left(-h_s \left[ (x_s - \tilde{x}_s^p)^2 + (x_s - \tilde{x}_s^q)^2 \right] \right) dx_s \right] =$$

$$= \sigma_f^2 \prod_{j=-s} J_j - \sigma_f^4 \sum_{p=1}^n \sum_{q=1}^n \left[ k_{pq} \prod_{j=-s} I_j(\mathbf{x}_p) \prod_{j=-s} I_j(\mathbf{x}_q) R_{pqs} \right]$$
(14)

The derivation of the integral  $R_{pqs}$  is presented separately:

$$R_{pqs} = \int_{0}^{1} \exp\left(-h_{s}\left[(x_{s} - \tilde{x}_{s}^{p})^{2} + (x_{s} - \tilde{x}_{s}^{q})^{2}\right]\right) dx_{s} =$$

$$= * \left|a^{2} + b^{2} = \frac{1}{2}\left[(a + b)^{2} + (a - b)^{2}\right]\right| =$$

$$= \exp\left[-\frac{h_{s}}{2}\left(\tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right)^{2}\right] \int_{0}^{1} \exp\left[-\frac{h_{s}}{2}\left(2x_{s} - \tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right)^{2}\right] dx_{s} =$$

$$= * \left|g_{s} = \sqrt{\frac{h_{s}}{2}}\left(2x_{s} - \tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right), dg_{s} = \sqrt{2h_{s}}dx_{s}, g_{s}(0) = -\sqrt{\frac{h_{s}}{2}}\left(\tilde{x}_{s}^{p} + \tilde{x}_{s}^{q}\right), g_{s}(1) = \sqrt{\frac{h_{s}}{2}}\left(2 - \tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right)\right| =$$

$$= \exp\left[-\frac{h_{s}}{2}\left(\tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right)^{2}\right] \frac{1}{\sqrt{2h_{s}}} \int_{g_{s}(0)}^{g_{s}(1)} \exp\left(-g_{s}^{2}\right) dg_{s} =$$

$$= \exp\left[-\frac{h_{s}}{2}\left(\tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right)^{2}\right] \frac{1}{\sqrt{2h_{s}}} \frac{\sqrt{\pi}}{2} \left(\operatorname{erf}\left[g_{s}(1)\right] - \operatorname{erf}\left[g_{s}(0)\right]\right) =$$

$$= \frac{\sqrt{\pi}}{2} l_{s} \exp\left[-\frac{1}{4l^{2}}\left(\tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right)^{2}\right] \left(\operatorname{erf}\left[\frac{1}{2l_{s}}\left(2 - \tilde{x}_{s}^{p} - \tilde{x}_{s}^{q}\right)\right] + \operatorname{erf}\left[\frac{1}{2l_{s}}\left(\tilde{x}_{s}^{p} + \tilde{x}_{s}^{q}\right)\right]\right)$$

$$(15)$$

This concludes the evaluation of the integral L in (14) with the exact analytic form for the components  $I_j(\mathbf{x})$  in (9),  $J_j$  in (12) and  $R_{pqs}$  in (15).

On the next step to finalize the calculation of (6), we evaluate the second part M in the equation.

$$M = \int_{0}^{1} \int_{[0,1]^{d-1}} \int_{[0,1]^{d-1}} m_{*}(\mathbf{x}) m_{*}(\hat{\mathbf{x}}) d\mathbf{x}_{-s} d\mathbf{x}'_{-s} dx_{s} =$$

$$= \int_{0}^{1} \left[ z_{-s}^{T}(\mathbf{x}) \left( K + \sigma^{2} \right)^{-1} \widetilde{\mathbf{y}} z_{-s}^{T}(\hat{\mathbf{x}}) \left( K + \sigma^{2} \right)^{-1} \widetilde{\mathbf{y}} \right] dx_{s} =$$

$$= \sigma_{f}^{4} \sum_{p=1}^{n} \sum_{q=1}^{n} \left[ w_{p} w_{q} \prod_{j=-s}^{n} I_{j}(\mathbf{x}_{p}) \prod_{j=-s}^{1} I_{j}(\mathbf{x}_{q}) \int_{0}^{1} \exp\left(-h_{s} \left[ (x_{s} - \widetilde{x}_{s}^{p})^{2} + (x_{s} - \widetilde{x}_{s}^{q})^{2} \right] \right) dx_{s} \right] =$$

$$= \sigma_{f}^{4} \sum_{p=1}^{n} \sum_{q=1}^{n} \left[ w_{p} w_{q} \prod_{j=-s}^{1} I_{j}(\mathbf{x}_{p}) \prod_{j=-s}^{1} I_{j}(\mathbf{x}_{q}) R_{pqs} \right]$$

$$(16)$$

## Second component II from (5): $Var_*\{E(Y)\}$

Let us return to the equation in (5) and focus on the second term II

$$\mathbb{V}\text{ar}_{*}\{E(Y)\} = \int_{[0,1]^{d}} \int_{[0,1]^{d}} k_{*}(\mathbf{x}, \mathbf{x}') \, d\mathbf{x} d\mathbf{x}' = 
= \int_{[0,1]^{d}} \int_{[0,1]^{d}} K(\mathbf{x}, \mathbf{x}') d\mathbf{x} d\mathbf{x}' - \int_{[0,1]^{d}} \int_{[0,1]^{d}} K(\mathbf{x}, \tilde{X}) \left(K + \sigma^{2}\right)^{-1} K(\tilde{X}, \mathbf{x}') \, d\mathbf{x} d\mathbf{x}' = 
= Z - z^{T} \left(K + \sigma^{2}\right)^{-1} z$$
(17)

Again we recast the calculation in more simple steps and use the formulas that was presented previously. For instance, the computation of the integral z in (17) is reduced to the evaluation of  $I_j$  from the equation (9).

$$z(\mathbf{x}) = \int_{[0,1]^d} K(\mathbf{x}, \tilde{X}) d\mathbf{x} = \sigma_f^2 \prod_{j=1}^d I_j(\mathbf{x})$$
(18)

Analogously, to compute Z we address to the integral  $J_i$  that was calculated in (12)

$$Z = \int_{[0,1]^d} \int_{[0,1]^d} K(\mathbf{x}, \mathbf{x}') d\mathbf{x} d\mathbf{x}' = \sigma_f^2 \prod_{j=1}^d J_j$$
(19)

#### Third component *III* from (5): $\mathbb{E}_*\{E(Y)\}$

We address now to the calculation of the final third component in (5).

$$\mathbb{E}_{*}\{E(Y)\} = \left[\int_{[0,1]^d} K(\mathbf{x}, \widetilde{X}) d\mathbf{x}\right] \left[K + \sigma^2 I\right]^{-1} \widetilde{\mathbf{y}} = z^T \left(K(\widetilde{X}, \widetilde{X}) + \sigma^2\right)^{-1} \widetilde{\mathbf{y}} \stackrel{(18)}{=} \sigma_f^2 \prod_{j=1}^d I_j \left(K(\widetilde{X}, \widetilde{X}) + \sigma^2\right)^{-1} \widetilde{\mathbf{y}}$$
(20)

This derivation finalize the computation of the numerator from the formula (4), all three components, *I*, *II* and *III*, from (5) have been derived in analytic form.

### Inference for variance in denominator $\mathbb{E}_*\{Var(Y)\}$

The final step in the calculation of the estimate for the Sobol indices is the derivation of the analytic formula for the denominator in (4).

$$\mathbb{E}_{*}\{\operatorname{var}(Y)\} = \mathbb{E}_{*}\{E(Y^{2})\} - \mathbb{E}_{*}\{E(Y)\}^{2} = E\{\mathbb{E}_{*}(Y^{2})\} - \left(\mathbb{V}\operatorname{ar}_{*}\{E(Y)\} + (\mathbb{E}_{*}\{E(Y)\})^{2}\right) = E\left(\mathbb{V}\operatorname{ar}_{*}\{Y\} + \{\mathbb{E}_{*}(Y)\}^{2}\right) - \left(\mathbb{V}\operatorname{ar}_{*}\{E(Y)\} + (\mathbb{E}_{*}\{E(Y)\})^{2}\right) = IV - II - III$$
(21)

Similar to the previous routine for the numerator in (4), we divide the calculations in several steps. There are three components II, III and IV in (21), where II is summarized by formulas (17), (18) and (19), while III can be calculated using (20). The derivation of the fourth component IV is presented in the next section.

# Fourth component *IV* from (21): $\mathbb{E}_*\{E(Y)\}$

Here we perform the last calculation of the fourth component in (21).

$$E\{\mathbb{V}\mathrm{ar}_{*}\{Y\}\} + E\{\mathbb{E}_{*}(Y)\}^{2} = \int_{[0,1]^{d}} K(\mathbf{x}, \mathbf{x}) d\mathbf{x} - \int_{[0,1]^{d}} K(\mathbf{x}, \tilde{X}) \left[K + \sigma^{2} \mathbb{I}\right]^{-1} K(\tilde{X}, \mathbf{x}) d\mathbf{x} + \int_{[0,1]^{d}} \left[K(\mathbf{x}, \tilde{X}) \left(K + \sigma^{2}\right)^{-1} \widetilde{\mathbf{y}} K(\mathbf{x}, \tilde{X}) \left[K + \sigma^{2} \mathbb{I}\right]^{-1} \widetilde{\mathbf{y}} d\mathbf{x}\right] =$$

$$= \sigma_{f}^{2} - \sigma_{f}^{4} \sum_{p=1}^{n} \sum_{q=1}^{n} \left[k_{pq} \prod_{s=1}^{d} R_{pqs}\right] + \sigma_{f}^{4} \sum_{p=1}^{n} \sum_{q=1}^{n} \left[w_{p} w_{q} \prod_{s=1}^{d} R_{pqs}\right], \qquad (22)$$

where the derivation for  $R_{pqs}$  is shown in (15).

### Final formulas for Sobol indices

Here we present the final formulas for Sobol indices' estimates  $\hat{S}_s$  defined as:

$$\hat{S}_{s} = \frac{\mathbb{E}_{*}\{\text{Var}\{E(Y|X_{s})\}\}}{\mathbb{E}_{*}\{\text{Var}(Y)\}}, \ s = 1, ..., d.$$
(4)

We start with the analytic expression for the numerator  $\mathbb{E}_*\{Var\{E(Y|X_s)\}\}\)$  in 4.

$$\mathbb{E}_{*}\{\operatorname{Var}\{E(Y|X_{S})\}\} = \mathbb{E}_{*}\{E(E(Y|X_{S}))^{2}\} - \mathbb{V}\operatorname{ar}_{*}\{E(Y)\} - (\mathbb{E}_{*}\{E(Y)\})^{2} = I - II - III.$$
 (5)

For the first term *I* in 5, we get

$$I: \left| \mathbb{E}_* \{ E(E(Y|X_s))^2 \} = \sigma_f^2 \prod_{j=-s} J_j - \sigma_f^4 \sum_{p=1}^n \sum_{q=1}^n \left[ (k_{pq} - w_p \, w_q) R_{pqs} \prod_{j=-s} I_j \left( \tilde{\mathbf{x}}^{(p)} \right) I_j \left( \tilde{\mathbf{x}}^{(q)} \right) \right].$$

where

$$J_{j} = 2 l_{j} \left[ \sqrt{\frac{\pi}{2}} \operatorname{erf} \left( \frac{1}{\sqrt{2} l_{j}} \right) + l_{j} \left( \exp \left( -\frac{1}{2 l_{j}^{2}} \right) - 1 \right) \right],$$

$$R_{pqs} = \frac{\sqrt{\pi}}{2} l_s \exp\left(-\frac{1}{4l_s^2} \left(\tilde{x}_s^{(p)} - \tilde{x}_s^{(q)}\right)^2\right) \left(\operatorname{erf}\left[\frac{1}{2l_s} \left(2 - \tilde{x}_s^{(p)} - \tilde{x}_s^{(q)}\right)\right] + \operatorname{erf}\left[\frac{1}{2l_s} \left(\tilde{x}_s^{(p)} + \tilde{x}_s^{(q)}\right)\right]\right),$$

and

$$I_{j}\left(\tilde{\mathbf{x}}^{(p)}\right) = \sqrt{\frac{\pi}{2}} l_{j} \left[ \operatorname{erf}\left(\frac{1}{\sqrt{2}l_{j}} \left(1 - \tilde{x}_{j}^{(p)}\right)\right) + \operatorname{erf}\left(\frac{1}{\sqrt{2}l_{j}} \tilde{x}_{j}^{(p)}\right) \right].$$

The second term II in 5 can then be written as

$$II: \boxed{\mathbb{V}\mathrm{ar}_*\{E(Y)\} = \sigma_f^2 \prod_{j=1}^d J_j - \sigma_f^4 \left[ \prod_{j=1}^d I_j(\widetilde{X}) \right]' \left[ K + \sigma_f^2 I \right]^{-1} \left[ \prod_{j=1}^d I_j(\widetilde{X}) \right]}.$$

Finally, for the third III term of 5 we get

$$III: \left(\mathbb{E}_*\{E(Y)\}\right)^2 = \left(\sigma_f^2 \prod_{j=1}^d I_j \left(K(\tilde{X}, \tilde{X}) + \sigma^2\right)^{-1} \widetilde{\mathbf{y}}\right)^2$$

The expression for the denominator  $\mathbb{E}_{*}\{Var(Y)\}\$  of 4 has the following form:

$$\mathbb{E}_{*}\{\operatorname{Var}(Y)\} = \mathbb{E}_{*}\{E(Y^{2})\} - \mathbb{V}\operatorname{ar}_{*}\{E(Y)\} - (\mathbb{E}_{*}\{E(Y)\})^{2} = IV - II - III.$$
 (21)

As we can see, the formula 21 contains one further term compared to the expression of the numerator 5, which is given by

$$IV: \left| \mathbb{E}_* \{ E(Y^2) \} = \sigma_f^2 - \sigma_f^4 \sum_{p=1}^n \sum_{q=1}^n \left[ k_{pq} \prod_{s=1}^d R_{pqs} \right] + \sigma_f^4 \sum_{p=1}^n \sum_{q=1}^n \left[ w_p \ w_q \prod_{s=1}^d R_{pqs} \right].$$