

Some distance properties of tailbiting codes

Handlery, Marc; Höst, Stefan; Johannesson, Rolf; Zyablov, Viktor V.

Published in:

[Host publication title missing]

DOI:

10.1109/ISIT.2001.936153

2001

Link to publication

Citation for published version (APA):

Handlery, M., Höst, S., Johannessón, R., & Zyablov, V. V. (2001). Some distance properties of tailbiting codes. In [Host publication title missing] (pp. 290) https://doi.org/10.1109/ISIT.2001.936153

Total number of authors:

General rights

Unless other specific re-use rights are stated the following general rights apply:

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.

 • You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

Read more about Creative commons licenses: https://creativecommons.org/licenses/

Take down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

Some Distance Properties of Tailbiting Codes¹

Marc Handlery, Stefan Höst, Rolf Johannesson
Department of Information Technology
Lund University, Box 118
S-221 00 Lund, Sweden
e-mail: {marc,stefanh,rolf}@it.lth.se

Abstract — The active tailbiting segment distance for convolutional codes is introduced. Together with the earlier defined active burst distance, it describes the error correcting capability of a tailbiting code encoded by a convolutional encoder. Lower bounds on the new active distance as well as an upper bound on the ratio between tailbiting length and memory of encoder such that its minimum distance d_{\min} equals the free distance d_{free} of the corresponding convolutional code are presented.

I. Introduction

Tailbiting codes can be obtained by terminating rate R=b/c convolutional codes into block codes of length l c-tuples [1]. For simplicity, we consider only binary codes. The error correcting capability of a block code is estimated via d_{\min} . There is no description which error patterns with more than $\lfloor \frac{d_{\min}-1}{2} \rfloor$ errors can be corrected. In order to describe the error correcting capability of a tailbiting code beyond the minimum distance argument, we define the active tailbiting segment distance a_j^{tbs} . We also give an upper bound on the length of a tailbiting code so that d_{\min} equals d_{free} of the corresponding convolutional code. This is useful when analyzing concatenated coding schemes containing tailbiting encoders.

II. The Active Tailbiting Segment Distance Consider the convolutional code $\mathcal C$ encoded by a rate R=b/c encoder. The binary matrix σ_t denotes the encoder state at time t. Let $\mathcal S^{\sigma_s,\sigma_e}_{[t_1,t_2]}$, $0 \leq t_1 < t_2$, be the set of state sequences $\sigma_{[t_1,t_2]} = \sigma_{t_1} \dots \sigma_{t_2}$ that start in state σ_s and terminate in state σ_e , and do not have two consecutive zero states with zero input in between. Let j_b be the smallest positive integer such that $\mathcal S^{0,0}_{[0,j_b+1]} \neq \emptyset$. The jth order active burst distance [2] is $a_j^b \triangleq \min_{\mathcal S^{0,0}_{[0,j+1]}} \left\{ w_H \left(v_{[0,j]} \right) \right\}$, $j \geq j_b$. For any code $\mathcal C$, a_j^b is invariant over the set of its canonical encoders [2]. It is lower-bounded by a linearly increasing function $a_j^b \geq \alpha j + \beta^b$, $j \geq j_b$, where α is the asymptotic slope, and β^b is chosen as large as possible. Let j_r be the smallest number of steps that, starting in the allzero state, take us to any reachable state.

Definition 1 The jth order active tailbiting segment distance is $a_j^{tbs} \triangleq \min_{\mathcal{S}_{[j_r,j_r+j+1]}^{\sigma,\sigma}} \left\{ w_{\mathrm{H}} \left(\boldsymbol{v}_{[j_r,j_r+j]} \right) \right\}$, where $\boldsymbol{\sigma}$ denotes any possible encoder state.

Theorem 1 The active tailbiting segment distance is lower-bounded by $a_i^{tb} \ge \alpha(j+1)$, for all $j \ge 0$.

Victor V. Zyablov
Inst. for Problems of Information Transm.
Russian Academy of Science
Moscow, Russia
e-mail: zyablov@iitp.ru

III. PROPERTIES OF TAILBITING CODES VIA THE ACTIVE DISTANCES

We define an *incorrect path* at the receiver to be any trellis path differing from the *transmitted path*. For any $k_1, k_2 < l$, let $e_{[k_1,k_2]}$ denote the Hamming weight of the error pattern $e_{[k_1,k_2]} = e_{k_1}e_{k_1+1}\dots e_{k_2}$, where e_i , $0 \le i < l$, are c-tuples and all indices are evaluated modulo l. Then, we have

Theorem 2 Consider a tailbiting code \mathcal{C}^{tb} of length l c-tuples encoded by a convolutional encoder. Then, for $j_b < l$, a maximum likelihood (ML) decoder corrects all error patterns $e_{[0,l-1]}$ that satisfy $e_{[t,\ t+j\ \mathrm{mod}\ l]} < \min\left\{a_j^b/2,\ a_{l-1}^{tbs}/2\right\}$ for $0 \le t < l$, $j_b \le j < l$. For $j_b \ge l$, all error patterns that satisfy $e_{[0,l-1]} < a_{l-1}^{tbs}/2$ are corrected.

Example 1 A tailbiting code of length l=18 2-tuples encoded by $G(D)=(1+D+D^2-1+D^2)$ with $d_{\min}=5$ is used on a binary symmetric channel. From Theorem 2 follows that

Consider a tailbiting code of length l c-tuples with minimum distance d_{\min} . The free tailbiting length l_{free} is the shortest length l for which d_{\min} will remain equal to d_{free} of the corresponding convolutional code for all tailbiting lengths greater than or equal to l_{free} . The free tailbiting length is upper-bounded by $l_{\text{free}} \leq \lfloor d_{\text{free}}/\alpha \rfloor$.

IV. Ensemble Properties of the Active Tailbiting Segment Distance

The concept of the active distances can be generalized to timevarying convolutional encoders.

Theorem 3 There exists a rate R = b/c convolutional code \mathcal{C} encoded by a time-varying encoder of memory m such that $a_j^{tb} > \rho(j+1)c + O(\log m), \quad for \ j = O(m) \geq j_o \quad m \to \infty$

where $\rho = h^{-1}(1-R)$ is the Gilbert-Varshamov parameter, h() is the binary entropy function, and j_o is the smallest integer satisfying $(1-R)(j+1)c \geq 4\log m$.

Using the Heller asymptotic bound we obtain

Theorem 4 There exists a tailbiting code C^{tb} encoded by a time-varying encoder of memory m, such that $\lim_{m\to\infty} l_{\text{free}}/m \leq \frac{1}{2\rho}$.

REFERENCES

- G. Solomon and H. C. A. van Tilborg, "A connection between block and convolutional codes," SIAM J. Appl. Math., vol. 37, 1979
- [2] S. Höst, R. Johannesson, and V. V. Zyablov, "Active distances for convolutional codes", *IEEE Trans. Inform. Theory*, vol. 44, Mar. 1999.

'n

¹This research was supported in part by the Swedish Academy of Science in cooperation with the Russian Academy of Sciences and in part by the Swedish Research Council for Engineering Sciences under Grant 97-723 and 98-501.