General Disclaimer

One or more of the Following Statements may affect this Document

- This document has been reproduced from the best copy furnished by the organizational source. It is being released in the interest of making available as much information as possible.

- This document may contain data, which exceeds the sheet parameters. It was furnished in this condition by the organizational source and is the best copy available.

- This document may contain tone-on-tone or color graphs, charts and/or pictures, which have been reproduced in black and white.

- This document is paginated as submitted by the original source.

- Portions of this document are not fully legible due to the historical nature of some of the material. However, it is the best reproduction available from the original submission.

Produced by the NASA Center for Aerospace Information (CASI)

SCHOOL OF ENGINEERING
OLD DOMINION UNIVERSITY
NORFOLK, VIRGINIA

Technical Report 75-T10

ANALYTICAL SIMULATION OF THE FAR-FIELD JET NOISE AND THE UNSTEADY JET FLOW-FIELD BY A MODEL OF PERIODIC SHEDDING OF VORTEX RING FROM THE JET EXIT

By

Chen-Huei Liu

Final Technical Report

Summary of Research

In recent studies of turbulent flow fields, successful results have
been obtained by the introduction of appropriate phys... model and the
simulation of the turbulent flow is reduced to the de... ination of few
parameters. In several experimental investigations on turbulent free jets,
flow field resembling that of vortex rings have been reported. It
is therefore of interest to construct the theoretical flow field due to
shedding of vortex rings, to identify the controlling parameters and to
find out whether the theoretical model can successfully simulate the un-
steady pressure field near jet and consequently the far field noise.

The basic parameters contained in the analytic solutions are the
epoch at which a vortex ring is shed near the jet exit and the eddy
viscosity coefficient. These parameters can be identified from the ex-
perimental data for the real-time pressure and from the spread of the
mixing layer of jet. Also the function controlling the rolling up of
the vortex sheet to a ring will be adjusted to fit the steep unsteady
pressure variation in the experimental data as the vortex ring passing
over each station. The essential details of the theoretical investi-
gation are presented in reference 1. The results of the theoretical
analysis show good qualitative agreement with the experimental data.

In paper 1, the near field pressure fluctuation induced by a tur-
bulent shear layer around a jet has been simulated by shedding of
circular vortex rings immersed in a uniform stream. In order to enforce
the enlargement of the vortex ring as the shear layer spreads, one
can replace the uniform stream by a steady flow of a point source with

its mass flux inside the angle of the spreading shear layer matched with the mass flux of the jet. Thus a steady radial flow component from the axis of the jet is created. Unfortunately, the steady flow velocity of a point source decreases as the inverse square power of the distance and the decrease is too fast as compared with the experimental data. To create a steady flow field which will expand the radii of the vortex rings and with a steady velocity which will not decrease so fast as point source, a linear source distribution along a circle of radius R, say the radius of the jet, located near the jet exit will be introduced. The velocity potential due to this ring source can be written as

$$\phi(r,x) = -\frac{mR}{\pi} [x^2+(r+R)^2]^{-1/2} F(\Lambda)$$

with $\Lambda = \{4rR/[x^2+(r+R)^2]\}^{1/2}$. The linear intensity m can be related to the mass flux of the jet by the equation

$$m = 2Q/(\pi R) .$$

The corresponding steady velocity components are

$$\phi_x = \frac{mRx}{2\pi} [x^2+(r-R)^2]^{-1} [x^2+(r+R)^2]^{-1/2} E(\Lambda)$$

and

$$\phi_r = -\phi/(2r) - \frac{x^2+R^2-r^2}{2r} [\phi_x/x] .$$

In the analysis of the noise propagation from the real time pressure variation in the near field to far field, it was confirmed that there

exists a layer where the Laplace equation holds. The purpose of this intermediate potential layer is to filter out the components of short wave lengths in the near field data. However, this objective can be realized by examining directly the solution of the simple wave equation and discarding components which decay exponentially with respect to the radial distance from the axis of the jet.

For a periodic solution of the wave equation

$$\frac{1}{c^2} \phi_{tt} - \Delta\phi = 0$$

With axial wave length ℓ and circumferential wave number n, it can be written as

$$e^{i(\omega t - 2\pi x/\ell + n\theta)} R(r)$$

where R(r) obeys the Bessel equation

$$r^2 R'' + rR' + (\mu r^2 - n^2)R = 0$$

with $\mu^2 = (\omega/c)^2 - (2\pi/\ell)^2$.

The solution decays exponentially with respect to r when $\mu < 0$. That is for a given ω, the Fourier components of the near field data with short wave length ℓ such that

$$\ell < \frac{2\pi c}{\omega}$$

can be discarded in the study of the propagation to far field.

Publications and Papers Resulting from Research

1. "Simulation by Vortex Rings of the Unsteady Pressure Field Near a Jet," with L. Maestrello and M. D. Gunzburger. AIAA Paper No. 75-438, AIAA Second Aeroacoustics Specialists Conference, March 24-26, 1975, Hampton, VA. To appear in the Proceedings of the 2nd AIAA Aeroacoustics Conference, Vol I - Jet, Combustion and Engine Core Noise.

2. "Scattering of Coherent Sound Waves by Atmospheric Turbulence," with P. L. Chow and L. Maestrello. AIAA Paper No. 75-545, AIAA Second Aeroacoustics Specialists Conference, March 24-26, 1975, Hampton, VA.

3. "Numerical Study of Sound Progation in a Jet Flow," with S. L. Padula. To appear as NASA TN D-8012.